

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
19 May 2011 (19.05.2011)

(10) International Publication Number
WO 2011/060145 A1

- (51) International Patent Classification: **G01R 13/00** (2006.01) 21409 (US). **SLAY, Frederick, M.** [US/US]; 22 Gregorie Neck, Okatie, SC 29909 (US).
- (21) International Application Number: PCT/US2010/056352 (74) Agent: **PALAN, Perry**; Barnes & Thornburg LLP, 750 17th Street NW, Suite 900, Washington, DC 20006 (US).
- (22) International Filing Date: 11 November 2010 (11.11.2010) (81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PE, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data: PCT/US2009/064120 12 November 2009 (12.11.2009) US 61/379,100 1 September 2010 (01.09.2010) US
- (71) Applicant (for all designated States except US): **PAUL REED SMITH GUITARS LIMITED PARTNERSHIP** [US/US]; 380 Log Canoe Circle, Stevensville, MD 21666 (US) (84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK,
- (72) Inventor: **SMITH, Jack, W.** (deceased).
- (72) Inventors; and
- (75) Inventors/Applicants (for US only): **SMITH, Paul, Reed** [US/US]; 394 Forest Beach Road, Annapolis, MD

[Continued on next page]

(54) Title: A PRECISION MEASUREMENT OF WAVEFORMS USING DECONVOLUTION AND WINDOWING

| | | ← Frequency Bin → | | | | | | |
|--|-----|-------------------|-------|-------|-------|-------|-------|-------|
| | | 609.4 | 625.0 | 640.6 | 656.3 | 671.9 | 687.5 | |
| Time Slice | ↑ | 157 | -74.7 | -77.6 | -74.3 | -60.9 | -50.0 | -46.1 |
| | 158 | -78.3 | -78.8 | -72.3 | -57.4 | -48.6 | -47.7 | |
| | 159 | -74.5 | -84.0 | -71.3 | -54.8 | -42.0 | -52.1 | |
| | 160 | -71.2 | -72.7 | -68.7 | -52.9 | -49.9 | -61.4 | |
| | 161 | -75.6 | -66.6 | -61.9 | -52.0 | -52.6 | -59.9 | |
| | 162 | -79.7 | -64.9 | -57.7 | -52.9 | -55.4 | -61.6 | |
| | 163 | -82.4 | -63.5 | -56.8 | -55.5 | -58.6 | -73.7 | |
| ↓ <td style="text-align: center;">164</td> <td style="text-align: center;">-72.2</td> <td style="text-align: center;">-61.2</td> <td style="text-align: center;">-59.3</td> <td style="text-align: center;">-60.4</td> <td style="text-align: center;">-61.7</td> <td style="text-align: center;">-67.9</td> | 164 | -72.2 | -61.2 | -59.3 | -60.4 | -61.7 | -67.9 | |

(57) Abstract: The invention consists of new ways of constructing a Measuring Matrices (MMs) including time deconvolution of Digital Fourier Transforms DFTs. Also, windowing functions specifically designed to facilitate time deconvolution may be used, and/or the DFTs may be performed in specific non-periodic ways to reduce artifacts and further facilitate deconvolution. These deconvolved DFTs may be used alone or correlated with other DFTs to produce a MM.

FIG. 2

WO 2011/060145 A1

SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG). **Published:**

— with international search report (Art. 21(3))

A PRECISION MEASUREMENT OF WAVEFORMS USING DECONVOLUTION AND WINDOWING

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] The present application claims the benefit of priority to U.S. Application Serial No. 61/379100, filed September 1, 2010, and PCT Patent Application No. PCT/US2009/064120 filed November 12, 2009, the contents of which are incorporated herein by reference in their entirety.

Field of the Invention

[0002] The invention relates to the time-frequency-amplitude analysis and measurement of waveforms and compound waveforms. Note that the word “signal” is a popular synonym for the more general “waveform” and both may be used interchangeably here. A compound waveform consists of multiple waveforms (or signals) mixed together. While most of this document refers to the audio frequency range, a waveform for the purposes of this invention is not limited to any particular frequency range or complexity. Any technology which measures waveforms/signals as part of its process may be assisted by this machine and process.

Background of the Invention

[0003] Given a compound waveform, it is desirable to accurately measure the waveform and its components, which may have been spawned by several sources. This is difficult when the waveform includes signals produced by different sources overlapping in time and frequency, low energy signals eclipsed by higher energy signals, rapid changes in frequency, and/or rapid changes in amplitude. If these waveforms could be more accurately measured and analyzed, it would greatly increase our ability to understand what these waveforms contain and how to separate and/or modify them.

[0004] Analysis of waveforms is traditionally accomplished in the time and frequency domains. Typically, these waveforms are first captured digitally as amplitude samples in time, then a series of transforms are used to measure the signals and the result is displayed in a time, frequency and amplitude matrix. A variety of techniques have been developed to extract time/frequency/amplitude information from the time-series data. However, representing how the

frequency and amplitude change with respect to time can be challenging, particularly when there are abrupt frequency and/or amplitude changes, or signals from multiple sources occupy the same time and frequency regions.

[0005] One common transform for obtaining time, frequency, and amplitude information is the Discrete Fourier Transform (DFT). Unfortunately, there is a tradeoff between frequency and time resolutions resulting from the size (dimension) of the DFT. The time window inspected by a DFT is proportional to its dimension. Thus, a large dimension DFT inspects a larger time window than a small dimension DFT. This larger time window makes a large dimension DFT slow to react to dynamic changes.

[0006] Conversely, a large dimension DFT slices up the frequency range into finer segments. The maximum frequency measured by the DFT is half the sampling rate of the digitized signal. A DFT of dimension X divides the frequency range from 0 to the max into $X/2$ equal sized "bins." Thus, the size of each frequency bin in a DFT is equal to two times the sampling rate divided by its dimension.

[0007] So, higher dimension DFTs have higher frequency resolution but lower time resolution. Lower dimension DFTs have higher time resolution but lower frequency resolution. Because of this tradeoff, practitioners have sought modified DFTs or other alternative methods to accurately represent dynamic, time-varying waveforms with good resolution in both time and frequency. The Precision Measuring Matrix (PMM) (US Patent application No. PCT/US2009/064120) is just such a method. This invention extends the PMM method.

[0008] Fast Fourier Transforms (FFTs) are typically used to perform convolutions and deconvolutions. The Convolution Theorem states that under suitable conditions the Fourier transform of a convolution or two functions is the pointwise product of the Fourier transforms of the functions. It is usually simpler (and faster) to transform two functions, multiply them, and transform back than to perform a brute force convolution. More to the point, it is dramatically simpler and faster to use the convolution theorem when deconvolving. Brute force deconvolution involves solving N equations in N unknowns. Transforming the two functions, dividing, and transforming back is much easier. Brute force deconvolution is not only computationally daunting, it can be impossible. When deconvolving a series of numbers, the result is often unstable. Thus, deconvolution is, in practice, virtually always done using transforms.

[0009] The inventors have been issued several patents, which are hereby incorporated by reference. They are: Fast Find Fundamental Method, U.S. Patent No. 6,766,288 B1; Method of Modifying Harmonic Content of a Complex Waveform, U.S. Patent No. 7,003,120 B1; and Method of Signal Shredding, U.S. Patent No. 6,798,886 B1. Application No. PCT/US2009/064120 filed November 12, 2009 is also hereby incorporated by reference.

SUMMARY

[00010] Embodiments of the invention provide a machine-implemented method for digital signal processing, comprising: obtaining a digital signal from conversion of an analog signal or from data storage; constructing MMs (as per Patent Application No. PCT/US2009/064120) comprised of cells containing the amplitudes for particular times and frequencies with marked correlated maxima.

[00011] In accordance with the disclosed embodiments, a new way of constructing MMs is provided which utilizes time deconvolution of FFTs and the use of windowing functions specifically designed to facilitate time deconvolution. FFTs may be performed in non-periodic ways to reduce artifacts and further facilitate deconvolution. These deconvolved FFTs may be used alone as a MM or may be correlated with other FFTs (either deconvolved or not) to produce a PMM.

BRIEF DESCRIPTION OF THE DRAWINGS

[00012] Figure 1 shows a schematic diagram for forming a PMM according to an exemplary embodiment of the invention.

[00013] Figure 2 shows a view of an example measuring matrix with simple maxima marked according to an exemplary embodiment of the invention.

[00014] Figure 3 illustrates an exemplary embodiment of one potential implementation of the invention.

[00015] Figure 4 shows a schematic diagram for forming a Measuring Matrix according to an exemplary embodiment of the invention.

[00016] As explained above, disclosed embodiments provide new ways of identifying related cells in PMMs constructed based on an obtained digital signal. As explained in Application No. PCT/US2009/064120, PMMs are comprised of cells containing the amplitudes

for particular times and frequencies with marked correlated maxima. Identifying related cells using domain relationships of the maxima and partial chains of maxima in the PMMs enables one to identify and separate sound sources within a complex compound waveform. Thus, new ways of identifying related cells in PMMs have significant utility and practical applications.

[00017] Preliminary to an in depth discussion of the disclosed embodiments, it should be understood that, broadly speaking, PMMs are constructed by performing a plurality of FFTs (or their equivalent) on to generate Measuring Matrices (MMs), which are matrices of cells representing the spectral amplitude of a digital signal to be analyzed. Thus, each FFT creates, for a particular time slice, a row or column of cells (one cell for each frequency bin).

[00018] A PMM is a matrix of time, frequency and amplitude events generated from the MM with correlated maxima marked as described in Patent Application No. PCT/US2009/064120. It should be appreciated that, where necessary, the generated MMs may be stretched to provide overlap to ensure that there is appropriate coverage throughout the PMM as explained that patent application.

[00019] In accordance with the present disclosure, a new way of constructing MMs is provided which utilizes time deconvolution of FFTs and the use of windowing functions specifically designed to facilitate time deconvolution. FFTs may be performed in non-periodic ways to reduce artifacts and further facilitate deconvolution. These deconvolved FFTs may be used alone as a MM or may be correlated with other FFTs (either deconvolved or not) to produce a PMM.

[00020] Thus, the disclosed embodiments are contrary to that of conventional use of FFTs because, instead of using FFTs to do deconvolutions, disclosed embodiment utilize deconvolution to perform FFTs (or, more specifically, to improve the FFTs).

[00021] As should be understood from the following detailed explanations, some windowing functions improve ease with which FFT output can be deconvolved. For example, N equations in N unknowns may simplify to a recursive formula that involves only totaling a few terms. Furthermore, if the windowing function is asymmetric, with the more recent samples getting the greater weight, the deconvolution may become stable.

[00022] Accordingly, disclosed embodiments of the invention deconvolve the output of a series of FFTs, while using specific windowing functions to make the FFT easier and better

behaved; in addition, the FFTs may be performed at opportunistic times so as to reduce the FFT artifacts.

[00023] With this preliminary and generalized explanation of the disclosed embodiments in mind, the following provides more specific definitions of various terms used in the followed detailed description.

Definitions

[00024] The following definitions are used herein.

[00025] FT: Fourier Transform - an algorithm that computes the amplitudes of the spectrum for a waveform.

[00026] DFT: Discrete Fourier Transform - an algorithm that computes the amplitudes of the spectrum for a discrete (digitized) waveform. The DFT output can be a complex number or just the real amplitude. Many of the preferred embodiments of this invention only need the real amplitude. Unless specifically described as complex, all references to DFTs herein are for DFTs with real output.

[00027] FFT: Fast Fourier Transform - a fast running DFT method that is so popular that its name is often used synonymously with DFT. DFT and FFT are used interchangeably herein.

[00028] Window: The portion of time used by a Fourier Transform (or equivalent technique). In a DFT the window size (in samples) is known as the dimension of the DFT. For example, if a signal is digitized with 8000 samples per second, a DFT with a dimension of 4000 will operate on 4000 samples (one half-second) of data.

[00029] Windowing Technique: A popular DFT method whereby the samples within the window are not all treated equally. For example, a simple DFT with dimension 4000 will simply transform the 4000 samples. With a windowing technique, the 4000 samples will be modulated to give more weight to the samples in the middle and less weight to the samples at the beginning and the end. Windowing techniques are designed to reduce the side lobes/artifacts in the DFT's frequency response.

[00030] dB: decibel - logarithmic ratio of measurement used in, for example, acoustics and electronics measurements and calculations.

[00031] dBFS: dB Full Scale - DB relative to the maximum peak level in the digital representation.

[00032] Time Slice: A portion of time. A time slice may, for example, be represented by an FFT run on a particular time window of data. However, the window will typically be much larger than the time slice it represents and centered on the time slice. The size of the time slices is determined by the spacing between successive FFT runs, not by the size of the window. For a digitized signal with 8000 samples per second, if a new FFT is run every 8 samples, then the time slices are 8 samples (1 millisecond) wide. The FFT window might be 4000 samples (a half-second or 500 time slices) wide.

[00033] Frequency Bin: A small range of frequencies (e.g. 1702-1704Hz)

[00034] Cell: A unit in a matrix. Typically, a cell represents a frequency bin in a time slice and contains an amplitude in dBFS.

[00035] MM: Measuring Matrix - A matrix of cells representing the spectral amplitude of a waveform over time. A measuring matrix is generated by repeated FFTs (or the equivalent). Each FFT creates, for its time slice, a row (or column) of cells – one cell for each frequency bin. The amplitude in each cell is the amplitude for that frequency bin in that time slice. The cells are then inspected and marked, as appropriate, as maxima. A measuring matrix can be of infinite length, when processing a continuous signal in near real time. For a limited time waveform, a measuring matrix can be of finite length. For convenience and clarity, a time slice in a measuring matrix is a row. Hereafter, the word “row”, if used without any explanation, means the portion of a measuring matrix representing a time slice (or, in some cases, a time interval such as single sample of the signal).

[00036] Maximum Cell: A cell marked as having one or more types of maxima.

[00037] Simple Maximum Cell: A cell whose amplitude is greater than the cells immediately adjacent. If a cell's amplitude is greater than that of the cells in the same time slice that are just above it and just below it in frequency, the cell is a frequency peak simple maximum. If a cell's amplitude is greater than that of the cells in the same frequency bin that are just before it and just after it in time, the cell is a time peak simple maximum. A single cell can be both a time and frequency simple maximum. Time peak and frequency peak simple maximum cells may be distinctly marked or may be treated as synonymous and just called “simple maximum cells,” or, “simple maxima,” for short.

[00038] Associated Maximum (“Little Brother”) Cell: A cell adjacent to a simple maximum whose amplitude is within a designated threshold of the simple maximums and also

greater than that of the cell on the other side. If a cell is a frequency peak simple maximum, the cells in the same time slice that are just above and below the simple maximum in frequency are candidates for associated maxima. If a cell is a time peak simple maximum, the cells in the same frequency bin that immediately precede it and succeed it are candidates for associated maxima. In an exemplary embodiment, if the amplitude in the candidate cell preceding a simple maximum is within 2dB of the simple maximum's amplitude and also greater than the amplitude of the cell that precedes it, then it would be marked as a little brother. In an exemplary embodiment, if the amplitude in the candidate cell just above the simple maximum in frequency is within 3dB of the simple maximum's amplitude and also greater than the amplitude of the cell just above it in frequency, then it would be marked as a little brother. The dB thresholds for little brothers adjacent in time need not be the same as for little brothers adjacent in frequency. Time and frequency little brothers may be distinctly marked or may be treated as synonymous and marked simply as little brothers. A single cell can be both.

[00039] PMM: Precision Measuring Matrix - A MM with correlated maxima marked. (Now, in accordance with embodiments of this disclosure, any MM with precision maxima marked. Such precision maxima may be found without correlating multiple MMs, when a single MM is of sufficiently high precision, through deconvolution.)

[00040] Preliminary to the more detailed description of embodiments of this disclosure, a summary review of supporting technology provided in previously filed Application No. PCT/US2009/064120 (incorporated by reference) is provided to fully disclose the context of the embodiments. In accordance with the embodiments of that previously filed disclosure, a machine-implemented method for digital signal processing is provided. That method, as shown in Figure 1 is a machine-implemented method for digital signal processing, comprising: obtaining a digital signal from conversion of an analog signal or from data storage at 101a, b; 102; constructing one or more MMs comprised of cells containing the amplitudes for particular times and frequencies at 103-107; marking maxima in these matrices based on comparisons of the cell amplitudes at 108-112; and relating those maxima to find correlated maxima, where multiple maxima agree in both time and frequency at 113. A new matrix, called a PMM, is generated with the correlated maxima marked at 114 and outputting the PPM at 115. (Note: all these maxima are local maxima but, for brevity, we refer to them simply as "maxima.")

[00041] Each MM is typically generated by repeated transformation of the input signal using, for example, an FFT. Each transformation represents a portion of time, called a time slice, in the input signal and has a row of cells, each cell corresponding to a frequency range, called a frequency bin. Each cell is populated with an amplitude, representing the signal strength for its corresponding frequency bin/time slice. Cells in each MM having maximum amplitudes within preferably each time slice and/or frequency bin are identified and marked. Many methods for identifying maxima may be used, yielding many types of maxima.

[00042] Figure 2 shows a view of an example measuring matrix produced by blocks 103-107 of Fig. 1 with simple maximum cells marked by blocks 108-112 of Fig. 1. In this example, a row is a time slice, and a column is a frequency bin. The number in each cell is the corresponding amplitude measurement (in dBFS).

[00043] The frequency peak simple maximum cells are marked with a dark border and the time peak simple maximum cells are marked with a grey background. For example, frequency peak simple maxima may be cells in a time slice in an MM having an amplitude that exceeds that of the two adjacent cells in frequency. Thus, for example, in Fig. 2, cell (160, 671.9) is marked as a frequency peak simple maximum (with a dark border) because it has an amplitude that is greater than its adjacent cells (160, 656.3) and (160, 687.5).

[00044] Similarly, time peak simple maximum cells are cells with local maximum amplitude within a particular frequency bin. Thus, for example, in Fig. 2, cell (159, 671.9) is marked as a time peak simple maximum (with a shaded background) because it has an amplitude greater than that of the adjacent cells (158, 671.9) and (160, 671.9).

[00045] Although little brothers are not marked in Fig 2, the data provides some indication of where they might be. For example, assuming a 3dB threshold for little brothers, note that cell (160, 671.9) is marked with a dark border as a frequency peak simple maximum cell while adjacent cells (160, 656.3) and (160, 687.5) are candidates for associated maximum cells; however, only cell (160, 656.3) is close enough in amplitude to qualify as an associated maximum (within 3dB). Because the amplitude of that cell is also greater than that of cell (160, 640.6), it may be a little brother.

[00046] This same determination may be made for associated maximum cells in a time slice. Thus, maxima in various matrices and/or of various types that coincide in time and

frequency may be marked in a PMM. Adjacent correlated maxima in the PMM may then be linked together as partial chains.

[00047] It should also be understood that a maximum cell may be identified by comparing its amplitude with the amplitudes of adjacent cells or by comparing the amplitudes of other specifically related cells. A cell is a simple maximum cell if the amplitude of the cell is greater than the amplitudes of its adjacent cells. Other types of maxima may include: associated “little brother” maxima, angle maxima, and burglar maxima. If multiple maxima are found for the same time slice and frequency bin (for example, in different MMs), then the maxima may coincide; as a result, the corresponding cell in the PMM may be marked as a correlated maximum.

[00048] The amplitude in each cell in the PMM is populated with a function of the values in the corresponding cells in the originating MMs (e.g., a weighted average).

[00049] Various MMs and PMMs may have high resolution and accuracy measurements for instantaneous frequency and amplitude of a time series signal. This may be accomplished by constructing multiple MMs of varying sizes, marking the maxima in the MMs, and then correlating the maxima. Smaller-sized transforms provide better time resolution while the larger-sized transforms provide better frequency resolution. For this reason, two or more measuring matrices (differing in time and frequency resolutions) may be used to build a PMM.

[00050] Adjacent maxima in a PMM can be linked into chains called partial chains. This linking is accomplished by connecting any two maximum cells in adjacent time slices that are in identical or close frequency bins.

[00051] In accordance with one disclosed embodiment, two MMs may be created using FFTs of different dimensions; simple maxima and little brothers (in both time and frequency) may be marked with, for example, a 2 dB threshold for the little brothers. In such an implementation, all four types of maxima (i.e., time or frequency, and simple or little brother) may be marked simply as “maxima.”

[00052] The corresponding PMM may be created by comparing cells in the two MMs with matching time and frequency and marking maxima in the PMM where both have maxima. The cells in the PMM may then be populated with the average amplitude of the corresponding cells in the original MMs.

[00053] Alternative implementations and embodiments may be produced by variations of the above. For example, the time maxima may be eliminated and only frequency maxima may be used. Alternatively, the little brother threshold may be changed from 2 dB to any other value; moreover, the little brother maxima may be eliminated.

[00054] Furthermore, more than two MMs may be created and correlated to generate the PMM. When more than two MMs are used, the agreement between all of them need not be universal. For example, if five different MMs are used to generate the PMM, three out of five maxima at the same time and frequency may be required to identify a correlated maximum. Alternative determinations are also possible.

[00055] Moreover, rather than simply treating all maxima equally or of equal weight, a little brother may be treated differently from a simple maximum. It should also be appreciated that the criteria for a correlated maximum may be more complicated than simple counting or addition –however, any mathematical formula is possible.

[00056] Additionally, a correlated maximum may be determined differently for different frequency ranges. Thus, for low frequencies, larger dimension MMs may be useful for increased frequency resolution. Conversely, for high frequencies, smaller dimension MMs may be sufficient, thereby improving efficiency and speed of analysis.

[00057] Thus, it should be appreciated that any combination of these variations may be used in an exemplary embodiment.

[00058] Moreover, any windowing technique might be used. Thus, multiple MMs can be generated using the same dimension FFT but different windowing techniques. Maxima may then be marked in these MMs (possibly with different marking criteria), and the MMs may then be compared to identify correlated maxima and build the PMM. Alternatively, multiple MMs may be produced using both different dimensions and different windowing techniques. Thus, it should be appreciated that the possible combinations are endless.

[00059] In order to better understand the functionality explained in relation to Fig. 1, Fig. 3 provides an alternative representation of the operation of the components previously illustrated in Fig. 1 for providing the novel methodologies and functionality. As shown in Fig. 3, an input signal at 1005 is input to a signal processing module 1001. The module 1001 includes a measurement engine 1002, a marking engine 1003, and a comparing engine 1004, which effectively cooperate to produce a PMM.

[00060] It should be understood that each of these engines 1002-1004 included in the signal processing module 1001 (and the signal processing module 1001 itself) may be implemented utilizing one or more computers with at least one Central Processing Unit (CPU) and at least one memory device (not illustrated in FIG. 3 but illustrated, for example, as 1002 in FIG. 1).

[00061] Further, the measurement engine 1002, marking engine 1003, and comparing engine 1004 may be implemented in whole or in part utilizing, for example, a Field Programmable Gated Array (FPGA), a Digital Signal Processing (DSP) chip, a Graphic Processing Unit (GPU), an Application Specific Integrated Circuit (ASIC), etc. Furthermore, the measurement engine 1002, marking engine 1003, and comparing engine 1004 may be implemented at least in part utilizing software modules (discussed above with reference to FIG. 1) as one or more engines and stored on computer-readable storage.

[00062] The PMM generated by the comparing engine 1004 may be provided as output data 1006. The output data 1006 may be provided to output module 1007 which stores, displays, and/or transmits the output data.

[00063] As explained throughout the present disclosure, the disclosed embodiments may be implemented utilizing software operating on one or more pieces of hardware, which may include, example, a computer. Thus, the disclosed embodiments may run on a single processor with a single core, a single processor with multiple cores, or multiple processors with single or multiple cores. Furthermore, the software may run on one or more servers that interact with one or more user interfaces at one or more locations that may be remote to one another.

[00064] Furthermore, that software may implement the functionality disclosed herein with reference to the modules, components and engines illustrated in Figs. 1 and 3. Some or all of the functionality provided by the disclosed embodiments may be provided using software, general or specialized digital signal processor chips, dedicated hardware, firmware, etc. Additionally, the functionality may be embodied on one or more circuit boards comprising, for example, digital signal processor chips, to be mounted in a computer or other module.

[00065] Furthermore, some functionality provided by the disclosed embodiments may be implemented using parallel computing hardware. Thus, for example, a main memory of a parallel processor computing device may be either shared memory (shared between all

processing elements in a single address space), or distributed memory (in which each processing element has its own local address space).

[00066] In accordance with a disclosed embodiment, new ways of generating a MM may create a PMM as part of a new dynamic computer machine process that produces accurate amplitude and frequency information in relation to time. To better understand the utility of that disclosed embodiment, Figure 4 provides an alternative theoretical model for the disclosed embodiment. Specifically, in accordance with the embodiment, a set of method operations are performed beginning at 202, wherein a transform performs a series of periodic FFTs on a signal to transform the input into the frequency domain. It should be understood that each FFT produces a set of amplitudes by frequency within a given time slice, as explained above with regard to Fig. 2. Subsequently, at 204, time deconvolution is performed to compare the cells in the matrix generated at 202 to produce another matrix, identical in shape but with the amplitudes in each cell computed based on the time deconvolution algebra. As a result, a matrix is generated which is more precise than the original, but otherwise identical in terms of what it represents and how it is used. Subsequently, at 206, an MM generator then marks the cells as depicted, for example, in Fig. 2.

[00067] The operations performed in Fig. 4 are identical to the creation of a measuring matrix in US Patent application No. PCT/US2009/064120 except that the present disclosure provides an additional deconvolution operation performed at 204 and may utilize exponential windowing of the FFT. Thus, the operations performed in Fig. 4 may be substituted for the dual-stage formation of the MM illustrated in Fig. 1, wherein operations are performed at, e.g., 103 and 108, 104 and 109, 105 and 110, etc. The increased utility provided by this disclosed embodiment may be best appreciated when it is recognized that a regular (i.e., non-deconvolved) FFT may actually be quite imprecise in frequency and/or time.

[00068] Deconvolution involves comparing an FFT's output with previous FFTs' outputs and solving algebraically for what is new in the most recent FFT's output. However, this can be a difficult (or even impossible) task, depending on the windowing function selected in the generation of the FFTs. Typical windowing functions (e.g., Hamming or Hanning) are not conducive to deconvolution. However, an asymmetric windowing function, particularly a decaying exponential or a function that ends in a decaying exponential, can be more easily deconvolved.

[00069] Conceptually, the simplest variation of deliberate selection of windowing function characteristics to optimize deconvolution is the use of an exponential window of infinite width. This is analogous to the exponential smoothing method used in statistics. More specifically, given a series of values (X_T), an exponentially smoothed average (S_T) can be produced by weighting the most recent X_T more heavily. A smoothing constant α gives the weight given to the most recent value. Prior values may be given exponentially less weight going back in time. Thus:

$$[00070] \quad S_T = \sum_{i=0}^{\infty} \alpha(1-\alpha)^i X_{T-i}$$

[00071] This can be reduced to the recursive formula:

$$[00072] \quad S_T = \alpha X_T + (1-\alpha)S_{T-1}$$

[00073] Time deconvolution requires derivation of the X 's from the S 's as a function of time and across time slices, which is fairly straightforward by simply solving for X_T :

$$[00074] \quad X_T = \frac{S_T - (1-\alpha)S_{T-1}}{\alpha}$$

[00075] Thus, if only the exponentially smoothed averages was known from, for example, a daily tracking poll leading up to an election, the actual daily polling figures used could be derived (assuming α was known). It should be appreciated, however, that actual tracking polls typically use a simple moving average which is, in practice, impossible to deconvolve.

[00076] Continuing with the analogy to statistical, exponential smoothing techniques, since an FFT window cannot be infinite, the recursive formula gets an extra term. When the sum is limited to N terms, the formula for S_T becomes:

$$[00077] \quad S_T = \alpha X_T + (1-\alpha)S_{T-1} - \alpha(1-\alpha)^N X_{T-N}$$

[00078] Hence, the deconvolved formula for X_T gains a term too:

$$[00079] \quad X_T = \frac{S_T - (1-\alpha)S_{T-1} + (1-\alpha)^N X_{T-N}}{\alpha}$$

[00080] However, because $(1-\alpha)^N$ may be very small, this extra term may actually be neglected. However, since X_{T-N} is an earlier term (and thus known), it remains straightforward to include.

[00081] Successive FFTs can be treated analogously to this statistical, exponential smoothing technique. Thus, if a windowing function is exponential, each frequency bin in each new FFT output may be analogous to a new S_T . Thus, the X_T is analogous to the “new” (or latest) portion of the FFT (for that frequency bin). This recognized relationship yields accurate time information from a long FFT (which, it should be understood, has accurate frequency information but inaccurate time information).

[00082] Unfortunately, the use of asymmetric windowing functions does a poor job of reducing artifacts inherent in FFTs, in particular, side-lobes. Windowing functions reduce artifacts by reducing the starting and ending amplitude of the signal being transformed. For example, a decaying exponential reduces the ending amplitude but not the starting amplitude.

[00083] However, as recognized in an embodiment disclosed herein, one way around the problems associated with asymmetric windowing functions is to only perform FFTs at opportunistic times when the starting amplitude is small. Although disclosed embodiments of generating an MM may involve repeated FFTs performed at regular intervals (e.g., every 64 samples), in such embodiments the FFTs may be performed opportunistically, at irregular intervals, only being done when, for example, the signal crosses 0, so that the amplitude of a sample near that zero crossing is small. It should be noted that, in such an implementation, the dimension of all the FFTs must be the same, e.g., 4096, for the bins to be comparable.) Thus, for example, an FFT might be performed at sample number 1000 (when the signal crossed 0), and the next FFT performed at sample 1109 (when the signal next crossed 0 again). That next FFT would represent a time slice of 109 samples, as it analyzed that many “new” samples of the signal. Also, 109 samples would have dropped off the “back” of that next FFT. Any deconvolution methodology would have to explicitly account for this.

[00084] When an MM is generated using FFTs performed opportunistically at irregular intervals, each row of the MM may represent one FFT (as shown in Fig. 2). However, since each row may not represent the same time slice, the size of the time slice represented by each row may have to be stored and dealt with in subsequent processing.

[00085] Alternatively, a separate row may be used for each sample. Thus, each new FFT may fill as many rows as the width of its time slice (109 rows in the example above). It should be noted that these operations and transformations are computer processing intensive but

are also conceptually simple; as a result, the operations and transformations greatly simplify subsequent processing.

[00086] The many rows produced by each new FFT may be filled with identical values, or smoothing methods may be used so that the cell values do not jump abruptly from one FFT to the next.

[00087] Nevertheless, a time slice (e.g., including 109 samples in the above example) may be longer than desired. Since, in this disclosed embodiment, the length of a time slice may be determined by when the signal crosses zero, one further solution to the issue is to modify the signal to cross zero more often. This may be accomplished by reducing the low frequency information in the signal. More specifically, the signal may be pre-processed by feeding it through a high pass filter before performing the FFT. This high pass filter may be analog or digital.

[00088] In accordance with at least one disclosed embodiment, a windowing function may be selected that ends in a decaying exponential but begins with some simple function that starts small and ramps up in a way that is easily deconvolved (e.g., a linear function). Thus, a starting point may always have a small amplitude, thus reducing the side-lobes. This may enable successive FFTs to be performed at regular intervals.

[00089] It should be appreciated that any of the above-described techniques may be performed in reversed time as well. By combining the result obtained in forward time with the result generated in reverse time, further increased precision may be obtained.

[00090] Also, various windowing functions and different dimension FFTs may be combined, as per Patent Application No. PCT/US2009/064120.

[00091] In particular, the deconvolved FFTs may be of such precision that they alone may be used to produce more accurate amplitude values in a MM. Thus, cross correlation of different FFTs to form PMM may not be necessary. Therefore, the rest of the construction of the MM and PMM may be implemented using the approaches disclosed, for example, in Patent Application No. PCT/US2009/064120.

[00092] As explained above, with relation to Figs. 1 and 3, the disclosed embodiments may be embodied by software on a digital computer machine. It may run on a single processor with a single core, a single processor with multiple cores, or multiple processors with single or multiple cores. The invention may be embodied using general or specialized digital signal

processor chips. The invention may be embodied in dedicated hardware. The invention may be embodied on one or more circuit boards comprising, for example, digital signal processor chips, to be mounted in a computer or other device. Some or all of the functionality provided by the disclosed embodiments may be provided using software, general or specialized digital signal processor chips, dedicated hardware, firmware, etc. Additionally, the functionality may be embodied on one or more circuit boards comprising, for example, digital signal processor chips, to be mounted in a computer or other module.

[00093] Some functionality provided by the disclosed embodiments may be implemented using parallel computing hardware. Thus, for example, a main memory of a parallel processor computing device may be either shared memory (shared between all processing elements in a single address space), or distributed memory (in which each processing element has its own local address space).

[00094] Furthermore, disclosed embodiments may be implemented wherein the matrix data structure may be replaced by other data structures that can logically serve the same function. These data structures may be made up of fields and/or include, but are not limited to, for example, a sparse matrix, a linked queue, etc.

[00095] Moreover, there are many foreseeable variations, for example, identified maximum cells may be represented by a sparse matrix, an identified chain of cells may be represented by a linked queue, etc.

[00096] The invention may have a wide range of applications, including, but not limited to, for example, signal time-variance analysis including audio, audio spectrum analysis, signal analysis in an applicable industry in any frequency range, data compression, digital cochlea for the deaf, "voice print" information, etc.

[00097] The information developed by the invention may be used to provide new or improved inputs to other signal processors, analysis devices, algorithms, systems, and organizations. Records of related partial chains running across the time-frequency plane, together with the amplitudes or interpolated amplitudes along each chain, may provide a rich and concise record of the components of particular signal sources. Signals that were previously hidden by stronger signals may be measured and visualized, particularly when the partials are linked into partial chains in the PMM visual display.

[00098] Moreover, the functionality and technical effects provided by the disclosed embodiments may be utilized to provide new or improved inputs to other signal processors, analysis devices, algorithms, systems, and organizations. For example, records of related partial chains running across the time-frequency plane, together with the amplitudes or interpolated amplitudes along each chain, may provide a rich and concise record of the components of particular signal sources. Signals that were previously hidden by stronger signals may be measured and visualized, particularly when the partials are linked into partial chains in the PMM visual display.

[00099] Thus, the examples and embodiments described herein are non-limiting examples. The invention is described in detail with respect to exemplary embodiments, and to those skilled in the art will now be apparent from the foregoing that changes and modifications may be made without departing from the invention in its broader aspects, and the invention, therefore, as defined in the claims is intended to cover all such changes and modifications as fall within the true spirit of the invention.

[000100] Exemplary embodiments of the invention can be used to accurately measure sound components even when the sound components are part of a compound waveform containing a mixture of sounds. Exemplary embodiments of the invention may also be used, for example, for compound waveforms containing sounds even when the sounds come in short or long duration bursts and/or are changing in pitch and/or in amplitude.

[000101] The examples and embodiments described herein are non-limiting examples. The embodiments described in detail with respect to exemplary embodiments, and to those skilled in the art should be apparent from the foregoing that changes and modifications may be made without departing from the invention in its broader aspects, and the invention, therefore, as defined in the claims is intended to cover all such changes and modifications as fall within the true spirit of the invention.

[000102] Although the present invention has been described and illustrated in detail, it is to be clearly understood that this is done by way of illustration and example only and is not to be taken by way of limitation. The scope of the present invention is to be limited only by the terms of the appended claims.

Claims

What is claimed is:

1. A method of forming a matrix of time, frequency and amplitude of an input signal, the method comprising:

obtaining an input signal in the form of a digital waveform signal from data storage or from conversion of a physical analog signal received from an analog source or captured by a physical analog device;

transforming the input signal into the frequency domain over time;

time deconvoluting the transformed signal; and

creating a measuring matrix of the deconvolved signal.

2. The method of claim 1 including using a windowing function designed to facilitate time deconvolution.

3. The method of claim 2, wherein the windowing function is a decaying exponential.

4. The method of claim 2, wherein the windowing function is an initial linear ramp followed by a decaying exponential.

5. The method of claim 1, wherein the time deconvoluting is performed by:

$$X_T = \frac{S_T - (1 - \alpha)S_{T-1} + (1 - \alpha)^N X_{T-N}}{\alpha}, \text{ where } S_T \text{ is an exponentially smoothed}$$

average, X_T , is the deconvoluted value at time T and α is a smoothing constant.

6. A method of performing Fast Fourier Transforms FFT comprising:
determining when a first element of a window of an input signal is small for each window; and

performing a series of FFTs, not at regular intervals but the determined time of the small first element for that window.

7. The method of claim 6, limited to when the signal crosses zero (changes sign).
8. The method of claims 1 or 2 combined with the method of claims 4 or 7.
9. The method of claims 1, 2, 3, 4, 5, 6, 7 or 8, wherein the method is done both forwards and backwards — the FFTs are performed on the signal in regular time (forwards) and also on the signal in reversed time (“played backwards”).
10. The method of claim 1, wherein the matrix has a row for each FFT.
11. The method of claim 1, wherein the matrix has a row for each sample in the digitized signal and each FFT corresponds to many rows in the matrix.
12. The method of claim 11, wherein all the rows corresponding to a particular FFT are filled in with identical values.
13. The method of claim 12, wherein the cells are subsequently smoothed using a weighted averaging method so as to eliminate abrupt jumps from rows corresponding to a particular FFT and rows corresponding to the next FFT.
14. The method of claims, 11, 12 or 13, combined with the method of claim 8, wherein each cell’s value is produced by averaging the values from the forwards and the backwards methods.
15. The method of claims 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13 or 14, wherein a precision measuring matrix (PMM) is from a plurality of measuring matrices
16. The method of claim 15, wherein the deconvolved FFT is used to determine the amplitude value of some cells but the production and marking of the cells as a maxima is done using other FFTs.

17. The method of claim 1 or 6, wherein the method is performed on a processor.




FIG. 1

| | | ← Frequency Bin → | | | | | | | | | |
|----------------|-----|-------------------|-------|-------|-------|-------|-------|--|--|--|--|
| | | 609.4 | 625.0 | 640.6 | 656.3 | 671.9 | 687.5 | | | | |
| ↑ Time Slice ↓ | 157 | -74.7 | -77.6 | -74.3 | -60.9 | -50.0 | -46.1 | | | | |
| | 158 | -78.3 | -78.8 | -72.3 | -57.4 | -48.6 | -47.7 | | | | |
| | 159 | -74.5 | -84.0 | -71.3 | -54.8 | -42.6 | -52.1 | | | | |
| | 160 | -71.2 | -72.7 | -68.7 | -52.9 | -49.9 | -61.4 | | | | |
| | 161 | -75.6 | -66.6 | -61.9 | -52.0 | -52.6 | -59.9 | | | | |
| | 162 | -79.7 | -64.9 | -57.7 | -52.9 | -55.4 | -61.6 | | | | |
| | 163 | -82.4 | -63.5 | -56.8 | -55.5 | -58.6 | -73.7 | | | | |
| | 164 | -72.2 | -61.2 | -59.3 | -60.4 | -61.7 | -67.9 | | | | |

FIG. 2




FIG. 3




FIG. 4

INTERNATIONAL SEARCH REPORT

International application No.

PCT/US 10/56352

A. CLASSIFICATION OF SUBJECT MATTER

IPC(8) - G01R 13/00 (2010.01)

USPC - 702/66

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
USPC: 702/66Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched
USPC: 702/57; 702/77; 708/5; 708/315; 708/420 (text search - see terms below)

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

PubWEST(USPT,PGPB,EPAB,JPAB); Google

Search Terms: Fourier, transform, dft, fft, short-time, matrix, matrices, measurement, window, zero, crossing, deconvolve, deconvoluted, linear, exponential, smoothed, time slice, frequency, bin, windowing

C. DOCUMENTS CONSIDERED TO BE RELEVANT

| Category* | Citation of document, with indication, where appropriate, of the relevant passages | Relevant to claim No. |
|-----------|--|------------------------|
| Y | SAWADA et al., SPECTRAL SMOOTHING FOR FREQUENCY-DOMAIN BLIND SOURCE SEPARATION, September 2003 [retrieved on 06 January 2011]. Retrieved from the Internet:<URL:http://www.kecl.ntt.co.jp/icl/signal/iwaenc03/cdrom/data/0070.pdf> pgs 81-82, 102 | 1-5, 10-13, 17/1 |
| Y | CASEY, Auditory Group Theory with Applications to Statistical Basis Methods for Structured Audio, Chapter 3 [online], 02 February 1998 [retrieved on 06 January 2011]. Retrieved from the Internet:<URL:http://alumni.media.mit.edu/~mkc/thesis/>pgs 311, 313 | 1-7, 10-13, 17/1, 17/6 |
| Y | DE HAAN, A SURVEY ON METHODS FOR TIME-FREQUENCY ANALYSIS, Thesis [online], March 1998 [retrieved on 06 January 2011]. Retrieved from the Internet:<URL:http://www.bth.se/fou/cuppsats.nsf/all/af1cac2d8dea8bb9c1256def004e1c5e/\$file/A%20Survey%20on%20Methods%20for%20Time-Frequency%20Analysis.pdf> pg 31 | 3-4 |
| Y | US 4,884,229 A (DEKKER) 28 November 1989 (28.11.1989), entire document especially col 1, lns 58-66 | 5 |
| Y | US 5,780,759 A (SZALAY) 14 July 1998 (14.07.1998), entire document especially col 2, lns 11-18 | 7 |
| Y | US 2008/0034870 A1 (KURT-ELLI) 14 February 2008 (14.02.2008), entire document especially paras [0028]-[0029], [0149] | 12-13 |

 Further documents are listed in the continuation of Box C.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

07 January 2011 (07.01.2011)

Date of mailing of the international search report

26 JAN 2011

Name and mailing address of the ISA/US

Mail Stop PCT, Attn: ISA/US, Commissioner for Patents
P.O. Box 1450, Alexandria, Virginia 22313-1450

Facsimile No. 571-273-3201

Authorized officer:

Lee W. Young

PCT Helpdesk: 571-272-4300
PCT OSP: 571-272-7774

INTERNATIONAL SEARCH REPORT

International application No.

PCT/US 10/56352

| C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT | | |
|---|---|-----------------------|
| Category* | Citation of document, with indication, where appropriate, of the relevant passages | Relevant to claim No. |
| Y | OZBEK et al., MUSICAL NOTE AND INSTRUMENT CLASSIFICATION WITH LIKELIHOOD-FREQUENCY-TIME ANALYSIS AND SUPPORT VECTOR MACHINES, December 2007 [retrieved on 06 January 2011]. Retrieved from the Internet:<URL: <a 112="" 471="" 890="" 903"="" data-label="Page-Footer" href="http://doc-0c-94-docsviewer.googleusercontent.com/viewer/securedownload/dsn1aovipa7i846lsfcf94nedj8q2p4u/6p80eg02o0l2k7o9qjpls8g21q77oio/129441690000/Ymw=/AGZ5hq8BgbJY1gwaOYx83cPOdNw6/QRHRUVTaFh1Zzl3c3U1OXdLRXpmbjdUVkVndHEtallMzVTT3VPTVcyYm9uVHI3dUZJSjdeXpiakd6ZmVBLUdUbGNEUDQyNkg3ajJ2bDZKQ3ZTTVZGTVBIZDNLsJBYaWd1VFBkQUx6MkhBNm4yaHJFZjVhM0tUQUo5V29jQUZJYS1xNGFrdC1PMXI=?a=gp&filename=download&chan=EQAAAE4jsXHXBcaZcaZNQOG//57SwmkYEVNd9SrNBPnFb8IA&docid=412f94d7fad684276ac48ae1435b53b8&sec=AHsqidZUOC0zTgXHE-HEPdy4kf2xopNFDMApOWSAj5Qm_MdrMEhTcDgDeozCNjP1xHRUY9v7om&nonce=7enj82u88oc2a&user=AGZ5hq8BgbJY1gwaOYx83cPOdNw6&hash=d8qjgp4iqbdivrtm5eqifoak4bc1ntfp>pg 941</td> <td>6-7, 17/6</td> </tr> <tr> <td>Y</td> <td>----</td> <td></td> </tr> <tr> <td>A</td> <td>US 2003/0223354 A1 (OLSZEWSKI) 04 December 2003 (04.12.2003), entire document especially para [0173]</td> <td>1-7, 10-13, 17/1, 17/6</td> </tr> <tr> <td>A</td> <td>US 2006/0265218 A1 (SAMADANI) 23 November 2006 (23.11.2006), entire document</td> <td>1-7, 10-13, 17/1, 17/6</td> </tr> <tr> <td>A</td> <td>US 2001/0045153 A1 (ALEXANDER et al.) 29 November 2001 (29.11.2001), entire document</td> <td>1-7, 10-13, 17/1, 17/6</td> </tr> <tr> <td>A</td> <td>US 4,797,923 A (CLARKE) 10 January 1989 (10.01.1989), entire document</td> <td>1-7, 10-13, 17/1, 17/6</td> </tr> </tbody> </table> </div> <div data-bbox=">Form PCT/ISA/210 (continuation of second sheet) (July 2009) | |

INTERNATIONAL SEARCH REPORT

International application No.

PCT/US 10/56352

Box No. II Observations where certain claims were found unsearchable (Continuation of item 2 of first sheet)

This international search report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

- 1. Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:

- 2. Claims Nos.:
because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:

- 3. Claims Nos.: 8-9 and 14-16
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box No. III Observations where unity of invention is lacking (Continuation of item 3 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

- 1. As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims.
- 2. As all searchable claims could be searched without effort justifying additional fees, this Authority did not invite payment of additional fees.
- 3. As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims for which fees were paid, specifically claims Nos.:

- 4. No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

Remark on Protest

- The additional search fees were accompanied by the applicant's protest and, where applicable, the payment of a protest fee.
- The additional search fees were accompanied by the applicant's protest but the applicable protest fee was not paid within the time limit specified in the invitation.
- No protest accompanied the payment of additional search fees.