

US009270512B2

# (12) United States Patent

#### Eliaz et al.

# (54) NONLINEARITY COMPENSATION FOR

(71) Applicant: MagnaCom Ltd., Petach Tikva (IL)

RECEPTION OF OFDM SIGNALS

(72) Inventors: Amir Eliaz, Moshav Ben Shemen (IL);

Ilan Reuven, Ganey Tikva (IL)

(73) Assignee: MagnaCom Ltd. (IL)

(\*) Notice: Subject to any disclaimer, the term of this

patent is extended or adjusted under 35

U.S.C. 154(b) by 0 days.

(21) Appl. No.: 14/541,312

(22) Filed: Nov. 14, 2014

## (65) Prior Publication Data

US 2015/0358191 A1 Dec. 10, 2015

#### Related U.S. Application Data

(63) Continuation of application No. 14/298,373, filed on Jun. 6, 2014, now Pat. No. 8,891,701.

(51) Int. Cl.

#04L 27/26 (2006.01)

#04B 1/10 (2006.01)

#04L 1/20 (2006.01)

#04W 16/14 (2009.01)

## (58) Field of Classification Search

None

See application file for complete search history.

#### (56) References Cited

## U.S. PATENT DOCUMENTS

4,109,101 A 8/1978 Mitani 4,135,057 A 1/1979 Bayless, Sr. et al.

# (10) Patent No.: US 9,270,512 B2 (45) Date of Patent: Feb. 23, 2016

4,797,925 A 1/1989 Lin 5,111,484 A 5/1992 Karabinis 5,131,011 A 7/1992 Bergmans et al. 5,202,903 A 4/1993 Okanoue (Continued)

#### FOREIGN PATENT DOCUMENTS

WO	2007/000495 A1	1/2007
WO	2012/092647 A1	7/2012
WO	2013030815 A1	3/2013

#### OTHER PUBLICATIONS

Equalization: The Correction and Analysis of Degraded Signals, White Paper, Agilent Technologies, Ransom Stephens V1.0, Aug. 15, 2005 (12 pages).


(Continued)

Primary Examiner — Leon-Viet Nguyen (74) Attorney, Agent, or Firm — McAndrews, Held & Malloy, Ltd.

#### (57) ABSTRACT

An electronic receiver may comprise nonlinear distortion modeling circuitry, interference estimation circuitry, and sequence estimation circuitry. The receiver may receive an orthogonal frequency division multiplexing (OFDM) symbol in the form of an electromagnetic signal. The nonlinear distortion modeling circuitry may generate a nonlinear distortion model that models nonlinear distortion introduced to the received electromagnetic signal en route to the sequence estimation circuitry. The interference estimation circuitry may estimate inter-subcarrier interference present in the received OFDM symbol based on the generated nonlinear distortion model. The estimating of the inter-subcarrier interference may comprise applying the nonlinear distortion model to one or more candidate vectors generated by the sequence estimation circuitry. The sequence estimation circuitry may sequentially process a plurality of received virtual subcarrier values of the OFDM symbol using the estimated inter-subcarrier interference.

#### 32 Claims, 6 Drawing Sheets



# US 9,270,512 B2 Page 2

(56)	Referen	ices Cited	8,681,889 B2	3/2014	
77.0	D. CEPTA TE	DOOR DEED VED	8,731,413 B1		Dave et al.
U.S.	PATENT	DOCUMENTS	8,737,458 B2 8,744,003 B2	5/2014 6/2014	
5 240 200 A	0/1002	Chan at al	8,781,008 B2	7/2014	
5,249,200 A 5,283,813 A		Chen et al. Shalvi et al.	8,804,879 B1	8/2014	
5,291,516 A		Dixon et al.	8,811,548 B2	8/2014	
5,394,439 A	2/1995	Hemmati	8,824,572 B2	9/2014	
5,432,822 A		Kaewell, Jr.	8,824,599 B1 8,824,611 B2	9/2014 9/2014	
5,459,762 A		Wang et al.	8,831,124 B2	9/2014	
5,590,121 A 5,602,507 A		Geigel et al. Suzuki	8,842,778 B2	9/2014	
5,757,855 A		Strolle et al.	8,873,612 B1	10/2014	
5,784,415 A		Chevillat et al.	8,885,698 B2	11/2014	
5,818,653 A		Park et al.	8,885,786 B2 8,891,701 B1	11/2014 11/2014	
5,886,748 A 5,889,823 A	3/1999	Lee Agazzi et al.	8,897,387 B1	11/2014	
5,915,213 A		Iwatsuki et al.	8,897,405 B2	11/2014	
5,930,309 A		Knutson et al.	8,948,321 B2	2/2015	
6,009,120 A		Nobakht	8,972,836 B2 8,976,853 B2	3/2015 3/2015	
6,167,079 A 6,233,709 B1		Kinnunen et al. Zhang et al.	8,976,911 B2	3/2015	
6,272,173 B1		Hatamian	8,982,984 B2	3/2015	
6,335,954 B1		Bottomley et al.	8,989,249 B2		Zerbe et al.
6,356,586 B1		Krishnamoorthy et al.	9,003,258 B2 2001/0008542 A1	4/2015	
6,516,025 B1		Warke et al.	2001/0008542 A1 2002/0016938 A1	2/2001	Wiebke et al.
6,516,437 B1 6,532,256 B2	3/2003	Van Stralen et al. Miller	2002/0123318 A1		Lagarrigue
6,535,549 B1		Scott et al.	2002/0150065 A1	10/2002	Ponnekanti
6,591,090 B1	7/2003	Vuorio et al.	2002/0150184 A1		Hafeez et al.
6,675,184 B1*		Matsui 708/322	2002/0172297 A1 2003/0016741 A1		Ouchi et al. Sasson et al.
6,690,754 B1 6,697,441 B1		Haratsch et al. Bottomley et al.	2003/0010741 A1 2003/0132814 A1		Nyberg
6,785,342 B1		Isaksen et al.	2003/0135809 A1	7/2003	
6,871,208 B1		Guo et al.	2003/0210352 A1		Fitzsimmons et al.
6,968,021 B1		White et al.	2004/0009783 A1 2004/0037374 A1		Miyoshi
6,985,709 B2	1/2006		2004/003/3/4 A1 2004/0081259 A1		Gonikberg Ammer et al.
7,158,324 B2 7,190,288 B2		Stein et al. Robinson et al.	2004/0086276 A1		Lenosky
7,190,721 B2		Garrett	2004/0120409 A1		Yasotharan et al.
7,205,798 B1	4/2007	Agarwal et al.	2004/0142666 A1		Creigh et al.
7,206,363 B2		Hegde et al.	2004/0170228 A1 2004/0174937 A1	9/2004	Vadde Ungerboeck
7,215,716 B1 7,269,205 B2	5/2007 9/2007		2004/0203458 A1	10/2004	
7,467,338 B2	12/2008		2004/0227570 A1		Jackson et al.
7,830,854 B1		Sarkar et al.	2004/0240578 A1	12/2004	Thesling
7,974,230 B1		Talley et al.	2004/0257955 A1 2005/0032472 A1	2/2004	Yamanaka et al. Jiang et al.
8,005,170 B2 8,059,737 B2	8/2011 11/2011	Lee et al.	2005/0032472 A1 2005/0047517 A1	3/2005	Georgios et al.
8,175,186 B1		Wiss et al.	2005/0089125 A1*	4/2005	Zhidkov 375/346
8,199,804 B1		Cheong	2005/0123077 A1	6/2005	
8,248,975 B2		Fujita et al.	2005/0135472 A1 2005/0163252 A1		Higashino McCallister et al.
8,265,561 B2 *		Nakamura 455/63.1	2005/0103232 AT 2005/0193318 A1		Okumura et al.
8,351,536 B2 8,422,589 B2		Mazet et al. Golitschek Edler Von Elbwart	2005/0220218 A1		Jensen et al.
-,,		et al.	2005/0265470 A1		Kishigami et al.
8,432,987 B2		Siti et al.	2005/0276317 A1 2006/0067396 A1		Jeong et al. Christensen
8,498,591 B1		Qian et al.	2006/0007390 A1 2006/0109780 A1		Fechtel
8,526,523 B1 8,548,072 B1	9/2013 10/2013		2006/0109935 A1		McQueen et al.
8,548,089 B2		Agazzi et al.	2006/0171489 A1		Ghosh et al.
8,548,097 B1	10/2013	Eliaz	2006/0203943 A1 2006/0239339 A1		Scheim et al. Brown et al.
8,553,821 B1	10/2013		2006/0239339 A1 2006/0245765 A1		Elahmadi et al.
8,559,494 B1 8,559,496 B1	10/2013 10/2013		2006/0280113 A1	12/2006	
8,559,498 B1	10/2013		2007/0047121 A1		Eleftheriou et al.
8,565,363 B1	10/2013		2007/0092017 A1 2007/0098059 A1	4/2007	Abedi Ives et al.
8,566,687 B1	10/2013		2007/0098039 A1 2007/0098090 A1		Ma et al.
8,571,131 B1 8,571,146 B1	10/2013 10/2013		2007/0098116 A1		Kim et al.
8,572,458 B1	10/2013		2007/0110177 A1	5/2007	Molander et al.
8,582,637 B1	11/2013	Eliaz	2007/0110191 A1		Kim et al.
8,599,914 B1	12/2013		2007/0127608 A1		Scheim et al.
8,605,832 B1 8,665,941 B1	12/2013 3/2014		2007/0140330 A1 2007/0189404 A1		Allpress et al. Baum et al.
8,665,992 B1	3/2014		2007/0189404 A1 2007/0213087 A1		Laroia et al.
8,666,000 B2	3/2014	Eliaz	2007/0230593 A1	10/2007	Eliaz et al.
8,675,769 B1	3/2014		2007/0258517 A1		Rollings et al.
8,675,782 B2	3/2014	Eliaz	2007/0291719 A1	12/2007	Demirhan et al.

U.S. PATENT DOCUMENTS  2008/000789 A1 12/095 Jose et al.  2014/000881 A1 22/011 Elizac  2014/000881 A2 22/014 Sand  2014/000881 A1 22/011 Elizac  2014/000881 A1 22/011 Elizac  2014/000881 A2 42/014 Song et al.  2014/000881 A1 42/014 Elizac  2008/000781 A1 72/005 Glypose et al.  2014/000881 A1 42/014 Elizac  2008/000781 A1 72/005 Glypose et al.  2014/000881 A1 42/014 Elizac  2008/000781 A1 72/005 Glypose et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2008/000781 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2009/0007851 A1 12/000 Shriai et al.  2014/010531 A1 42/014 Elizac  2014/0105	(56) References Cited		ces Cited	2013/0121257 A1 5/2013 He et al.		
2008/000789 Al   2008   30 et al   2014/000881 Al   2014		U.S. P	ATENT	DOCUMENTS	2013/0343487 A1 12/2013 Eliaz	
2008.049598 Al   22008   March al   2014/009897 Al   4.2014   Eliza	2008/0002789	Δ1	1/2008	Ino et al		
2008.0130716 A.J   62008 Choe at J.   2014/0105267 A.J   42014 Eliaz   42014						
2008.019378 A.J.   62008 Copeland   2014/0193567 A.J.   42014 Eliaz   2008/019378 A.J.   72008 Alpress et al.   2014/019332 A.J.   42014 Eliaz   2016/01938 A.J.   2016/0193						
2008.019377 Al   7,2008 Alfgress et al.   2014-0105268 Al   4,2014 Elinz   2014-0106889 Al   1,2009 Closes   2009-01053 Al   1,2009 Closes   2009-01053 Al   1,2009 Closes   2009-01053 Al   2,2009 Closes   2,0009-01053 Al   2,000						
2009/00028234 Al   1/2009   2009/0002834 Al   2009/0002834 A			7/2008	Allpress et al.		
2009-0003428 Al   1-2009   2009-002534 Al   2-2009   2-2009-002534 Al   2-2009-002534 Al   2-2009-002504 Al   2-200						
2009.0028234 Al   2009   Calvarial   375127   2014/01/33580 Al   2014   Eliaz   2014/01/33580 Al   2014/01/33580					2014/0108892 A1 4/2014 Eliaz	
2009/0058820	2009/0028234	A1	1/2009	Zhu		
2009-003580 Al   32006   2009-003680 Al   42006   2009-003680 Al   42						
2009.0115813 Al 5:2009   Hongo et al.   20140161170 Al 6:2014   Elizaz						
2009.012854 A1						
2009/0137212   A1   5/2009   Beltoserkovsky   2014/0247904   A1   20214   Eliaz   2009/02245226   A1   20209   McKown   2014/0247904   A1   20214   Eliaz   2014/026861   A1   20216   Chrabie et al.   2014/026861   A1   20216   Chrabie et al.   2014/026861   A1   20216   Clerck et al.   2014/0376388   A1   122016   Clerck et al.   2014/0376388   A1   122016   Clerck et al.   2015/004843   A1   22210   Clerck et al.   2015/004843						
2009/02/1308 Al   9209   Rottomley   2014/02/9861 Al   92/014 Eliaz   2014/0301507 Al   102/014 Eliaz   2014/0308328 Al   112/009   Clerckx et al.   2014/0308328 Al   112/016   Eliaz   2014/0308328 Al   112/016   Chen   2015/001/030838 Al   2010   Chen   2015/001/08 Al   12/016   Chen   2015/001/08 Al   12/016   Eliaz   2014/0308328 Al   12/016   Chen   2015/004/9843 Al   22/015   Eliaz   2016/006/2708 Al   3/2016   Rajkotia et al.   2015/006/3708 Al   3/2016   Rajkotia et al.   2015/006/3499 Al   3/2015   Eliaz   2016/006/3858 Al   6/2016   Chen   2015/006/398 Al   3/2016	2009/0137212	A1	5/2009	Belotserkovsky		
2009/02/2863 Al   2009/02/2865 Al   10/2009   Robinson et al.   2014/03/1525 Al   10/2014   Eliaz   2009/02/2865 Al   10/2009   Chrabisch et al.   2014/03/1525 Al   10/2014   Eliaz   2015/03/1525 Al   10/2014						
2009/024526   Al   10/2009   Robinson et al.   2014/03/19/7   Al   10/2014   Eliaz   2009/020620   Al   11/2009   Chraibch et al.   2014/03/15/28   Al   11/2014   Eliaz   2019/020620   Al   11/2009   Clercke et al.   2014/03/63/8   Al   12/2015   Eliaz   2010/0002692   Al   2010   Cohen   2016/00/63/8   Al   2015   Eliaz   2010/003100   Al   2010   Sun et al.   2015/00/63/89   Al   2015   Eliaz   2010/003703   Al   2010   Sun et al.   2015/00/63/89   Al   3/2015   Eliaz   2010/003703   Al   2010   Khayrallah   2015/00/73/89   Al   3/2015   Eliaz   2010/003703   Al   2010   Cohen   2015/00/73/89   Al   3/2015   Eliaz   2010/003010   Al   2010   Cohen   2015/00/73/89   Al   3/2015   Eliaz   2010/0030250   Al   2010   Cohen   2015/00/73/89   Al   3/2015   Eliaz   2010/00205050   Al   2010   Cohen   2016/00/73/89   Al   3/2015   Eliaz   2010/00205050   Al   2010   Cohen   2016/00/73/89   Al   3/2015   Eliaz   2010/00205050   Al   2010   Cohen   2016/00/73/89   Al   2010   Cohen   2016/00/7					2014/0286459 A1 9/2014 Eliaz	
2009/03/2962   Al   11/2009   Transes et al.   2014/03/3638   Al   12/2014   Eliaz   2015/00/03/100   Al   1/2016   Bims   2015/00/1008   Al   1/2015   Eliaz   2016/00/3438   Al   2/2010   Cohen   2015/00/9484   Al   1/2015   Eliaz   2016/00/2075   Al   3/2016   Rajkotia et al.   2015/00/3439   Al   3/2016   Rajkotia et al.   2015/00/3439   Al   3/2016   Khayrallah   2015/00/3439   Al   3/2016   Khayrallah   2015/00/3439   Al   3/2015   Eliaz   2016/00/3439   Al   3/2016   Forenza et al.   2015/00/3439   Al   3/2015   Eliaz   2016/00/3209   Al   7/2010   Aue   2016/00/20/383   Al   8/2010   Yu et al.   2016/00/20/3834   Al   8/2010   Alpress et al.   2016/00/20/3834   Al   8/2010   Value   2016/00/20/3834   Al   1/2010   Davies   2016/00/23/384   Al   1/2010   Davies   2016/00/23/384   Al   1/2010   Davies   2016/00/23/384   Al   1/2010   Davies   2016/00/39/39   Al   1/2010   Davies   2016/00/39/39/39   Al   1/2010   Davies   2016/00/39/39/39/39   Al   1/2010   Davies   2016/00/39/39/39/39   Al   1/2010   Davies   2016/00/39/39/39/39/39/39/39/39/39/39/39/39/39/			10/2009	Robinson et al.		
2009/032384   Al   12/2009   Eder et al.						
2016/0034253   Al   2/2010   Sun et al.   2015/0049843   Al   2/2015   Reuven et al.   2015/0067705   Al   2/2010   Sun et al.   2015/0067872   Al   2/2015   Eliaz   2015/0063499   Al   3/2015   Eliaz   2015/0063499   Al   3/2015   Eliaz   2015/0078493   Al   3/2015						
2010/0039100   Al   2/2010   Sum et al.   2015/0057322   Al   2/2015   Eliaz   2015/007349   Al   3/2015   Eliaz   2015/007089   Al   3/2015   Eliaz   2015/007089   Al   3/2015   Eliaz   2015/007849   Al   3/2010   Al   2010   Al   2010   Al   2010   Eliaz   Al   2010						
2010/0062705 Al 3/2010 Rajkotia et al.   2015/0063499 Al 3/2015 Eliaz   2010/00163085 Al 6/2010 Khayrallah   2015/0070889 Al 3/2015 Eliaz   2015/0070889 Al 3/2016 Vict al.   2010/0020577 Al 8/2010   Vict al.   2010/00205874 Al 8/2010   Vict al.   2010/00205874 Al 8/2010   Ece et al.   2010/00215107 Al 8/2010   Pavics   2010/0023898 Al 1/2010   Pavics   2010/0023898 Al 1/2010   Pavics   2010/00238481   Al 1/2010   Pavics   2010/00239325   Al 1/2010   Pavics   2010/00239325   Al 1/2010   Minytalani et al.   2011/0064171   Al 3/2011   Huang et al.   2011/006487 Al 3/2011   Solution et al.   2011/006487 Al 8/2012   Vict al.   2011/006497 Al 3/2011   Vict al.   2011/0073530   Al 7/2011   Solution et al.   2011/0073530   Al 7/2011   Vict al.   2011/0103455   Al 8/2011   Vict al.   2011/0103455   Al 8/2011   Vict al.   2011/0103455   Al 8/2011   Vict al.   2011/0103453   Al 8						
2010/01/88085 Al   6/2010   Khayrallah   2015/007489 Al   3/2015   Eliaz   2015/0078491 Al   3/2015   2015/0078491 Al   3/2015   Eliaz   2015/0078491 Al	2010/0062705	A1	3/2010	Rajkotia et al.		
2010/01/20393						
2010/02/02/05/05 Al   8/2010   Cue st al.					2015/0078491 A1 3/2015 Eliaz	
Modulation and Coding for Linear Gaussian Channels, G. David   Forney, Jr., and Gottfried Ungerboeck, IEEE Transactions of Information Theory, vol. 44, No. 6, Oct. 1998 pp. 2384-2415 (32 pages).   Polito   Po					OTHER PUBLICATIONS	
Modulation and Coding for Linear Gaussian Channels, G. David						
2010/020832 A1   8/2010   Lee et al.						
Solition   Computer Science   Computer   Computer Science   Computer   C						
Dubus c al.						
Cosine (RRC) filtering, (2002), pp. 1-23 (23 pages).	2010/0220825	A1	9/2010	Dubuc et al.		
Chan, N., "Partial Response Signaling with a Maximum Likelihood Sequence Estimation Receiver" (1980). Open Access Dissertations and Theses. Paper 2855, (123 pages). The Viterbi Algorithm, Ryan, M.S. and Nudd, G.R., Department of Computer Science, Univ. of Warwick, Coventry, (1993) (17 pages). The Viterbi Algorithm, Ryan, M.S. and Nudd, G.R., Department of Computer Science, Univ. of Warwick, Coventry, (1993) (17 pages). R. A. Gibby and J. W. Smith, "Some extensions of Nyquist's telegraph transmission theory," Bell Syst. Tech. J., vol. 44, pp. 1487-2011/003455 A1 * 3/2011 Kim et al. 375/201 Kim et al. 2011/013459 A1 6/2011 Kim et al. 2011/0164492 A1 7/2011 Ma et al. 2011/0123856 A1 8/2011 Weight Science (11) Silverman et al. 2011/01248266 A1 9/2011 Barsoum et al. 2011/0248266 A1 9/2011 Barsoum et al. 2011/0248366 A1 10/2011 Silverman et al. 2011/0248366 A1 10/2011 Shiue et al. 2011/0248366 A1 10/2011 Shiue et al. 2011/0319978 A1 12/2011 Wu et al. 2011/0319978 A1 12/2011 Wu et al. 2011/0319978 A1 12/2011 Wu et al. 2012/0051464 A1 3/2012 Chabie et al. 2012/0015443 A1 5/2012 Jao et al. 2012/016617 A1 5/2012 Jao et al. 2012/0163489 A1 6/2012 Ramakrishnan 2012/0177138 A1 7/2012 Chrabieh et al. 2012/0177138 A1 7/2012 Chrabieh et al. 2012/0027248 A1 8/2012 Abmed et al. 2012/0027248 A1 8/2012 Chrabieh et al. 2012/0027248 A1 8/2012 Chrabieh et al. 2012/0027248 A1 8/2012 Chrabieh et al. 2013/0028299 A1 12/2013 Liu et al. 2013/004887 A1 2/2013 Liu et al. 2013/004887 A1 2/					· · ·	•
2011/0051864 Al   202101   2011/0064171 Al   3/2011   2011/0064171 Al   3/2011   2011/0064171 Al   3/2011   2011/0064171 Al   3/2011   2011/0074500 Al   3/2011   3/2011   3/2011   2011/0074500 Al   3/2011   3						t
2011/0051864 Al   3/2011   Chalia et al.					* * * *	S
2011/0064171   A1   3/2011   Huang et al.						c
2011/0074506   A1   3/2011   Bouillet et al.   3/2012   Bouillet et al.   3/2013   South   Bouillet et al.   3/2014   South   Bouillet et al.   3/2014   South   Bouillet et al.   3/2016   South	2011/0064171	A1	3/2011	Huang et al.		
2011/0074506 A1   3/2011   Kleider et al.   375/260   2011/009986 A1   4/2011   Kwon et al.   375/260   2011/013455 A1   5/2011   Forrester et al.   375/232   2011/0134899 A1   6/2011   Jones, IV et al.   2011/015064 A1   2011/0164492 A1   7/2011   Ma et al.   2011/0188550 A1   8/2011   Wehinger   2011/0243266 A1   0/2011   Barsoum et al.   2011/0243266 A1   10/2011   Roh   2011/0249709 A1   2011/0310978 A1   12/2011   Nam et al.   2011/0310978 A1   12/2011   Wu et al.   2011/0310978 A1   2012/0025909 A1   2012/016647 A1   5/2012   Koren et al.   2012/0177138 A1   7/2012   Chrabieh et al.   2012/0207248 A1   2012/0207248 A1   2012/0207248 A1   2013/0028299 A1   2012/03028299 A1   2012/0						
2011/090986 A1	2011/0074506	A1		Kleider et al.		
2011/0134859 A1						
2011/0134899 A1 6/2011 Jones, IV et al. 2011/0150064 A1 6/2011 Kim et al. 2011/016064 A1 7/2011 Ma et al. 2011/016030 A1 7/2011 Wehinger 2011/0182329 A1 7/2011 Barsoum et al. 2011/0248266 A1 10/2011 Barsoum et al. 2011/0249709 A1 10/2011 Shiue et al. 2011/0310978 A1 12/2011 Nam et al. 2011/0310978 A1 2012/0025909 A1 2012/0027132 A1 2012/0027132 A1 2012/0027134 A1 3/2012 Kamuf et al. 2012/01730489 A1 6/2012 Ramakrishnan 2012/016617 A1 5/2012 Ramakrishnan 2012/017318 A1 7/2012 Chrabieh et al. 2013/0028299 A1 8/2013 Liu et al. 2013/002829 A1 1/2013 Tsai Liu et al. 2013/0024877 A1 2/2013 Liu et al. 2013/0044877 A1 2/2013 Liu et al. 2015/005040 A1 2/2013 Liu et al. 2013/0044877 A1 2/2013 Liu et al. 2015/005040 A1 2/2013 Liu et al. 2013/0044877 A1 2/2013 Liu et al. 2015/005040 A1 2/2013 Liu et al. 2015/0044877 A1 2/2013 Liu et al. 2015/004877 A1 2/2013 Liu et al. 2015/0044877 A1 2/2013 Liu et al. 2015/00504 A1 2/2013 Liu et al. 2015/0044877 A1 2/2013 Liu et al. 2015/0044877 A1 2/2013 Liu et al. 2015/00504 A1 2/2013 Liu et al. 2015/0044877 A1 2/2013 Liu et al. 2015/004877 A1 2/2013 Liu et al.						
2011/0150064   A1   7/2011   Ma et al.	2011/0134899	A1	6/2011	Jones, IV et al.		,
2011/0170630 A1 7/2011 Silverman et al. 7/2011 Webinger 295, Mar. 1990. 2011/0188550 A1 8/2011 Wajcer et al. 2011/0243266 A1 9/2011 Barsoum et al. 2011/0243266 A1 10/2011 Roh 22, No. 5, pp. 624-636, May 1974. 2011/0249709 A1 10/2011 Seshadri et al. 2011/0310823 A1 12/2011 Seshadri et al. 2011/0310823 A1 12/2011 Seshadri et al. 2011/0310978 A1 12/2011 Sum et al. 2012/0025909 A1 2/2012 Got et al. 2012/0025909 A1 2/2012 Rouquette 2012/0051464 A1 3/2012 Kamuf et al. 2012/0120990 A1* 5/2012 Ramakrishnan 2012/0177138 A1 7/2012 Chrabieh et al. 2012/0207248 A1 8/2012 Ahmed et al. 2012/0207248 A1 8/2012 Ahmed et al. 2013/0028299 A1 1/2013 Tsai Silverman et al. Nyquist signaling," IEEE Trans. Inform. Theory, vol. 36, pp. 289-295, Mar. 1990. G. Ungerboeck, "Adaptive maximum-likelihood receiver for carrier modulated data-transmission systems," IEEE Trans. Commun., vol. 22, No. 5, pp. 624-636, May 1974. G. D. Forney, Jr., "Maximum-likelihood sequence estimation of digital sequences in the presence of intersymbol interference," IEEE Trans. Inform. Theory, vol. 18, No. 2, pp. 363-378, May 1972. A. Duel-Hallen and C. Heegard, "Delayed decision-feedback sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. M. V. Eyubog •lu and S. U. Qureshi, "Reduced-state sequence estimation with set partitioning and decision feedback," IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988. W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						a
2011/0188550 A1 8/2011 Wajcer et al. 2011/0248266 A1 9/2011 Barsoum et al. 2011/0249709 A1 10/2011 Shiue et al. 2011/0275338 A1 11/2011 Seshadri et al. 2011/0310823 A1 12/2011 Wu et al. 2011/0310978 A1 12/2011 Wu et al. 2012/0025909 A1 2/2012 A1 2/2012 Stamuf et al. 2012/0027132 A1 2/2012 Kamuf et al. 2012/0051464 A1 3/2012 Kamuf et al. 2012/016617 A1 5/2012 Koren et al. 2012/0163489 A1 6/2012 Ramakrishnan 2012/0177138 A1 7/2012 Chrabieh et al. 2012/027248 A1 8/2012 Ahmed et al. 2013/0028299 A1 1/2013 Tsai 2013/0028299 A1 1/2013 Tsai 2013/0024877 A1 2/2013 Liu et al.  G. Ungerboeck, "Adaptive maximum-likelihood receiver for carrier modulated data-transmission systems," IEEE Trans. Commun., vol. 22, No. 5, pp. 624-636, May 1974. G. D. Forney, Jr., "Maximum-likelihood sequence estimation of digidisequences in the presence of intersymbol interference," IEEE Trans. Inform. Theory, vol. 18, No. 2, pp. 363-378, May 1972. A. Duel-Hallen and C. Heegard, "Delayed decision-feedback sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. M. V. Eyubog •lu and S. U. Qureshi, "Reduced-state sequence estimation of digidisequence estimation of digidisequence in the presence of intersymbol interference," IEEE Trans. Inform. Theory, vol. 18, No. 2, pp. 363-378, May 1972. A. Duel-Hallen and C. Heegard, "Delayed decision-feedback sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. M. V. Eyubog •lu and S. U. Qureshi, "Reduced-state sequence estimation of itigical mation with set partitioning and decision feedback," IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988. W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						-
2011/0228869         A1         9/2011         Barsoum et al.         modulated data-transmission systems," IEEE Trans. Commun., vol.           2011/0249709         A1         10/2011         Roh         22, No. 5, pp. 624-636, May 1974.           2011/0275338         A1         11/2011         Seshadri et al.         G. D. Forney, Jr., "Maximum-likelihood sequence estimation of digital sequences in the presence of intersymbol interference," IEEE           2011/0310978         A1         12/2011         Nam et al.         Trans. Inform. Theory, vol. 18, No. 2, pp. 363-378, May 1972.           2012/0025909         A1         2/2012         Jo et al.         A. Duel-Hallen and C. Heegard, "Delayed decision-feedback sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436,           2012/0051464         A1         3/2012         Kamuf et al.         May 1989.           2012/0120990         A1*         5/2012         Koren et al.         May 1989.           2012/0163489         A1         6/2012         Ramakrishnan         Commun., vol. 36, pp. 13-20, Jan. 1988.           2012/0207248         A1         8/2012         Ahmed et al.         W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						
2011/0249709 A1 10/2011 Roh 22, No. 5, pp. 624-636, May 1974.  2011/0275338 A1 11/2011 Seshadri et al. Seshadr						
2011/0275338 A1 11/2011 Seshadri et al. Nam et al. 12/2011 Vu et al. 12/2012 Vu et al. 12/2012 A1 2/2012 A2/2012 A2/2012 A2/2014 A1 3/2015 A1 2/2012 A1 2/2013 A1 2/2014 A1 2012/0016617 A1 5/2012 A1 2/2012 A1 2/2012 A1 2/2013 A1 2/2013 A1 2/2014 A1 3/2015 A1 2/2015 A1 2/2015 A1 2/2015 A1 2/2016 A1 5/2016 A1 5/2012 A1 2/2016 A1 5/2012 A1 2/2018 A1 5/2012 A1 2/2018 A1 5/2012 A1 2/2018 A1 5/2012 A	2011/0243266	A1	10/2011	Roh		
2011/0310823 A1 12/2011 Nam et al. 2011/0310978 A1 12/2011 Wu et al. 3012/0025909 A1 2/2012 Rouquette Simulation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. 2012/012/016617 A1 5/2012 Koren et al. 375/219 Koren et al. 375/219 Ramakrishnan Chrack, "IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. 2012/0163489 A1 6/2012 Ramakrishnan Chrack, "IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. 2012/0163489 A1 6/2012 Ramakrishnan Chrack, "IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989. 2012/0163489 A1 6/2012 Ramakrishnan Chrack, "IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988. 2012/0177138 A1 7/2012 Chrabieh et al. W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						
2011/03/109/8 Al 2/2012 Wu et al. 2/2012 Jo et al. 2/2012 Al 2/2012 Rouquette Samuf et al. 2012/0027132 Al 2/2012 Kamuf et al. 3/2012 Koren et al. 3/2012 Koren et al. 375/219 Sulvey and S						3
2012/0027132 A1 2/2012 Joe et al. sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436, May 1989.  2012/0106617 A1 5/2012 Jao et al. Jao et al. Jao et al. Size of the first of	2011/0310978	A1	12/2011	Wu et al.		k
2012/0051464 A1 3/2012 Kamuf et al. 5/2012 Jao et al. May 1989.  M. V. Eyubog •lu and S. U. Qureshi, "Reduced-state sequence estimation with set partitioning and decision feedback," IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988.  May 1989.  M. V. Eyubog •lu and S. U. Qureshi, "Reduced-state sequence estimation with set partitioning and decision feedback," IEEE Trans. Commun., vol. 36, pp. 13-20, Jan. 1988.  W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.					sequence estimation," IEEE Trans. Commun., vol. 37, pp. 428-436	
2012/0120990       A1 * 5/2012       Koren et al	2012/0051464	A1	3/2012	Kamuf et al.	•	
2012/0163489       A1       6/2012       Ramakrishnan       Commun., vol. 36, pp. 13-20, Jan. 1988.         2012/0177138       A1       7/2012       Chrabieh et al.       W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile 2013/0044877         2013/0044877       A1       2/2013       Liu et al.       Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.					, ,	
2012/0177138 A1 7/2012 Chrabieh et al. W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "An 2012/0207248 A1 8/2012 Ahmed et al. efficient method for prefilter computation for reduced-state equalization," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile 2013/0044877 A1 2/2013 Liu et al. Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						•
2013/0028299       A1       1/2013       Tsai       tion," Proc. of the 11th IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.	2012/0177138	A1	7/2012	Chrabieh et al.		
2013/0044877 A1 2/2013 Liu et al. Radio Commun. PIMRC, vol. 1, pp. 604-609, London, UK, Sep.						
··					· ·	

#### (56) References Cited

#### OTHER PUBLICATIONS

W. H. Gerstacker, F. Obernosterer, R. Meyer, and J. B. Huber, "On prefilter computation for reduced-state equalization," IEEE Trans. Wireless Commun., vol. 1, No. 4, pp. 793-800, Oct. 2002.

Joachim Hagenauer and Peter Hoeher, "A Viterbi algorithm with soft-decision outputs and its applications," in Proc. IEEE Global Telecommunications Conference 1989, Dallas, Texas, pp. 1680-1686, Nov. 1989.

S. Mita, M. Izumita, N. Doi, and Y. Eto, "Automatic equalizer for digital magnetic recording systems" IEEE Trans. Magn., vol. 25, pp. 3672-3674,1987.

E. Biglieri, E. Chiaberto, G. P. Maccone, and E. Viterbo, "Compensation of nonlinearities in high-density magnetic recording channels," IEEE Trans. Magn., vol. 30, pp. 5079-5086, Nov. 1994.

W. E. Ryan and A. Gutierrez, "Performance of adaptive Volterra equalizers on nonlinear magnetic recording channels," IEEE Trans. Magn., vol. 31, pp. 3054-3056, Nov. 1995.

X. Che, "Nonlinearity measurements and write precompensation studies for a PRML recording channel," IEEE Trans. Magn., vol. 31, pp. 3021-3026, Nov. 1995.

O. E. Agazzi and N. Sheshadri, "On the use of tentative decisions to cancel intersymbol interference and nonlinear distortion (with application to magnetic recording channels)," IEEE Trans. Inform. Theory, vol. 43, pp. 394-408, Mar. 1997.

Miao, George J., Signal Processing for Digital Communications, 2006, Artech House, pp. 375-377.

Xiong, Fuqin. Digital Modulation Techniques, Artech House, 2006, Chapter 9, pp. 447-483.

Faulkner, Michael, "Low-Complex ICI Cancellation for Improving Doppler Performance in OFDM Systems", Center for Telecommunication and Microelectronics, 1-4244-0063-5/06/\$2000 (c) 2006 IEEE. (5 pgs).

Stefano Tomasin, et al. "Iterative Interference Cancellation and Channel Estimation for Mobile OFDM", IEEE Transactions on Wireless Communications, vol. 4, No. 1, Jan. 2005, pp. 238-245.

Int'l Search Report and Written Opinion for PCT/IB2013/01866 dated Mar. 21, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/001923 dated Mar. 21, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/001878 dated Mar. 21, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/002383 dated Mar. 21, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/01860 dated Mar. 21, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/01970 dated Mar. 27, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/01930 dated May 15, 2014.

Int'l Search Report and Written Opinion for PCT/IB2013/02081 dated May 22, 2014.

Ai-Dhahir, Naofal et al., "MMSE Decision-Feedback Equalizers: Finite-Length Results" IEEE Transactions on Information Theory, vol. 41, No. 4, Jul. 1995.

Cioffi, John M. et al., "MMSE Decision-Feedback Equalizers and Coding—Park I: Equalization Results" IEEE Transactions on Communications, vol. 43, No. 10, Oct. 1995.

Eyuboglu, M. Vedat et al., "Reduced-State Sequence Estimation with Set Partitioning and Decision Feedback" IEEE Transactions on Communications, vol. 36, No. 1, Jan. 1988.

Khaled M. Gharaibeh, Nonlinear Distortion in Wireless Systems, 2011, John Wiley & Sons, 2nd Edition, chapter 3, pp. 59-81.

Forney, G. David Jr., "Coset Codes—Part I: Introduction and Geometrical Classification" IEEE Transactions on Information Theory, vol. 34, No. 5, Sep. 1988.

Prlja, Adnan et al., "Receivers for Faster-than-Nyquist Signaling with and Without Turbo Equalization".

Int'l Search Report and Written Opinion for PCT/IB2014/002449 dated Mar. 12, 2015.

Digital predistortion of power amplifiers for wireless applications (Doctoral dissertation, Georgia Institute of Technology). Retrieved from the internet <a href="http://http://202.28.199.34/multim/3126235.pdf">http://http://202.28.199.34/multim/3126235.pdf</a> Ding, L. Mar. 31, 2005.

Digital predistortion for power amplifiers using separable functions. Signal Processing, IEEE Transactions on, 58(8), 4121-4130. Retrieved from the internet <a href="http://arxiv.org/ftp/arxiv/papers/1306/1306.0037.pdf">http://arxiv.org/ftp/arxiv/papers/1306/1306.0037.pdf</a>> Jiang, H., & Wilford, P.A. Aug. 8, 2010.


Digital predistortion linearization methods for RF power amplifiers. Teknillinen korkeakoulu. Retrieved from the Internet <a href="http://lib.tkk.fi/Diss/2008/isbn9789512295463/isbn9789512295463.pdf">http://lib.tkk.fi/Diss/2008/isbn9789512295463/isbn9789512295463.pdf</a> Teikari I. Sep. 30, 2008.


Kayhan, F., et al., Joint Signal-Labeling Optimization for Pragmatic Capacity under Peak-Power Constraint, 978-1-4244-5637, 2010.


Kayhan, F., et al., Constellation Design for Transmission over Nonlinear Satellite Channels, Oct. 5, 2012.


Kayhan, F., et al., Signal and Labeling Optimization for Non-Linear and Phase Noise Channels, Department of Electronics and Telecommunications.


\* cited by examiner



















212 312 310  $\underline{G}_n : \underline{G}_n$ Successor Buffer generation 306 Nonlinear Survivor Distortion selection  $PM_n^{1,1}:PM_n^{M,K}$ metric calculation  $\underline{Y}_n$ Buffer  $\hat{\underline{F}}$ 

FIG. 7B





# NONLINEARITY COMPENSATION FOR RECEPTION OF OFDM SIGNALS

#### CLAIM OF PRIORITY

This application is a continuation of U.S. patent application Ser. No. 14/298,373, filed Jun. 6, 2014 (now patented as U.S. Pat. No. 8,891,701).

### INCORPORATION BY REFERENCE

The entirety of U.S. Pat. No. 8,781,008 titled "Highly-Spectrally-Efficient Transmission Using Orthogonal Frequency Division Multiplexing" is hereby incorporated herein by reference.

#### BACKGROUND

Limitations and disadvantages of conventional approaches to reception of signals in the presence of nonlinear distortion will become apparent to one of skill in the art, through comparison of such approaches with some aspects of the present method and system set forth in the remainder of this disclosure with reference to the drawings.

#### BRIEF SUMMARY

Methods and systems are provided for nonlinearity compensation for reception of OFDM signals, substantially as illustrated by and/or described in connection with at least one of the figures, as set forth more completely in the claims.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 shows an example transmitter operable to generate 35 inter-carrier correlated (ICI) orthogonal frequency divisions multiplexed (OFDM) signals.

FIG. 2 shows an example receiver operable to recover information from received ICI OFDM signals.

FIG. 3 shows an example implementation of the reduced 40 state sequence estimation (RSSE) circuitry of FIG. 2.

FIG. 4A shows a first example implementation of the non-linear distortion model determination circuitry of FIG. 2.

FIG. 4B shows a second example implementation of the nonlinear distortion model determination circuitry of FIG. 2. 45

FIG. 5 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a generalized third-order nonlinear distortion model.

FIG. **6** shows a first example implementation of the interference estimation circuitry of FIG. **2** for use with a digital 50 clipping nonlinear distortion model.

FIGS. 7A-7D show an example implementation in which the receiver of FIG. 2 performs two or more iterations over the subcarriers of an OFDM symbol to recover the data of the OFDM symbol in the presence of nonlinear distortion.

#### DETAILED DESCRIPTION

As utilized herein the terms "circuits" and "circuitry" refer to physical electronic components (i.e. hardware) and any 60 software and/or firmware ("code") which may configure the hardware, be executed by the hardware, and or otherwise be associated with the hardware. As used herein, for example, a particular processor and memory may comprise a first "circuit" when executing a first one or more lines of code and may 65 comprise a second "circuit" when executing a second one or more lines of code. As utilized herein, "and/or" means any

2

one or more of the items in the list joined by "and/or". As an example, "x and/or y" means any element of the three-element set  $\{(x), (y), (x, y)\}$ . As another example, "x, y, and/or z" means any element of the seven-element set  $\{(x), (y), (z), (x, y), (x, z), (y, z), (x, y, z)\}$ . As utilized herein, the terms "e.g.," and "for example" set off lists of one or more non-limiting examples, instances, or illustrations. As utilized herein, circuitry is "operable" to perform a function whenever the circuitry comprises the necessary hardware and code (if any is necessary) to perform the function, regardless of whether performance of the function is disabled, or not enabled, by some user-configurable setting.

FIG. 1 shows an example transmitter operable to generate inter-carrier correlated (ICI) orthogonal frequency divisions multiplexed (OFDM) signals. Shown is a transmitter that comprises encoder circuitry 102, mapper circuitry 104, intersubcarrier interference (ICI) generation circuitry 106, inverse fast Fourier transform (IFFT) circuit 108, and analog front end (AFE) 110.

The encoder circuitry **102** receives a vector of bits <u>B'</u> which are the bits of a particular OFDM symbol. The encoder circuitry **102** converts the bits <u>B'</u>, to a vector of bits <u>B</u>, in accordance with a forward error correction (FEC) algorithm 25 (e.g., Reed-Solomon, Low-Density Parity Check, Turbo, and/or the like).

The mapper circuit 104, is operable to map the vector  $\underline{B}$  to a vector A according to a selected modulation scheme. For example, for a quadrature amplitude modulation (QAM) scheme having an alphabet size of M (M-QAM), the mapper may map each  $Log_2(M)$  bits of B to a value represented as a complex number and/or as in-phase (I) and quadrature-phase (Q) components. Although M-QAM is used for illustration in this disclosure, aspects of this disclosure are applicable to any modulation scheme (e.g., pulse amplitude modulation (PAM), amplitude shift keying (ASK), phase shift keying (PSK), frequency shift keying (FSK), etc.). Additionally, points of the M-QAM constellation may be regularly spaced ("on-grid") or irregularly spaced ("off-grid"). Furthermore, the constellation used by the mapper 104 may be optimized for best bit-error rate (BER) performance (or adjusted to achieve a target BER) that is related to log-likelihood ratio (LLR) and to optimizing mean mutual information bit (MMIB) (or achieving a target MMIB).

The ISC generation circuitry 106 is operable to process A to generate a vector  $\underline{C}$ . The elements of  $\underline{A}$  are referred to herein as "virtual subcarrier values" of the particular OFDM symbol and the elements of C are referred to herein as the corresponding "physical subcarrier values" of the particular OFDM symbol, where: the vector A comprises N values, the vector C comprises P values, N and P are positive integers,  $N \ge 2$ , and  $N \ge P$ . The N elements of A are represented herein as  $a_1:a_N$ , with any particular one of the values represented as  $a_n$ . The P elements of C are represented herein as  $c_1:c_P$ , with any 55 particular one of the values represented as  $c_p$ . In an example implementation, the processing performed by the circuitry 106 may comprise cyclic filtering and/or decimation such that each of the ISC values of C depends on a plurality (perhaps all) of the elements of A. In an example implementation, the circuitry 106 may be similar to, or the same as, circuits 104 and 106 of the above incorporated Unites States Patent Application Publication US2013/0343473. In an example implementation,  $\Delta$  (an integer) pilot symbols may be inserted at the IFFT and the total number of physical subcarriers may be  $P+\Delta$ , where P is thus the quantity of data-carrying subcarriers.

The inverse fast Fourier transform (IFFT) circuit **108** is operable to convert the physical subcarrier value vector C (of

length P) to a corresponding vector of P time-domain samples (i.e., the time-domain representation of the particular OFDM symbol).

The analog front end (AFE) 110 is operable to convert the P time-domain values output by IFFT 108 to an analog representation, upconvert the resulting analog signal, and amplify the upconverted signal for transmission onto a channel 112. Thus, the transmitter front-end 118 may comprise, for example, a digital-to-analog converter (DAC), mixer, and/ or power amplifier. The front-end 118 may introduce nonlinear distortion and/or phase noise (and/or other non-idealities) to the transmitted signal 117. The nonlinear distortion introduced by the circuit 118 may be represented as  $NL_{Tx}$  which may be, for example, a polynomial, or an exponential (e.g., Rapp model). The model of the nonlinear distortion may incorporate memory (e.g., Volterra series). The transmitted values C, after being converted to the time domain, experiencing the nonlinear distortion introduced by the AFE 110, and passing through the channel 112 (which may also introduce nonlinear distortion and/or noise), emerge as a signal 113.

FIG. 2 shows an example receiver operable to recover information from received ICI OFDM signals. The receiver comprises an analog front-end 202, time domain preprocessing circuitry 204, a fast Fourier transform (FFT) circuit 208, frequency domain preprocessing circuitry 206, nonlinear distortion model determination circuitry 214, interference estimation circuitry 210, and reduced state sequence estimation (RSSE) circuitry 212.

The AFE 202 is operable to process the signal 113 corresponding to a particular OFDM signal to a vector of S' samples of the particular OFDM symbol. Such processing may comprise, amplification, downconversion (to IF or baseband), and analog-to-digital conversion. Thus, the receiver 35 front-end 202 may comprise, for example, a low-noise amplifier, a mixer, and/or an analog-to-digital converter. The AFE 202 may, for example, sample the received signal 113 P times per OFDM symbol period resulting in a S' of length P (where pilot symbols are used, the AFE 202 may sample P+ $\Delta$  times 40 per OFDM symbol). Due to non-idealities, the receiver frontend 202 may introduce nonlinear distortion and/or phase noise to the signal S'. The nonlinear distortion introduced by the front end 202 may be represented as  $NL_{Rx}$  which may be, for example, a polynomial, or an exponential (e.g., Rapp 45 model). The model of the nonlinear distortion may incorporate memory (e.g., Volterra series).

The time domain preprocessing circuitry **204** is operable to perform time-domain processing of the samples <u>S'</u> to generate received physical subcarrier value vector <u>S</u>. Such processing 50 may include, for example, timing acquisition, phase correction, frequency correction, decimation, DC removal, IQ mismatch correction, filtering, windowing, removal of pilot symbols, cyclic prefix removal, and/or the like.

The FFT **208** is operable to convert the time-domain physical subcarrier value vector  $\underline{S}$  (of length P) to a corresponding vector of P frequency-domain samples (i.e., convert the time-domain representation of  $\underline{S}$  to the frequency-domain representation of S).

The frequency domain preprocessing circuitry 206 is operable to perform frequency domain processing of the output of the FFT 208 to generate a vector  $\underline{Y}$ , which is a vector of N received virtual subcarrier values. Such processing may include, for example, performing the inverse of the ICI generation circuitry 106 (FIG. 1), and performing per-subcarrier 65 equalization. The elements of  $\underline{Y}$  are represented herein as  $y_1:y_N$ , with any particular one of the values represented as  $y_n$ .

4

The RSSE circuitry **212** is operable to perform reduced state sequence estimation on the vector  $\underline{Y}$  to generate a vector  $\underline{\hat{A}}$  which is the receiver's decision vector ("best guess" as to the transmitted virtual subcarrier value vector  $\underline{\hat{A}}$ ). Details of an example implementation of RSSE circuitry **212** are described below with reference to FIG. **3**.

The nonlinear distortion model determination circuitry 214 is operable to determine a model, NL, that represents/ enables reproduction of (to a desired accuracy) the nonlinear distortion experienced by the signal S' in the transmitter, the channel, and/or the receiver. In an example implementation, the nonlinear distortion introduced by the AFE 110 of the transmitter may be dominant and NL may be a representation of  $NL_{Tx}$ . The nonlinear distortion model, NL, may be, for example, a logical and/or mathematical expression, a look-up table, and/or any other suitable representation of the nonlinear distortion. Any one or more of a variety of model types may be used for NL, with each model type being characterized by one or more parameters. The model type and/or parameter values may be communicated directly by the transmitter (e.g., during handshaking) and/or may be learned by the receiver by processing signals received from the transmitter (e.g., selection of the model type and/or training of the parameter values may be based on preambles sent by the transmitter). In an example implementation, NL may comprise an AM/AM parameter whose value is dependent on transmitted signal strength, and an AM/PM parameter whose value is dependent on transmitted signal strength. In such an example implementation, received signal strength may be used as a proxy for transmitted signal strength and the received signal strength may be applied to the look-up table to determine appropriate values of the AM/AM and AM/PM parameters.

The interference estimation circuitry 210 is operable to estimate the interference, <u>F</u>, present in the received virtual subcarrier values <u>Y</u>, based on <u>Y</u> and based on NL. Details of example implementations of 210 are described below with reference to FIGS. 5 and 6.

FIG. 3 shows an example implementation of the reduced state sequence estimation (RSSE) circuitry of FIG. 2. The example RSSE circuitry 212 shown in FIG. 3 comprises nonlinear distortion circuitry 302, metric calculation circuitry 306, survivor selection circuitry 308, buffering circuitry 310, successor generation circuitry 312, and buffering circuitry 314. FIG. 2 depicts the RSSE circuitry 212 processing received virtual subcarrier value having index n (where 1≤n≤N) of a particular OFDM symbol.

The buffer circuitry **310** is operable to, upon completion of processing a particular received virtual subcarrier value of the OFDM symbol being processed, latch the selected survivor vectors such that those survivors are available for processing the next received virtual subcarrier value of the OFDM symbol. Thus, in FIG. **3**, which shows processing of received virtual subcarrier value having index n, the survivors selected upon completion of processing the received virtual subcarrier value having index n-1 ( $\widehat{\Delta}_{n-1}^1$ :  $\widehat{\Delta}_{n-1}^M$ ) are latched by the buffer **310** and output to the successor generation circuitry **312**. Each survivor  $\widehat{\Delta}_{n-1}^1$ :  $\widehat{\Delta}_{n-1}^M$  comprises up to n elements corresponding to one or more of subcarriers 0 through n-1. Elements of survivor  $\widehat{\Delta}_{n-1}^1$ :  $\widehat{\Delta}_{n-1}^M$  are represented herein as  $\widehat{\Delta}_{n-1}^1$ :  $\widehat{\Delta}_{n-1}^M$ , where D is the memory depth of the RSSE circuitry.

The successor generation circuitry 312 is operable to extend each of the M survivors from the previous iteration,  $\widehat{\underline{A}}_{n-1}^1$ ,  $\widehat{\underline{A}}_{n-1}^M$ , to K successors, resulting in successors  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$ . Elements of successor vector  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$  are represented herein

as  $\widehat{\underline{A}}_{n-1}^{1}$ : $\widehat{\underline{A}}_{n-1}^{M}$ , where  $\widehat{\underline{A}}_{n-1}^{1}$ : $\widehat{\underline{A}}_{n-1}^{M}$  is the element by which survivor  $\widehat{\underline{A}}_{n-1}^{1}$ : $\widehat{\underline{A}}_{n-1}^{M}$  was extended to create successor  $\widehat{\underline{A}}_{n-1}^{1}$ : $\widehat{\underline{A}}_{n-1}^{M}$ . The number of survivors, M, retained for each received virtual subcarrier value and the number of possible symbol transmitted virtual subcarrier values for which it is desired to search. Higher values of M and K may achieve improved results at the expense of increased size and complexity. In an example implementation, the value of K may be chosen to be the size of the constellation used by mapper 104 (FIG. 1) (e.g., for 64QAM K may be set to 64) such that each survivor is extended by each possible transmitted virtual subcarrier value.

The nonlinear distortion circuitry **302** is operable to, for each of the M×K successors  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$ , generate a candidate vector  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$  by introducing nonlinear distortion to the successor  $\underline{G}_n^{m,k}$ . Elements of candidate vector  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$  are represented herein as  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$ , where  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$  is the estimated constellation symbol of the (m,k) candidate for subcarrier index n,  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$  is the estimated constellation symbol of the (m,k) candidate for subcarrier index n–1, and so on (where n is less than D, D-n elements may be values from an initialization of the RSSE circuitry).

The nonlinear distortion introduced to each successor is determined based on NL from the nonlinear distortion model determination circuitry **214** (FIGS. **1**, **4**A, and **4**B). In this manner, the circuitry **302** attempts to reproduce (to desired/necessary accuracy) the nonlinear distortion experienced by the signal **113** (or S' where nonlinear distortion of the AFE **202** is accounted for in NL)).

The metric calculation circuitry **306** is operable to calculate branch a path metric,  $PM_n^{m,k}$  for each of the candidates  $\widehat{\underline{A}}_{n-1}^1$ ,  $\widehat{\underline{A}}_{n-1}^M$ , and output the path metrics to the survivor selection circuitry **308**. The path metric for candidate  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$  may be calculated as  $PM_n^{m,k}=BM_n^{m,k}+PM_{n-1}^{m,k}$ , where  $BM_n^{m,k}$  is the branch metric for candidate  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$ . The branch metric for candidate  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$  may be calculated based on  $\underline{F}$ . The manner in which the branch metric is calculated varies for different implementations. Some example branch metric calculations are described below with reference to FIGS. **5**, **6**, **7B**, **7C**, and **7D**.

The survivor selection circuitry **308** is operable to compare the path metrics for each of the candidates  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$  and select the M best candidates (corresponding to the M best path metrics) as the survivors  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$ .

The buffer circuitry 314 is operable to buffer samples of 50 signal  $\underline{Y}$  and/or initialization samples and may shift the samples out as signal  $\underline{Y}_n$ . For example, the first n elements of  $\underline{Y}_n$  may be equal to the first n elements of  $\underline{Y}$  and the remaining (D-n) elements of  $\underline{Y}_n$  may be known values used for initialization of the RSSE circuitry.

FIG. 4A shows a first example implementation of the nonlinear distortion model determination circuitry of FIG. 2. The example implementation of nonlinear distortion model determination circuitry 214 shown in FIG. 4A comprises circuitry 402 operable to estimate the nonlinear distortion experienced 60 by  $\underline{S}$  (the output of time-domain processing circuitry 204 in FIG. 2) in the time domain. The estimation of the nonlinear distortion may be based on, for example, preambles present in  $\underline{S}$ ', the received signal strength of 113, and/or based on control information (e.g., a model type best suited for the transmitter 65 from which signal 113 originated, initial nonlinear distortion model parameters, power level at signal 113 was transmitted,

6

and/or the like) communicated to the receiver (e.g., during handshaking and/or in frame headers of  $\underline{S}$ ). Once the time domain nonlinear distortion model, T, has been determined, it is passed to circuitry **404** which translates it to the frequency domain representation, NL. The frequency domain representation NL is then output by the circuitry **214**.

FIG. 4B shows a second example implementation of the nonlinear distortion model determination circuitry of FIG. 2. In the example implementation of FIG. 4B, the frequency domain NL is determined in the frequency domain directly from Y.

FIG. 5 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a generalized third-order nonlinear distortion model. The example implementation of the interference estimation circuitry 210 in FIG. 5 comprises interference calculation circuitry 502.

The notation  $f_n^{m,k}$  represents an estimate of the aggregate interference present in the received virtual subcarrier value having index n for candidate  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{m-1}^M$ . The aggregate interference estimate may, for example, be a complex number representing the magnitude and phase of the interference. The notation  $\underline{F}$  represents the vector (of length  $M \times K$ ) of aggregate interference estimates for all of the candidates  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{m-1}^M$  (i.e.,  $F = f_n^{1,1} \cdot f_n^{M,K}$ ). In some instances, the estimated aggregate interference may depend only on n (the received virtual subcarrier index) and may be the same for all of the candidates  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{m-1}^M$  (i.e., each of the estimates  $f_n^{1,1} \cdot f_n^{M,K}$  takes on the same value), but in other instances, the interference estimates may differ among the candidates  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{n-1}^M$ 

In a first variation, the aggregate interference estimate for candidate  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$  may be calculated exhaustively taking into account each of the other N-1 virtual subcarriers. This exhaustive calculation may comprise calculating  $f_n^{m,k} \alpha \Sigma_{i=0}^{N-1} \sum_{j=0}^{N-1} Z_i \cdot z_j^* \cdot z_{n-i+j}$ , where:  $\alpha$  is a parameter (or vector of parameters) determined by nonlinear model determination block  $\mathbf{208}$ ,  $\mathbf{z}_i = \mathbf{y}_i$  for  $\mathbf{i} \geq \mathbf{n}$ ,  $\mathbf{z}_i = \mathbf{g}_i^{m,k}$  for  $\mathbf{i} < \mathbf{n}$ ;  $\mathbf{z}_j = \mathbf{g}_j^{m,k}$  for  $\mathbf{j} < \mathbf{n}$ ,  $\mathbf{y}_i$  is a received virtual subcarrier value for subcarrier having index  $\mathbf{i}$ ,  $\mathbf{y}_j$  is the received virtual subcarrier value for subcarrier having index  $\mathbf{j}$ ,  $\mathbf{g}_i^{m,k}$  is the decision for the subcarrier having index  $\mathbf{i}$  for the  $(\mathbf{m},\mathbf{k})$  candidate, where  $\mathbf{g}_i^{m,k}$  is the decision the subcarrier having index  $\mathbf{j}$  for the  $(\mathbf{m},\mathbf{k})$  candidate.

In a second variation, the aggregate interference estimate for candidate  $\widehat{\underline{A}}_{n-1}^{1}$ :  $\widehat{\underline{A}}_{n-1}^{M}$  may be calculated taking into account only a selected subset of the other N-1 virtual subcarriers. This may reduce the amount of calculations necessary. This selective calculation comprise may calculating  $f_n^{m,k} = \alpha \sum_{i \in Q} \sum_{j \in Q} z_i \cdot z_j^* \cdot z_{n-i = j}$ , where  $\alpha$  is a parameter (or vector of parameters) determined by nonlinear model determination block 208, Q is a subset of the set 1:N;  $z_x = y_x$  for  $x \ge n$ ,  $z_x = g_x^{m,k}$  for x<n, and x is used as a generic for i and j. For 55 example, only indexes of virtual subcarriers having power above a determined threshold may be included in the set Q (based on the assumption that low-energy virtual subcarriers will experience relatively little nonlinear distortion and thus not contribute a lot of interference). The smaller the size of Q relative to the size of N, the more this selective calculation will reduce computational complexity/overhead.

Thus, common to both variations above is that, when calculating the interference present in received virtual subcarrier having index n due to another virtual subcarrier having index x for candidate  $\widehat{\Delta}_{n-1}^1$ ,  $\widehat{\Delta}_{n-1}^M$ , if a decision as to a transmitted virtual subcarrier having index x has already been generated

by the RSSE circuitry (i.e., x < n), then the decided value of x

(i.e.,  $g_x^{m,k}$ ) is used in the calculation, but if a decision as to a transmitted virtual subcarrier having index x has not yet been generated by the RSSE circuitry (i.e., x>n), then the received virtual subcarrier value having index x (i.e.,  $y_x$ ) is used for the calculation (based on the assumption that the interference in that received signal is relatively small compared to the desired signal and, therefore, error introduced is tolerable).

Once the estimated aggregate interference  $\mathbf{f}_n^{m,k}$  has been determined, the branch metric (represented as  $\mathrm{BM}_n^{m,k}$ ) for candidate  $\widehat{\mathbf{A}}_{n-1}^1 : \widehat{\mathbf{A}}_{n-1}^M$  may be calculated. In an example implementation, the following expression may be used:  $\mathrm{BM}_n^{m,k} = |\mathbf{y}_n - \widehat{\mathbf{A}}_{n-1}^1 : \widehat{\mathbf{A}}_{n-1}^M - \mathbf{f}_n^{m,k}|^2$ .

FIG. 6 shows a first example implementation of the interference estimation circuitry of FIG. 2 for use with a digital clipping nonlinear distortion model. In FIG. 6, the interference estimation circuitry 210 comprises clipped subcarrier determination circuit 602 and interference estimation circuit 604.

The clipped subcarrier determination circuit **602** is operable to determine which transmitted virtual subcarriers values were digitally clipped in the transmitter during the transmission that resulted in signal **113**. The circuit **602** then outputs the indexes of the clipped subcarriers to the circuit **604** as vector <u>I</u>. In an example implementation, the transmitter may directly send such information (e.g., in a header) and the circuit **602** may simply extract the information. In another example implementation, the circuit **602** may determine which transmitted virtual subcarrier values were digitally clipped based on the magnitude of the received virtual subcarrier values.

With a digital clipping model, the interference F may be determined by NL and I. Thus, once the circuitry 604 has been provided NL and I for a particular OFDM symbol, calculation of F may be straightforward (with much less computational complexity/overhead than for the implementation described with reference to FIG. 5). Once F is determined, the branch metric for candidate  $\widehat{\underline{A}}_{n-1}^{\perp}:\widehat{\underline{A}}_{n-1}^{M}$  may be calculated. The calculation of the interference may be simplified as compared to the calculation described with reference to FIG. 5. In an example implementation, it may be calculated using the following expression:  $\mathrm{BM}_n^{m,k} = \widehat{\underline{A}}_{n-1}^{\perp} : \widehat{\underline{A}}_{n-1}^M$ , which is substantially similar to the branch metric expression presented above with reference to FIG. 5 but with the m and k superscripts left off 45 of the interference term to indicate that the estimated aggregate interference present in the received virtual subcarrier having index n is the same for all candidates.

FIGS. 7A-7D show an example implementation in which the receiver of FIG. 2 performs two or more iterations over the 50 OFDM symbol to generate decisions as to the transmitted virtual subcarrier values of the OFDM symbol in the presence of nonlinear distortion. Shown in FIG. 7A is another example implementation of interference estimation circuitry 210, which comprises nonlinear distortion circuitry 702 and com-55 biner 704.

The nonlinear distortion circuitry **702** is operable to introduce nonlinear distortion to the received virtual subcarrier vector  $\underline{Y}$  to generate  $\underline{Y}$ . The nonlinear distortion introduced is determined based on NL from the nonlinear distortion model 60 determination circuitry **214** (FIGS. **1**, **4**A, and **4**B). In this manner, the circuitry **702** attempts to reproduce (to desired/necessary accuracy) the nonlinear distortion experienced by the signal **113** (or the signal  $\underline{S}$ ' where nonlinear distortion of the AFE **202** is accounted for in NL).

The combiner 704 combines  $\underline{Y}$  and  $\underline{Y}$ ' such that the output is the difference between  $\underline{Y}$  and  $\underline{Y}$ '. In this example imple-

8

mentation, the output of combiner **704** is  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$ —an initial approximation of the interference introduced by the nonlinear distortion experienced by  $\underline{Y}$ . It is acknowledged that, because there is interference present in  $\underline{Y}$  as a result of the nonlinear distortion that  $\underline{Y}$  experienced en route to the circuitry **210** (at least a portion of which NL is attempting to model), this  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$  is not going to be an exact measure of the actual interference present in  $\underline{Y}$ . Nevertheless, if the strength of the interference present in  $\underline{Y}$  is relatively small compared to the desired signal strength, the amount of additional interference contributed by the existing interference during application of NL may be small enough that  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$  is a suitable approximation.

Once  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$  is calculated as in FIG. 7A, a first iteration of processing the particular OFDM symbol is carried out by the RSSE circuitry 212 as shown in FIG. 7B. As is shown, during the first iteration on the particular OFDM symbol,  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$  is input to the metric calculation circuitry 306, and the N subcarriers are processed sequentially. For each subcarrier n, the sequential processing during the first iteration on the particular OFDM symbol comprises: extending, by successor generation circuitry 312, each of the M selected sur-25 vivors  $(\widehat{\underline{A}}_{n-1}^1; \widehat{\underline{A}}_{n-1}^M)$  from the previous subcarrier to K successors  $(\widehat{\underline{A}}_{n-1}^1;\widehat{\underline{A}}_{n-1}^M)$ ; distorting, by nonlinear distortion circuitry 302, each of the M×K successors to generate candidates  $\widehat{\underline{A}}_{n-1}^1:\widehat{\underline{A}}_{n-1}^M$ ; calculating, by metrics calculation circuitry 306, metrics for each candidate  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{n-n}^M$  using  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{n-1}^M$ ; and selecting, by survivor selection circuitry 308, the M best survivors  $\frac{\widehat{A}_{n-1}^1}{\widehat{A}_{n-1}^M}$ . Thus, the metrics for candidate  $\widehat{\underline{\underline{A}}}_{n-1}^1:\widehat{\underline{\underline{A}}}_{n-1}^M$  during the first iteration on the particular OFDM symbol are based on  $\widehat{\underline{A}}_{n-1}^{\top}$ :  $\widehat{\underline{A}}_{n-1}^{M}$  and  $y_{n+1}:y_{N}$  (as a result of using  $\underline{\widehat{A}}_{n-1}^1$ :  $\underline{\widehat{A}}_{n-1}^M$ ). Upon completing processing of all N subcarriers, the M selected survivors are  $\widehat{\underline{A}}_{n-1}^1 \cdot \widehat{\underline{A}}_{n-1}^M$ . In some instances, the accuracy of these survivors may be improved via one or more additional iterations over the particular OFDM symbol. FIGS. 7C and 7D illustrate an embodiment where a second iteration is performed in an attempt to improve the reliability of the estimates.

As is shown, in FIG. 7C, for the second iteration on the particular OFDM symbol,  $\frac{\widehat{\Delta}_{n-1}^1}{\widehat{\Delta}_{n-1}^M}$  (rather than  $\underline{Y}$  as was used in FIG. 7A) is used by circuitry **702** and **704** for calculating  $\underline{F}$ , which, as shown in FIG. 7D, is then input to metric calculation circuitry **306** for calculating metrics during the second iteration on the particular OFDM symbol.

During the second iteration on the particular OFDM symbol, the successors are processed similarly to the first iteration. For each subcarrier n, the sequential processing during the second iteration on the particular OFDM symbol comprises: extending, by successor generation circuitry 312, each of the M selected survivors  $(\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M)$  from the previous subcarrier to K successors  $(\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M)$  distorting, by nonlinear distortion circuitry 302, each of the M×K successors to generate candidates  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$ ; calculating, by metrics calculation circuitry 306, metrics for each candidate  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$  using  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$ ; and selecting, by survivor selection circuitry 308, the M best survivors  $\widehat{\Delta}_n^1; \widehat{\Delta}_n^M$ . Thus, the metrics for candidate  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$  during the first itenation on the particular OFDM symbol are based on  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$  and  $\widehat{\Delta}_{n-1}^1; \widehat{\Delta}_{n-1}^M$  (as a result of using  $\widehat{\underline{F}}$ ). Upon completing processing of all N subcarriers,

the M selected survivors are  $\widehat{\underline{A}}_{n-1}^1$ :  $\widehat{\underline{A}}_{n-1}^M$ , and the best of these  $(\widehat{\underline{A}}_{n-1}^1; \widehat{\underline{A}}_{n-1}^M)$  is selected for output to downstream circuitry such as a FEC decoder. In other implementations, additional iterations may be performed to refine these survivors even further.

In accordance with an example implementation of this disclosure, an electronic receiver (e.g., 200) may comprise nonlinear distortion modeling circuitry (e.g., 214), interference estimation circuitry (e.g., 210), and sequence estimation circuitry (e.g., 212). The receiver may receive an orthogonal frequency division multiplexing (OFDM) symbol in the form of an electromagnetic signal (e.g., 113). The nonlinear distortion modeling circuitry may generate a nonlinear distortion model (e.g., NL) that models nonlinear distortion introduced to the received electromagnetic signal en route to the 15 sequence estimation circuitry. The interference estimation circuitry may estimate inter- subcarrier interference present in the received OFDM symbol based on the generated nonlinear distortion model. The sequence estimation circuitry may sequentially process a plurality of received virtual sub- 20 carrier values (e.g., Y) of the OFDM symbol using the estimated inter-subcarrier interference. The processing may result in decisions as to a plurality of transmitted virtual subcarrier values (e.g.,  $\underline{\widehat{A}}_{n-1}^1$ :  $\underline{\widehat{A}}_{n-1}^M$ ) that correspond to the plurality of received virtual subcarrier values. The estimating of the inter-subcarrier interference may comprise applying the nonlinear distortion model to one or more candidate vectors  $(e.g., \underline{G}_n^{m,k})$  generated by the sequence estimation circuitry. The estimating of the inter-subcarrier interference may comprise determining which one or more of the transmitted virtual subcarrier values were digitally clipped in a transmitter from which the received electromagnetic signal originated. The estimating of the inter-subcarrier interference may comprise calculating the inter-subcarrier interference based on which one or more of the plurality of transmitted virtual subcarrier values were digitally clipped in the transmitter and based on the generated nonlinear distortion model. The determining which one or more of the plurality of transmitted virtual subcarrier values were digitally clipped in the transmitter may comprise determining magnitude of each of the plurality of received virtual subcarrier values. The estimating of the inter- subcarrier interference may comprise applying the nonlinear distortion model to the received electromagnetic signal to generate an intermediate electromagnetic signal (e.g., Y'). The estimating of the inter-subcarrier interference may comprise subtracting the received electromagnetic signal from the intermediate electromagnetic signal, a result of the subtraction being the estimate of the inter-subcarrier interference. The plurality of received virtual subcarrier values may comprise a first received virtual subcarrier value (e.g., y<sub>0</sub>) and a second received virtual subcarrier value (e.g.,  $y_1$ ). The sequential processing may comprise processing the first received virtual subcarrier value to generate a decision as to a first one of the plurality of transmitted virtual subcarrier values (e.g.,  $\widehat{\underline{A}}_{n-1}^1$ ;  $\widehat{\underline{A}}_{n-1}^M$ ) using an estimate of interference present in the first received virtual subcarrier value (e.g.,  $f_0$ ) that is based on the second received virtual subcarrier value. The sequential processing may comprise processing the second received virtual subcarrier value to generate a decision as to a second one of the plurality of transmitted virtual subcarrier values (e.g.,  $\underline{\widehat{A}}_{n-1}^1$ :  $\underline{\widehat{A}}_{n-1}^M$ ) using an estimate of interference present in the second received virtual subcarrier value (e.g.,  $f_1$ ) that is based on the generated decision as to the first one of the plurality of transmitted virtual subcarrier values. The plurality of received virtual subcarrier values may comprise a third received virtual subcarrier value (e.g., y<sub>2</sub>). The estimate

10

of interference present in the second received virtual subcarrier value may be based on the third received virtual subcarrier value. The sequential processing may comprise processing the third received virtual subcarrier value to generate a decision as to a third one of the plurality of transmitted virtual subcarrier values (e.g.,  $\widehat{\underline{A}}_{n-1}^1 : \widehat{\underline{A}}_{n-1}^M$ ) using an estimate of interference present in the third received virtual subcarrier value (e.g., f<sub>3</sub>) that is based on the generated decision as to the first one of the plurality of transmitted virtual subcarrier values and on the generated decision as to the second one of the plurality of transmitted virtual subcarrier values. The sequential processing may comprise generating a plurality of branch metrics (e.g.,  $\mathrm{BM}_0^{-1,1}$ :  $\mathrm{BM}_{N-1}^{M,K}$ ), wherein each of the plurality of branch metrics is based on a corresponding one of the received virtual subcarrier values, a candidate vector generated by the sequence estimation circuitry, and the estimated inter-subcarrier interference. For each of the plurality of received virtual subcarrier values, the estimating of the intersubcarrier interference may considers all others of the received virtual subcarrier values or only a subset of all others of the plurality of received virtual subcarrier values. The subset of all others of the plurality of received virtual subcarrier values may correspond to those of the plurality of received virtual subcarrier values having a magnitude above a determined threshold.

The present method and/or system may be realized in hardware, software, or a combination of hardware and software. The present methods and/or systems may be realized in a centralized fashion in at least one computing system, or in a distributed fashion where different elements are spread across several interconnected computing systems. Any kind of computing system or other apparatus adapted for carrying out the methods described herein is suited. A typical combination of hardware and software may be a general-purpose computing system with a program or other code that, when being loaded and executed, controls the computing system such that it carries out the methods described herein. Another typical implementation may comprise an application specific integrated circuit or chip. Some implementations may comprise a non-transitory machine-readable (e.g., computer readable) medium (e.g., FLASH drive, optical disk, magnetic storage disk, or the like) having stored thereon one or more lines of code executable by a machine, thereby causing the machine to perform processes as described herein.

While the present method and/or system has been described with reference to certain implementations, it will be understood by those skilled in the art that various changes may be made and equivalents may be substituted without departing from the scope of the present method and/or system. In addition, many modifications may be made to adapt a particular situation or material to the teachings of the present disclosure without departing from its scope. Therefore, it is intended that the present method and/or system not be limited to the particular implementations disclosed, but that the present method and/or system will include all implementations falling within the scope of the appended claims.

What is claimed is:

1. A receiver comprising:

an analog front end circuit operable to receive a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;

nonlinear distortion modeling circuitry operable to generate a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:

- a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol; and said model of said nonlinear distortion is a digital clipping model; and circuitry operable to:
- iteratively calculate metrics based on said received 5 OFDM symbol and said model of nonlinear distor-

determine values of said symbols based on said metrics.

- 2. The receiver of claim 1, wherein said model of said nonlinear distortion is stored in memory of said receiver as a 10 mathematical and/or logical expression.
- 3. The receiver of claim 1, wherein said model of said nonlinear distortion is stored in memory of said receiver as a look-up table.
- 4. The receiver of claim 3, wherein said look-up table is 15 indexed based on a transmitted signal power parameter.
- 5. The receiver of claim 1, wherein said generation of said model is based on control information received from a transmitter from which said OFDM symbol originated.
- 6. The receiver of claim 5, wherein said control informa- 20 tion comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.
- 7. The receiver of claim 5, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.
- 8. The receiver of claim 5, wherein said control information is received during handshaking with said transmitter.
- 9. The receiver of claim 5, wherein said control information is received in a preamble of said OFDM symbol.
  - 10. A method comprising:

in a receiver:

- receiving, by an analog front end circuit, a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
- generating, by nonlinear distortion modeling circuitry, a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
  - a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol; and said model of said nonlinear distortion is a digital clipping model;
- iteratively calculating, by circuitry of said receiver, metrics based on said received OFDM symbol and said model of nonlinear distortion; and
- determining, by circuitry of said receiver, values of said symbols based on said metrics.
- 11. The method of claim 10, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.
- 12. The method of claim 10, wherein said model of said nonlinear distortion is stored in memory of said receiver as a
- 13. The method of claim 12, wherein said look-up table is indexed based on a transmitted signal power parameter.
- 14. The method of claim 10, wherein said generating said model is based on control information received from a transmitter from which said OFDM symbol originated.
- 15. The method of claim 14, wherein said control information comprises an identification of a type of nonlinear distor- 60 tion model best suited for use with said OFDM symbol.
- 16. The method of claim 14, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.
- 17. The method of claim 14, comprising receiving said 65 control information during handshaking with said transmit-

12

- 18. The method of claim 14, comprising receiving said control information in a preamble of said OFDM symbol.
  - 19. A receiver comprising:
  - an analog front end circuit operable to receive a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
  - nonlinear distortion modeling circuitry operable to generate a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
    - a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol;
    - said model of said nonlinear distortion is stored in memory of said receiver as a look-up table; and
    - said look-up table is indexed based on a transmitted signal power parameter; and

circuitry operable to:

iteratively calculate metrics based on said received OFDM symbol and said model of nonlinear distor-

determine values of said symbols based on said metrics.

- 20. The receiver of claim 19, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.
- 21. The receiver of claim 19, wherein said generation of said model is based on control information received from a transmitter from which said OFDM symbol originated.
- 22. The receiver of claim 21, wherein said control infor-30 mation comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.
  - 23. The receiver of claim 21, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.
  - 24. The receiver of claim 21, wherein said control information is received during handshaking with said transmitter.
  - 25. The receiver of claim 21, wherein said control information is received in a preamble of said OFDM symbol.
    - 26. A method comprising:

in a receiver:

- receiving, by an analog front end circuit, a nonlinearly distorted orthogonal frequency division multiplexed (OFDM) symbol that is a result of a plurality of symbols transmitted on a plurality of subcarriers;
- generating, by nonlinear distortion modeling circuitry, a model of nonlinear distortion introduced to said OFDM symbol by a transmitter, wherein:
  - a result of said nonlinear distortion is inter-subcarrier interference in said received OFDM symbol;
  - said model of said nonlinear distortion is stored in memory of said receiver as a look-up table; and
  - said look-up table is indexed based on a transmitted signal power parameter; and
- iteratively calculating, by circuitry of said receiver, metrics based on said received OFDM symbol and said model of nonlinear distortion; and
- determining, by circuitry of said receiver, values of said symbols based on said metrics.
- 27. The method of claim 26, wherein said model of said nonlinear distortion is stored in memory of said receiver as a mathematical and/or logical expression.
- 28. The method of claim 26, wherein said generating said model is based on control information received from a transmitter from which said OFDM symbol originated.
- 29. The method of claim 28, wherein said control information comprises an identification of a type of nonlinear distortion model best suited for use with said OFDM symbol.

- **30**. The method of claim **28**, wherein said control information comprises initial values for parameters of said model of said nonlinear distortion model.
- **31**. The method of claim **28**, comprising receiving said control information during handshaking with said transmit- 5 ter.
- **32**. The method of claim **28**, comprising receiving said control information in a preamble of said OFDM symbol.

\* \* \* \* \*