Office de la Propriété Intellectuelle du Canada
Un organisme d'Industrie Canada

Canadian Intellectual Property Office
An agency of Industry Canada

CA 2928431 A1 2015/04/09

(21) 2 928 431

(12) DEMANDE DE BREVET CANADIEN
CANADIAN PATENT APPLICATION

(13) A1

(86) **Date de dépôt PCT/PCT Filing Date:** 2014/09/26
(87) **Date publication PCT/PCT Publication Date:** 2015/04/09
(85) **Entrée phase nationale/National Entry:** 2016/03/15
(86) **N° demande PCT/PCT Application No.:** US 2014/057880
(87) **N° publication PCT/PCT Publication No.:** 2015/050796
(30) **Priorités/Priorities:** 2013/10/04 (US61/887,321); 2014/09/25 (US14/497,248)

(51) **Cl.Int./Int.Cl.** ***H04B 7/00*** (2006.01)

(71) **Demandeur/Applicant:**
LI, SOL MINGSO, US

(72) **Inventeur/Inventor:**
LI, SOL MINGSO, US

(74) **Agent:** MACPHERSON LESLIE & TYERMAN LLP

(54) **Titre : SYSTEMES ET PROCEDES POUR PROGRAMMER, COMMANDER ET SURVEILLER DES RESEAUX SANS FIL**
(54) **Title: SYSTEMS AND METHODS FOR PROGRAMMING, CONTROLLING AND MONITORING WIRELESS NETWORKS**




FIG. 1

(57) **Abrégé/Abstract:**
A system for programming, controlling and monitoring wireless networks enabling a wireless device (Dev) being utilized and integrated into car electronic control module or home (or business) alarm/security system. This system also presents a general

CA 2928431 A1 2015/04/09

(21) **2 928 431**

(13) **A1**

(57) **Abrégé(suite)/Abstract(continued):**
control (robotic) device, which controls general input and output functions, where plurality of cellular handsets, Internet devices can co-control, monitor, share and exchange information through the cellular, the Internet networks and other wire/wireless network.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau

(43) International Publication Date
9 April 2015 (09.04.2015)

WIPO | PCT

(10) International Publication Number
WO 2015/050796 A1

(51) International Patent Classification:
*H04B 7/00* (2006.01)

(21) International Application Number:
PCT/US2014/057880

(22) International Filing Date:
26 September 2014 (26.09.2014)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
61/887,321 4 October 2013 (04.10.2013) US
14/497,248 25 September 2014 (25.09.2014) US

(72) Inventor; and
(71) Applicant : **LI, Sol Mingso** [US/US]; 11046 Grenache Way, Elk Grove, CA 95624 (US).

(74) Agent: **LIM, Kang S.**; 2491 San Ramon Valley Blvd. #1-229, San Ramon, CA 94583 (US).

(81) Designated States *(unless otherwise indicated, for every kind of national protection available)*: AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States *(unless otherwise indicated, for every kind of regional protection available)*: ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

*[Continued on next page]*

(54) **Title**: SYSTEMS AND METHODS FOR PROGRAMMING, CONTROLLING AND MONITORING WIRELESS NETWORKS

(57) **Abstract**: A system for programming, controlling and monitoring wireless networks enabling a wireless device (Dev) being utilized and integrated into car electronic control module or home (or business) alarm/security system. This system also presents a general control (robotic) device, which controls general input and output functions, where plurality of cellular handsets, Internet devices can co-control, monitor, share and exchange information through the cellular, the Internet networks and other wire/wireless network.




FIG. 1

WO 2015/050796 A1

WO 2015/050796 A1

**Published**:

— *with international search report (Art. 21(3))*

# SYSTEMS AND METHODS FOR PROGRAMMING, CONTROLLING AND MONITORING WIRELESS NETWORKS

## BACKGROUND

[0001] The present invention is in the field of wireless communication, in particular cellular communication where a wireless or wired device or Dev (e.g., appliance) can communicate wirelessly in the wireless network, particularly cellular network, wireless internet network and short range communication (SRC) network. The PCMD (Program Control & Monitor Device) or Dev (e.g., appliance: - the inventor uses the term "Dev" for the description of this invention in the rest of this text, while the term "appliance" will be used in the claims that follow at the end of this text) communicates with a handset (e.g., cellular handset) or plurality of cellular handset, and the Dev can also be directed by any one of the handsets (e.g., mobile devices), which also can be a smart phone, tablet, tablet PC, laptop PC, iPad-like device, PDA (Personal Digital Assistant), any portable electronic device or mobile device, so that the Dev can be used to monitor and control its environment, associated equipment, or plurality of associated equipment, and alert when any unauthorized or unsafe events take place, so its owner(s) can take appropriate measure to deal with the situation.

[0002] The Dev can also allow the user to add (register) another handset, so the owner of said handset can have the same access to the vehicle/home control and monitor system, as the original user. The Dev also lets the user remove (deregister) a missing, stolen or no longer used handset.

[0003] The Dev can also allow the user hundreds or thousands of miles (kilometers) away from home, to program the handset of a friend or a relative to have access to the home security and monitor system, so said friend or relative can stay at his/her home for a programmable period of time.

[0004] The Dev can also allow the user to program the handset of the household help personnel (i.e., cleaning person) to have access only to a certain limited function of the home security and monitor system, such as: entry and exit on certain day(s) of the week and certain time. And such the entry and exit record can be created, stored and viewed by the user.

[0005] The Dev can also alert the user when someone attempts to register his/her handset into its control and monitor system so the user can be aware of such attempt and has the option to allow or not allow it to take place.

[0006] The Dev can also let the user locate the GPS location of another missing registered handset via his/her handset.

[0007] The Dev can also allow the user to have the liberty of choosing another cellular service provider by providing a fairly simple mechanism to which it can be easily activated and registered into the new network.

[0008] The Dev can also allow the user remotely to enter and retrieve data to and from the GPS, and inquire the vehicle current location through said GPS.

[0009] The Dev can also allow the driver to pay the toll collector (i.e., bridges, highways) electronically and the transaction account is stored in memory for later review.

[0010] The Dev can also allow the user to record and view remotely the driving habit of other drivers, such as: driving speed, and optionally alerts the user when such maximum speed limit happens: where, when and the duration. It also allows car rental, taxi, truck companies, and the like, to have the driving record of each vehicle transmitted and stored into the company's storage servers for later review.

[0011] The Dev can also alert the car owner when an authorized moving or entry in of his/her vehicle. It lets the owner know the location and time of where and when the event took place.

[0012] The Dev can also alert the driver who might be leaving a child or pet inside his/her parked vehicle, which is extremely dangerous, when the temperature is either very warm or very cold outside.

[0013] The Dev can also allow the user to program, control, and monitor his/her vehicle and its accessories remotely through his/her handset.

[0014] The Dev can also alert the emergency center in case of an accident such as: a sudden impact happens to the vehicle and/or its airbag is inflated. It also lets the driver communicate via the hands-free speaker and microphone with the emergency operator. The driver can also talk to a family member of his/hers (another registered handset), with the aid of the vehicle "dial and talk" button, in case his/her phone does not work or is not in his/her possession.

[0015] The Dev can also allow the user to use its control and monitor system to program, control and monitor his/her home security system, such as: turning on or off the alarm, monitoring and viewing the house entries and exits, viewing its motion sensing devices, and observing its interior and exterior surroundings remotely, through his/her handset.

[0016] The Dev can also alert the home owner when an authorized or illegal entry takes place in his/her own house or business premises. It lets the owner know the exact location within the house or business premises, and time when it happened.

[0017] The Dev can also alert the home owner when the monitor camera detects changes in its inputs, then transmits the video images to the owner for his/her viewing and decision.

[0018] The Dev can also communicate wired/wirelessly with one or plurality of wireless handsets/terminals, computers, servers, and the like so account information can be exchanged between the Dev and one or plurality of device, such as: handsets/terminals, servers/computers (wire/wireless) to facilitate the financial (or non-finance) transaction or any other needed financial (or non-finance) exchanges.

[0019] The Dev can also communicate wired/wirelessly with one or plurality of household appliance/equipment at home or on business premises, with the assistance of the software application downloaded from a plurality of server on the internet, or transferred from said appliances/equipments to the Dev, then from Dev passed to the handset; therefore allow the user(s) through the handset to control, program, monitor, view, record, play back, said appliances/equipments via the Dev.

[0020] The Dev can also be programmed, controlled, and then communicates wired/wirelessly with institutions, such as: a utility company to pass monthly user's utility usage information (i.e., electric / water / [heating & cooking gas] meter reading) so said company's computers can process and calculate the charges. The utility company then completes the payment automatically, or transmits said information to user's handset, so he/she using said handset is able to complete the transaction by paying online.

[0021] The Dev can also let the user speak to a visitor who rings the door bell by alerting him/her via his/her handset (wherever he/she might be), thus allowing their communication through the intercom (front door speaker and microphone). The uninvited visitor is not aware that the owner might not be at home, at the present moment.

[0022] The Dev can also let the home owner monitor the well-being of his/her pets (dogs), by communicating with the Integrated Smart Pet Door (its door, speakers and cameras), to let them out to the backyard multiple times a day and for specified times, such as: opening its door and playing the owner voice on its speakers, and enticing/commanding them back into the house by replaying the same speaker, then closing and locking the pet door.

[0023] The Dev can also be embedded into robotic device, which can be programmed and controlled remotely by the handset via the cellular network. Cellular communication is more ubiquitous, practical, in real-time and anywhere than the internet. The robotic device can be used in situations, such as: long distance medical surgery, remote rescue mission, remote firefighting and rescue, package delivering flying drones and the like.

[0024] The Dev can also be embedded into black boxes, shipping containers, and the like which can be programmed and controlled by the handset or a computer via the cellular network or satellite network (or a hybrid network consisting of cellular, wireless, wire, terrestrial and satellite) to communicate its locations to said handset or said computer.

[0025] Since the Dev is a wireless device and particularly a cellular device, it needs to be registered and activated into a cellular network, so the network computers/servers can recognize it, and allow it into their network, in order for it to communicate with other mobile devices. Unlike cellular phone handsets, tablets, personal assistants, and the like, it communicates with other handsets or wireless devices, when programmed to do so by one or more of its registered handsets. It does not communicate with everybody's cellular device, nor does it respond, when others try to communicate with it. In other words, it will ignore or will not answer uninvited calls/messages (with the exception is that during its activation/registration). The Dev receives, decodes and executes commands and data from registered handset(s), and does its tasks/functions as intended/programmed, and transmits back information and/or status to handset(s)/devices. Commands and data from the handset can be in packet(s), in binary or combination of binary and ASCII text format. Commands from the handset also preferably contain encoded handset phone number, and encrypted password, so the Dev can differentiate them from unwanted sources. If the phone number and the password match with the stored ones in the Dev's memory, the Dev will execute the commands accordingly. Data can also be in video and audio text format. Information and/or status from the Dev can be in packet(s), and in binary or combination of binary, ASCII, video, streaming video and audio, or streaming audio text format. The Dev also sends messages (messages in the present invention, besides being text messages can also in the form data messaging: IM, MMS "Multimedia Message Service", iMessages) to the handset(s), to alert the owner(s) when an event happens, or sends commands to App Server or Email Server to email owner's password to his/her email address for password recovery; as are known to those of ordinary skill in the art.

[0026] The Dev's function is to monitor and control its environment, communicate with other intended wireless devices; and in such a case where it functions as a security device, it has to be installed in a position, where it is not easily removed or disabled by any un-wanted person. It preferably is in the form of an embedded electronic module consisting of a microcontroller or CPU, IC (integrated chipset), EPLD, volatile and non-volatile memory (i.e., flash, RAM, SDRAM, EEPROM, ROM, SSD, storage media, …) storages (for software code, application programs, cellular account information, OS, …), antenna(s), cellular phone/wireless LAN chipset, SRC (Short Range Communication) interfaces, components (NFC, WI-FI, Bluetooth, USB, wireless radio frequency (RF) technology), and general I/Os. The module can be part of the automobile controlling circuitry when applies to a vehicle, or part of the home security system, when applies to the house, and part of the electronic circuitry when applies to a robotic device or a shipping container.

[0027] The Dev can obtain, store and run software applications from other devices/servers wirelessly. In the case of a vehicle, it also contains finance account application to facilitate the toll fee transaction, when bridge toll or road toll requires. It also contains features, which allow user to

locate the GPS location of other registered handset(s). It also allows user to control devices/appliances at home or on remote premises by having automatic add and remove functions, which it uses to discover/find out other controlled devices, so it can add in their functionality, or later on to remove them as commanded by user via the handset.

[0028] It also offers a general purpose control system where the main handset can register other handsets, which then together can communicate with the Dev to coordinate in monitoring and controlling what is going on within the Dev's environment, such as: a robotic/surgery/search- rescue robot, and monitoring what's going through the cameras and sensors and display the real time image on the terminal screen. Or the general purpose control system can be embedded into black boxes, shipping containers and the likes so they will be programmed by the handset or computer and their positions can then be tracked and monitored by said handset or said computer.

[0029] These three applications - car, home, and robotic/surgery/search-rescue operations/shipping containers/black boxes are for cited examples and do not mean that the Dev is restricted for these applications only.

[0030] In its lifetime, it most likely has several ownership changing hands, and thus it has to be easily activated and registered by its new owner, when change of ownership takes place. It also prevents an unauthorized one from activating or registering, and also alerts its owner(s) when such event happens. This makes it very easy for owner to switch to another service provider while still being active with the current provider by having the owner (through the handset) activated the Dev into the new service provider's network. After the activation to the new service provider is successfully done, the Dev deactivates itself from the previous network, and also transmits commands to other registered handset(s) which will update the Dev's new phone number.

[0031] Cellular phones/devices already exist in automobiles but their functions are quite limited. The main function of the current system is to take over the call, when the driver's cellular phone rings, and thus allows him/her to answer it, and communicate hands-free with the outside caller. Some other applications allow the owner of the car to remotely lock/unlock the car or start up its engine. Part of the reason, the car manufacturers have not yet provided the complete solution, as presented herein by the present invention, is how to come up with a mechanism, so that the cellular phone system (which is already inside the vehicle cellular embedded phone module, as in the case, where it takes over the function of the driver's cellular handset) can be programmed, controlled, monitored, and thus be able to communicate with the owner's handset, and execute its functions as cited herein in the present invention. Extending the hardware (microcontroller and cellular chipset) so it can interface with other devices in the car, such as: its GPS, its engine oil/fuel level, speedometer reading, door locks, car alarm, ignition system and the like, will not do much, if a clear and straight forward mechanism by which the car owner can monitor, program, and have it activated

easily with his/her chosen cellular service provider so it can communicate with his/her cellular phone, has not been implemented as presented herein by the present invention.

[0032] House monitoring security system presents less of a challenge, since it is a stationary device and can be wired and monitored by a home security company. The house monitoring system also requires a phone line (expensive and prone to being disabled because the phone line can be cut) and comes with a pretty high price tag such as monthly service fee. The monitoring can only be as good as the system and the security personnel who have the responsibility of overseeing so many stations. The system has to be installed by the home security company, and they do not provide much except calling and/or alerting the owner, when something happened or the house has been breached. The owner has no idea what happened, and neither does the alarm company until the police arrives, or the owner gets home or to the business office. Often, this can be due to a false alarm, such as: a curtain falling and causing the motion sensor to trip. There are also home installed security cameras connected online to the manufacturer's website, where an owner can create, and later logs into his/her account, and sees what the cameras see, and observes what is going on. It is a passive system, in other words, the user cannot program it in order of for him/her to be alerted when a certain condition happens.

[0033] The present invention allows owner 24 hour monitoring system. It goes straight to the user's handset (and his/her family members'), instead of to a third party not having the capacity to fully monitor all activity, due to the multiple terminals they need to monitor. It alerts when something happens and owner(s) can see, in real-time, what happens in his/her handset (where the Dev already transmitted the related information). Programming, controlling, and monitoring are all done through the handset, while the current paid system requires keypad located inside the house, plus a remote hand-held device just to turn the system on/off, when user is near the house within a close proximity. The present invention also extends beyond providing security of home alarm system. It allows its owner(s) means to control and monitor other household appliances/equipments, such as: heating/AC, cable/satellite TV, Garage opener, entry door lock, help-alert wearer, sprinkler control system, door bell and intercom, pet's daily needs, electric meter reading and transmitting the information to utility company, and plurality of others.

[0034] There exist already on the market kits offered, by companies such as: AutoAlarm Pro at autoalarmpro.com and Viper Start at viper.com to car owners, so they can either assemble themselves or by professional installers into their vehicles, so they can remotely program, monitor, and be alerted, when a certain event or condition happens to their vehicles. The above solutions are not very practical since they require the owner to pay for the extra equipment, its installation cost, and it requires modification to the vehicle structure which could void certain parts of the car manufacturer's warranty. It also would be costly, since it is not part of the complete package when the car was built, and has to be installed later.

[0035] US Patent Application US20110244846A1 and US20080057929A1 by Min: "Cell Phone with Remote Control System" mentioned a remote Automobile and Home Control System by a mobile phone, within a mobile communication network, a plurality of remote systems and a server. Min described the interconnection and integration of the plurality of systems of his invention, in terms of hardware, but never mentioned how the device in vehicle/home gets registered and activated so it can be connected to the network, and how it obtained its owner's phone number and the numbers of all other handsets, so it could alert the owner and family about the unexpected events.

[0036] It is therefore apparent that an urgent need exists for improved systems and methods for programming, controlling, and monitoring wireless networks.

## SUMMARY

[0037] This present invention presents mechanism involving a wireless device (Dev) being utilized and integrated into car and home (or business) electronic control and alarm/security monitor systems. This present invention also presents a general control (robotic) device, which controls general input, and output functions, where plurality of cellular handsets, internet devices can co-control, monitor, share and exchange information through the cellular, the internet networks, and other wire/wireless networks. These three cited examples should not be restricted as the only applications, since there are many applications already exist, or have yet to be invented, which can benefit from the present invention's application.

[0038] Before activation of the Dev, the owner should preferably get in touch with his/her chosen cellular service provider, to obtain the wireless service plan for the Dev and receives activation parameters (activation data), such as: activation password and user ID, account number, and/or any required information (so the service provider can associate it/them with the subscriber), in order for the Dev to be successfully activated into the service provider's network. The owner can go to one of the service provider's sales office, get in touch by phone, or go online to obtain the required information.

[0039] Activation is getting easier as cellular handsets are becoming more common devices. But even for a cellular phone user, when choosing or switching to a different service provider, he/she needs to be present in person at one of the service provider's sales office, since he/she has to choose a new handset, while at the same time having it activated and registered by the service provider sales personnel. To cut down time, manpower and improve efficiency and minimize user's waiting and frustration, service providers find ways to simplify and speed up the activation processes, by providing automatic activation of the device, such as: over the air (OTA) and on demand activation (ODA). OTA means the Dev can temporarily connect to the network during activation, and ODA

means the cellular service provider can allocate any available phone number to the Dev during activation (thus Dev and its SIM, or U/SIM, or ModSIM (define by the inventor as Modified SIM) like storage area does not have to be pre-programmed with any phone number). If the user chooses the same service provider, as the one of his/her handset, the same account number can be used as a group account, as commonly practiced by service providers. The first thing the user/owner needs to do is to activate the Dev and register his/her handset phone number (along with his/her account information) to the Dev, so the Dev can communicate with the handset after it has been successfully activated.

[0040] Before or during the activation, the user also has to pass a certain activation data to the Dev, (using the handset); meaning the handset has to contain associated software for it to do so (communication between the Dev and handset). Normal handset does not contain software application to run the Dev, so during the start of the activation process (after the Dev's activation button is pushed or voice activated command is excited), the Dev tries to communicates to the handset via SRC. If no response or wrong response coming back from the handset, the Dev sends a message or messages to the handset, informing the user of the website, from which to download the needed software. After the software has been downloaded to the handset, the Dev and handset can communicate properly via SRC, so information can be exchanged, and the activation data required by the Dev can also be passed from the handset to the Dev. During this time, the Dev's software can also be updated if necessary, and at the pleasure of the user since the website might inform user through the handset of the choice.

[0041] The Dev activation request can be in the form of SMS, USSD string or any other means, as are known to those of ordinary skill in the art. During and before activation, the Dev and the handset communicate with each other via near distance communication , such as: Bluetooth, wire/wireless USB, NFC, WI-FI, wireless radio frequency (RF) technology or any as defined by this inventor as SRC (Short Range Communication), as are known to those of ordinary skill in the art.

[0042] The Dev activation can be started by pushing a button by the side of enclosure (in the case of the home control and monitor system) or the push button located by the interior rear mirror similar to one to program the garage opener (in the case for the car control and monitor system). Most would refer to this as syncing devices, device sync, etc. Activating the Dev into a cellular network is quite similar to programming the garage opener, except the former requires several more steps.

[0043] The Dev's activation is carried out by the service provider's equipment(s) known by various names, such as: service provider servers/computers, Authentication Center, Home Location Registry, activation server/computer, provision server/computer, or any other systems associated with or provided by the service provider; and is mentioned in the present invention, as the Provision Application Storage Computer/Server (PASC) or Provision Server 114. The provision server can be

part of the Service Provider internal network system, or it can reside separately on the internet/cellular network, as are known to those of ordinary skill in the art.

[0044] Note that the various features of the present invention described above may be practiced alone or in combination. These and other features of the present invention will be described in more detail below, in the detailed description of the invention, and in conjunction with the following figures.

## BRIEF DESCRIPTION OF THE DRAWINGS

[0045] In order that the present invention may be more clearly ascertained, some embodiments will now be described, by way of example, with reference to the accompanying drawings, in which:

[0046] Fig. 1 shows the preferred exemplary networks the present invention where Dev 106 is operating in.

[0047] Fig. 2 shows a preferred example of one hardware functional block diagram of the present invention of Dev 106 in the automobile application.

[0048] Fig. 3 shows a preferred example of second variation of hardware functional block diagram of the present invention of Dev 106 in the home application.

[0049] Fig. 4 shows a preferred example of third variation of hardware functional block diagram of the present invention of Dev 106 in robotic application.

[0050] Fig. 5 shows a preferred example of one software block diagram of the present invention of Dev 106 in the auto application.

[0051] Fig. 6 shows a preferred example of second variation of software block diagram of the present invention of Dev 106 in the home application.

[0052] Fig. 7A/7B shows a preferred example of software block diagram on handset 102, related to the present invention in communication with Dev 106 in automobile / home application.

[0053] Fig. 8 shows a preferred example of the flow diagram of present invention, in the downloading of required activation and application program into handset 102.

[0054] Fig. 9/10 shows a preferred example of handset's screen displays of present invention, in the downloading of required activation and application program into handset 102, in the automobile/ home application.

[0055] Fig. 11/13 shows a preferred example of handset's screen displays of present invention, in running/executing the just downloaded auto/home application software.

[0056] Fig. 12/14 shows a preferred example of handset's screen displays of present invention, in having Dev 106 activated into a network in auto/home application.

[0057] Figures 15A-18 show preferred examples of present invention, in having Dev 106 activated into a network.

[0058] Fig. 19/20 shows a preferred example of handset's screen displays and a flow diagram, presenting the Dev 106's initial file with user information and the communication interaction of said handset and said Dev, relating to the present invention in the auto/home application.

[0059] Fig. 21A shows a preferred example of handset's screen displays of a registered handset 102, adding (e.g., registering) a new handset into the Dev 106. After being added, the new handset 102 signs in, and thus registered into the Dev 106, and is able to control the Dev as much as the registered handset 102, relating to the present invention.

[0060] Fig. 21B shows preferred examples of handset's screen displays of a registered handset 102, adding 2 new handsets one after another into the Dev 106. After being added, the first new handset 102 signs in, thus registered into the Dev 106, and is restricted into controlling a limited function of the Dev 106. Similarly, the second handset 102 also signs in temporarily and its ability to control the Dev 106 terminates on a certain programmable date, relating to the present invention.

[0061] Fig. 22 shows a preferred example of handset's screen displays and a flow diagram, presenting the interaction between the registered handset 102, the Dev 106, added handset 102 and the App Server 108 during the sign-in of the added handset, relating to the present invention.

[0062] Fig. 23 shows a preferred example of handset's screen displays of a registered handset 102, in removing (e.g., deregistering) another registered handset from the Dev 106, relating to the present invention.

[0063] Fig. 24A shows a preferred example of handset's screen display and flow chart, presenting the user password recovery application of Dev 106, relating to the present invention.

[0064] Fig. 24B shows a preferred example of handset's screen displays and a flow diagram, presenting the configuration (command) of Dev 106, relating to the present invention in the auto/home application.

[0065] Fig. 24C shows a preferred example of handset's screen displays, presenting the Auto/Home Device/Dev Information (command) of Dev 106, relating to the present invention.

[0066] Fig. 25 shows a preferred example of handset's screen displays and a flow diagram, presenting the Handset Registration of a new handset 102 to Dev 106, relating to the present invention in the auto/home application.

[0067] Fig. 26 shows a preferred example of a flow diagram of the Dev 106 during the Handset Registration process of a new handset, and the notified Handset's screen displaying the Dev's notification messages to a registered handset 102, relating to the present invention.

[0068] Fig. 27 shows a preferred example of handset's screen displays and a flow diagram, presenting the App Update between handset 102 and of Dev 106, relating to the present invention.

[0069] Fig. 28/29 shows a preferred example of handset's screen displays of present invention, in having the active Dev 106 activated into another network, in auto/home application (in a case where the user picks/switches cellular service to a new provider).

[0070] Fig. 30 shows a preferred example of handset's screen displays and flow diagram, presenting the Control and Monitor menu of Dev 106, relating to the present invention in the automobile application.

[0071] Fig. 31/32 shows preferred examples of handset's screen displays and a flow diagram, presenting the GPS entries of Dev 106, relating to the present invention in the auto application.

[0072] Fig. 33 shows a preferred example of handset's screen displays, presenting the toll fee account setup menu, and the account activity listing of Dev 106, relating to the present invention in the auto application.

[0073] Fig. 34 shows an example of a toll collecting station with vehicles containing Devs/appliances 106, relating to the present invention in the automobile application.

[0074] Fig. 35 shows a preferred example of a flow diagram, presenting the interaction of various devices during a toll collection, relating to the present invention in the automobile application.

[0075] Fig. 36 shows a preferred example of a flow chart presenting the programming flow of Dev 106 during a toll fee collection, relating to the present invention in the automobile application.

[0076] Fig. 37 shows a preferred example of handset's screen displays and flow diagram as well as a flow chart, presenting another toll fee account setup, and the interaction between various devices and program flow of Dev 106, during a toll fee collection, relating to the present invention in the auto application.

[0077] Fig. 38 shows a preferred example of handset's screen displays and a flow chart, presenting vehicle locator of Dev 106 relating to the present invention in the automobile application.

[0078] Fig. 39 shows a preferred example of handset's screen displays and flow chart, presenting an inquiry handset's (102) screen interactions with Dev 106, in locating a missing handset 102, relating to the present invention.

[0079] Fig. 40 shows a preferred example of handset's screen displays and flow diagram, presenting the Route Tracking and Speedo-Alert Program and Setup, the interaction of various devices. The displays also show the Route Tracking and Speedo-Alert listings of the Dev 106, relating to the present invention in the automobile application.

[0080] Fig. 41A shows a preferred example of handset's screen displays, presenting an alert from Dev 106 to handset 102, when an unauthorized event occurs, relating to the present invention in the automobile application.

[0081] Fig. 41B shows a preferred example of handset's screen displays, presenting an alert from Dev 106 to handset 102, when an unusual event occurs, relating to the present invention in the automobile application.

[0082] Fig. 42 shows a preferred example of handset's screen displays, presenting the engine status from Dev 106 to handset 102, relating to the present invention in the automobile application.

[0083] Fig. 43 shows a preferred example of handset's screen displays, presenting the configuration of home security alarm of Dev 106, relating to the present invention in the home application.

[0084] Fig. 44 shows a preferred example of handset's screen displays, presenting the status and monitoring of home alarm function of Dev 106, relating to the present invention in the home application.

[0085] Fig. 45 shows a preferred example of handset's screen displays, presenting the program and control of home alarm function of Dev 106, relating to the present invention in the home application.

[0086] Fig. 46 shows a preferred example of handset's screen displays, presenting an alert from Dev 106 to handset 102, when an unauthorized event occurs, relating to the present invention in the home application.

[0087] Fig. 47 shows a preferred example of handset's screen displays, presenting an alert from Dev 106 to handset 102, when a camera event takes place, relating to the present invention in the home application.

[0088] Figures 48-51 show preferred examples of handset's screen displays, flow charts and diagrams, presenting the house-hold appliance addition by Dev 106, relating to the present invention in the home application.

[0089] Fig. 52 shows preferred examples of handset's screen displays, presenting a house-hold appliance removal by Dev 106, relating to the present invention in the home application.

[0090] Figures 53-54 show preferred examples of the interaction between various devices (Dev 106, handset 102 and other house-hold appliances), when handset 102 communicates with Dev 106 and other appliances through the SRC (Short Range Communication), when at home or on the premises, relating to the present invention in the home application.

[0091] Fig. 55A shows preferred example of handset's screen displays, presenting the communication between handset 102 and Dev 106, when user uses his/her handset 102 to control and program (via the Dev 106) the entertainment system, relating to the present invention in the home application.

[0092] Fig. 55B shows preferred example of handset's screen displays, presenting the communication between handset 102 and Dev 106, when user uses his/her handset 102 to open or close (via the Dev 106) the garage opener(s), relating to the present invention in the home application.

[0093] Fig. 56A shows preferred example of handset's screen displays, presenting the communication between handset 102 and Dev 106, when user uses his/her handset 102 to control and program (via the Dev 106) the heating and air conditioning system, relating to the present invention in the home application .

[0094] Fig. 56B shows preferred examples of handset's screen displays, presenting the communication between handset 102 and Dev 106, when user uses his/her handset 102 to lock or unlock (via the Dev 106) the entry door, relating to the present invention in the home application.

[0095] Fig. 57 shows preferred examples of handset's screen displays, presenting the communication between handset 102 and Dev 106, when user uses his/her handset 102 to control and program (via the Dev 106) the landscaping sprinkler system, relating to the present invention in the home application.

[0096] Figures 58 and 59 show preferred examples of handset's screen displays and a flow diagram, presenting the communication between handset 102, utility company 5982, Dev 106 and Electric Meter 4884, of the user receiving the monthly invoice and paying the electricity bill, to the utility company 5982, relating to the present invention in the home application.

[0097] Fig. 60A shows a preferred example of handset's screen displays and a flow diagram, presenting the communication of handset 102 and Dev 106, in the monitoring and talking to the wearer of Help Alert device 4874, relating to the present invention in the home application.

[0098] Fig. 60B shows a preferred example of handset's screens and flow diagram, presenting the communication of user using the handset 102 to communicate to intercom 4886 via Dev 106, in answering the door bell that is rang by a visitor, relating to the present invention in the home application.

[0099] Fig. 61 shows a preferred example of handset's screen displays and a flow diagram, presenting the communication of handset 102 and Dev 106, when user uses his/her handset 102 to program, set up and control (via the Dev 106) the integrated smart pet door control system, relating to the present invention in the home application.

[00100] Fig. 62 shows a preferred example of the interaction of various devices, relating to the present invention in the robotic application.

## DETAILED DESCRIPTION

[00101] The present invention will now be described in detail with reference to several embodiments thereof as illustrated in the accompanying drawings. In the following description, numerous specific details are set forth in order to provide a thorough understanding of embodiments of the present invention. It will be apparent, however, to one skilled in the art, that embodiments may be practiced without some or all of these specific details. In other instances, well known process steps and/or structures have not been described in detail in order to not unnecessarily obscure the present invention and all changes and modifications that come within the spirit of the invention are desired to be protected. The features and advantages of embodiments may be better understood with reference to the drawings and discussions that follow. Further, the "present invention" or "invention" is intended to refer to "embodiment(s) of the present invention".

[00102] Aspects, features, and advantages of exemplary embodiments of the present invention will become better understood with regard to the following description, in connection with the accompanying drawing(s). It should be apparent to those skilled in the art, that the described embodiments of the present invention provided herein, are illustrative only and not limiting, having been presented by way of example only. Alternative features serving the same or similar purpose may replace all features disclosed in this description, unless expressly stated otherwise. Therefore, numerous other embodiments of the modifications thereof are contemplated as falling within the scope of the present invention as defined herein and equivalents thereto. Hence, use of absolute terms, such as: for example, "will", "will not", "shall", "shall not", "must", and "must not", are not

meant to limit the scope of the present invention, as the embodiments disclosed herein are merely exemplary.

[00103] It is also understood that when using terms, such as: handset/Dev making, calling, talking, answering, alerting, letting, allowing, using, programming, controlling, monitoring, activating, downloading, detecting, obtaining, containing, assuming, fetching, transferring, updating, configuring, adding, registering, removing, deregistering, comparing, operating, sending, selecting, starting, locking, unlocking, recording, turning on, turning off, playing back, transmitting, translating, passing, bypassing, receiving, displaying, executing, communicating, encoding, encapsulating, encrypting, decrypting, extracting, decoding, processing, verifying, navigating, exchanging, running, informing, copying, refer to actions and processes of the application programs in either handset 102 or Dev 106 (program code, OS, I/O drivers and the like and their interprocess-communication) residing in the micro-computer system's memory and executed by the CPU, in association with its supporting components i.e., cellular chipset, memory devices, peripheral I/O, transceivers, amplifiers, analog front-end, discrete/integrated ICs.

[00104] It is also understood that unless expressly stated otherwise (such as: "new handset", "non-registered handset", "normal handset", "regular handset"); "handset" and "registered handset" are used interchangeably herein, for ease of presentation by the inventor, since a handset has to be registered into the Dev, in order for both to communicate with each other, as principal goal of this invention.

[00105] The present invention is about a wireless device "Dev or appliance". In particular, Dev is a cellular device, which resides or is part of a module controlling and monitoring its surrounding environment. In the following examples, three are cited and it does not mean that the Dev is restricted for these applications only. Controlling and programming means the Dev needs to be commanded or programmed to do so and its communication is restricted to a selected number of devices (their phone numbers are stored in the Dev's memory). There exists a need for a system and method of how the Dev is to be activated to a network with the companionship of the user's handset (or similar device cited previously), thus allowing the Dev to be registered and recognized by the network (at a later time); the way how the Dev is configured, programmed, controlled by the user/handset; the way additional handset(s) is(are) added/registered into Dev's memory, thus allowing additional users to program and utilize the Dev; the way a no longer used (an obsolete) handset is removed (deregistered) from Dev's memory; the way the Dev monitors and reports status and events from its I/O; the way the Dev knows which selected handsets/devices to exchange the information; the way the Dev knows which email addresses so it can request App Server to send information to; the manner how the Dev is programmed by one or more handsets (or wireless/mobile devices) for its many functions; the way the Dev alerts one or more handsets (or wireless/mobile devices) when an un-expected or potentially catastrophic event occurs; the way the

Dev switches to SRC network in communication with a registered handset, when the said handset is within its SRC network range; the way additional house-hold appliances/equipments is discovered and connected, and their applications are copied or downloaded (via download links) and run, so that said appliances can be programmed and controlled by user's handset via the Dev itself through the cellular network, or directly to said appliances via SRC network when the handset is within said medium range; and the way household appliances/equipments is removed from the Dev and from a handset when said appliance/equipment is no longer in use.

[00106] In order for the above summaries come into realization, these following steps preferably are to be taken:

[00107] The network it operates in: The present invention is in the field of wireless communication, in particular cellular communication or a long distance wired/wireless network or GSM network, CDMA network, WCDMA network, TD-SCDMA network, NAMPS network and/or networks operating in accordance with any derivatives – GPRS, EDGE, CDMA2000, LTE, TD-LTE – based on GSM/EDGE and UMTS/HSPA, 3GPP, 4G LTE, among other similar and future medium, such as: satellite network or a hybrid network consisting many types of media - wire, wireless, terrestrial and satellite as are known to those of ordinary skill in the art). It also involves "Short Range Communication" SRC (Short Range Communication), such as: Bluetooth, wireless USB, NFC, WI-FI, wireless LAN, or any wireless radio frequency (RF) technology as are known to those of ordinary skill in the art.

[00108] During activation process the Dev communicates with the handset through SRC (Bluetooth, wireless USB and the like) since cellular communication to the Dev has not yet been established or has been discontinued. The handset on the other hand has both the cellular and internet connections and thus can download activation and application software from the App Server into its memory if needed and be also used to pass needed activation information from the server to the Dev through SRC media before and during the Dev activation process.

[00109] With activation and application software resident in their memory (after successful download to the handset or update to the Dev), the Dev starts the activation process through Over The Air Activation (OTA). During this process, the Dev can temporarily connect to the service provider or service provider's equipment known as provision server or activation server/computer in order to be activated. The activation process can be summarized in three phases: First, - activation key and pre-activation data from the service provider and user's phone number along with user account information (i.e., vehicle make/home address, account name, account number) to the activated device. Second, - activation request, activation key, device identifier(s) and/or activation data from the activated device to the cellular provider. Finally, - the activation/registration data and acknowledgement from the cellular provider sent back to the activated device.

[00110] The exchange of messages for the activation of the Dev with the provision server does not necessarily mean it is a direct communication. The messages can go through many nodes and each one of them transmits these messages to each other or one another, and finally to the provision server. For instance, the messages first go to one or a series of towers or Base Transceiver Stations (BTS), which transmit(s) the messages to the service provider or MSC/VLR (Mobile Switching Center / Visitor Location Register). Because these messages are activation messages, the MSC/VLR then transmits them to HLR/AuC (Home Location Register/Authentication Center) and DBS (Database Server for data verification and the Provision Server or OTA (Over The Air) Activation Processor for being processed / acknowledged / approved (Fig. 1 of US Patent Application Publication by Chatterjee et at US 2013/0012207 A1 Jan. 10, 2013 and Fig. 1 of US Patent by Larsson US 8,331,990 B2 Dec. 11, 2012). The numbers of transmission the activation messages go through, how, where, and by which equipment(s) they are being processed and routed, are up to the service provider's internal layout and design architecture, and are outside the scope of the present invention. During the Dev Activation, the present invention just says data sent/received by the Provision Server, processed by the Provision Server and acknowledged by the Provision Server as are known to those of ordinary skill in the art.

[00111] The present invention also supports plugged-in SIM card 270 (Fig. 2) preferably already activated; otherwise if the user has to activate it, then the SIM storage module is already available. Also, the benefit of the SIM card for the user is the convenience of continue usage when he/she gets a new handset without having to have reactivate it and allowing it to retain all the personal information, such as: phone directory, personal messages and the like while such information is not needed in the Dev, and the Dev functions much differently from a smart handset. The Dev only communicates with a limited numbers of handsets or mobile devices as directed by the registered phone, or one of the registered phones, and unlike the handset, the Dev is not easy for the user to have access to its SIM card. Its task is to allow users to program, control and monitor what users want it to do. It also can observe and inform of what is going in its surroundings, thus providing the option to alert the users as programmed/instructed.

[00112] Choosing the service provider – The user should have in possession preferably a smart phone in order to maximize the use of the present invention. The present invention protocol utilizes a mechanism in having Dev activated and then provisioned into the network (and it thus can register and be recognized/authenticated by the network); configured, programmed, controlled, and monitored its security tasks; set up account for paying tolls; discovered house-hold device for remote control and usage and all the various functions, which make it into a real, useful and very powerful device; also registers/removes (de-registers) other handsets or no longer used handsets into/from the Dev so they can/cannot control, program, monitor and will not be/(no longer be) alerted by the Dev just as the main handset.

[00113] The user applies and obtains the network service to the Dev with the service provider either in person, through phone call, or online. The user provides information or personal data (Name, address, employer's name and address, credit card [for payment deposit], handset phone number to the service provider for approval) and the service provider in turn provides user a set of information such account number (service plan, service rate…), user ID, activation password and activation phone number or activation internet link (address). The service provider then generates a one-time and time limited ticket (one-time limited ticket), token or identifier UTAID (Unique Temporary Activation Identifier preferably consists of: activation type/methodology, security/encryption key, activation key) based on user's account and personal information, and transmits it to user's handset. The handset in turn, passes the UTAID to the Dev, which separates out the activation key, and transmits it along with the Dev's own identifier(s) and other parameters to the service provider during activation. Through this activation key, the service provider/provision server verifies against the one stored in its database server, and thus can associate it with the subscriber ('s account) during activation. The UTAID also preferably contains a byte, indicating activation methodologies (activation types) of NAM, SIM (or USIM or ModSIM) or any customized activation type/ methodology, which when received by the Dev, will allow the Dev to activate itself into the service provider network accordingly (either using NAM, SIM, USIM, ModSIM or any customized activation type/methodology). The UTAID also preferably contains a mathematically algorithm or security/encryption key; and thus when it is received, decoded, stored and executed by the Dev, will encrypt said Dev's voice and data transmission in total privacy. The UTAID can also optionally contain an IMSI, which the Dev uses to transmit during activation instead of using its dummy IMSI, as are known to those of ordinary skill in the art.

[00114] Other parameters which the Dev preferably provides during activation such as: - ESN/ MEID/IMEI (Electronic Serial Number / Mobile Equipment Identifier / International Mobile Equipment Identifier), which the service provider associates with the device as in the case for NAM activation, have been pre-programmed into the Dev's NAM while the Dev will store its assigned phone number and the user's account information during the activation. - The dummy IMSI or IMSI (International Mobile Subscriber Identity decoded from the UTAID if it is provided) which the service provider associates with the subscriber (subscriber identification) and IMEI (International Mobile Station Equipment Identity) which the service provider associates with the device (device identification), as in the case for SIM activation, along with the user's account information, can be stored into the Dev's SIM memory storage module areas during the activation.

[00115] Preferably, the service provider can also associate the Dev ID Parameter (542/642 of Fig 5/6), such as: Dev's SN (serial number), model number, manufacturer name with the device, which are already reside in the Dev's memory, while the user's account information, the Dev's

assigned phone number, and the TMSI can be stored into the Dev's memory storage module during the activation, as in the case for ModSIM activation.

[00116] Pre-activation - Un-registered handset: A regular handset normally does not contain activation and application software. When the activation button is pushed (preferably located similar to where built-in garage door openers are in vehicles near the rear-view mirror, in case for vehicle application, or by the side of the enclosure in case of home system application), the Dev sends activation query via SRC media to the handset (un-registered to the Dev) and waits for the appropriate response. When no or incorrect response comes back from handset, the Dev assumes the handset does not contain appropriate application software, and sends a text message providing the link to the server location to the handset, informing user that he/she needs to download the activation and application software from the application server (App Sever) into the handset, in order to activate the Dev and run application software to communicate to the Dev. The user then proceeds to download the activation and application software. Before or during the downloading, the App Server preferably checks to see if the requested download version is up to date and if necessary (besides downloading the latest version of the software to the handset), the Dev also needs to be updated (downloaded) with the newest revision. If this is the case, the handset not only downloads its own activation and application software from the App Server, but also the Dev's application of the latest version to its memory storage, and then transmits it to the Dev; or the handset transmits to the Dev the App Update command with the download web link, making said Dev download said app update. Each cellular service provider in conjunction with the manufacturer of the Dev supplies their own activation and application software, and preferably the service provider also supports OTA (Over The Air) activation and ODA (On Demand Activation) activation.

[00117] Dev Activation: before the user puts the Dev into usage, the Dev needs to be activated so it can be recognized (when it registers into the network), and thus allowed into the service provider network; and can therefore call/send messages or receive calls/messages from other devices. A user uses his/her handset in activating the Dev – the pre-activation data (activation User ID 1226/1426, activation password 1228/1428) to obtain UTAID from the service provider can be inputted by the user from the handset's touch screen and keyboard 1235/1435. The user also provides separate information to the Dev, such as: the handset's phone number 1229/1429 (along with the account information) since the handset phone is the very first device the Dev will send message to, after it has been recognized and connected into the service provider's network. After activation, the Dev does a power-on reset 249 (Fig. 2/3/4) and then is registered and recognized by the network (in 1519A/1519B, 1619A/1619B, and 1719/1819 of Figures 15A/15B, 16A/16B and 17/19) as are known to those of ordinary skill in the art. Preferably the user has to acknowledge

back with an Ok message so the Dev knows its communication link to the handset has been accomplished and user can start the Dev's initialization/configuration process right after.

[00118] During its communication with the Dev, the handset's own phone number (in 1229/1429 of Fig. 12/14) is preferably encapsulated and its data encrypted (with the same security/encryption key provide in UTAID as mentioned earlier) in its command packet(s), since not all handset voice/message carries (or is preceded with) its phone number (also known as caller ID); and therefore the Dev, when it receives said packet(s), preferably decrypts the data, decapsulates (reverses the encapsulation) or separates the handset's phone number from the command packet(s). Next the Dev compares it with its stored handset numbers and only responds if there is a match. From then on, the Dev will communicate with the handset via cellular network 118 or cellular and internet networks. (The Dev can preferably automatically switch to communicate with the handset via SRC network 104 when the handset is within its near distance vicinity or SRC network range, as is known to those of ordinary skill in the art). The Dev then can be initialized or configured by the user via the handset with information, such as: password (for added security), user's email address (for password recovery) and stores them into its memory. The user then can program, control and monitor the Dev, from then on, for its intended tasks.

[00119] The user can also command using his/her handset preferably with account security password (for added protection) to add in additional handsets, which the Dev will be allowed to communicate and directed by these handsets to do its tasks in the service of said handset user(s).

[00120] Dev activation can be either

[00121] . Using NAM (Number Assignment Module)

[00122] NAM principal parameters are assigned phone number, MIN/IMSI, System ID (ESN/MEID/IMEI), Access Overload Class, Group ID Mark, Initial Paging Channel, Lock Code, local use flag, A/B system selection and MIN mark flag.

[00123] . Using SIM (Subscriber Identification Module)

[00124] SIM principal parameters are IMSI, TMSI (temporary IMSI), MSISDN, and Authentication key (Ki) and possibly ICCID and IMEI.

[00125] . Using ModSIM (Modified SIM)

[00126] ModSIM principal parameters are assigned phone number, TMSI, Dev ID parameters and Authentication key (Ki).

[00127] The method and system will be explained in detail later in the figures that follow. In no way it implies that these are the only three ways for the Dev to be activated as are known to those of ordinary skill in the art. When there is a need for new and better ways of activation, the Dev

will be able to accommodate the requirement with appropriate software, which can be downloaded as discussed in the present invention as technology changes and improves.

[00128] Activation and Application software resides both in the handset and in the Dev.

[00129] . Activation software is used and executed by both of them during Dev activation and between each one of them or of both of them with the provision server.

[00130] . Application software is used and executed when the handset and the Dev communicate with each other. The software is downloaded over the wireless network (cellular, internet) or updated software can also be downloaded to run newer and improved version. (These software programs are stored in servers which the present invention refers as Device Application Storage Server – App Server 108)

[00131] During the activation period, communication between the handset and the Dev is via SRC (Short Range Communication) which is either Bluetooth, wireless USB, NFC, WI-FI, wireless LAN, or any wireless radio frequency (RF) technology as are known to those of ordinary skill in the art.

[00132] After the Dev has been successfully activated, it then runs the initialization reset (or self-power recycle), and then registers into the network (and thus will be recognized by the service provider's network). From then on, the Dev runs and executes its application software to communicate with user's handset (as mentioned previously, the handset can also be a smart phone, tablet, tablet PC, laptop PC, iPad-like device, PDA (Personal Digital Assistant), any portable electronic device or mobile device). Correspondingly, the user uses his/her handset (which had its application software downloaded) to communicate with the Dev, by going and scrolling through the handset's respected screens and related icons, to program the Dev 106 and thus control, command, monitor and view its programmed tasks. The user will also be informed (alerted) through his/her handset by the Dev when certain unauthorized events take place.

[00133] Methods and systems for programming, controlling and monitoring the Dev are described below.

[00134] According to one aspect of the invention (Figures 8-10), the Dev starts out (after its activation button has been pushed) by transmitting (via SRC media) to user's handset, a text message with the App Server's URL instructing him/her to download the required activation and application software, from said site into the handset in order to activate the Dev, then runs and executes the downloaded application, in order for the handset to communicate with the Dev.

[00135] According to one aspect of the invention (Figures 11/13, 12/14, 15A-18), the user then starts the Dev activation process, after having applied and obtained the service account for the Dev from his/her cellular provider, by executing the Activate icon in Dev Facility Menu (Fig.

11/13). During or before the activation process which can be either NAM (Fig. 15A/15B), SIM (Fig. 16A/16B), ModSIM (Fig. 17/18) or any new or improved activation methodology, the handset receives from the service provider or provision server an UTAID (Unique Temporary Activation Identifier which contains activation key and other parameters), which it then passes (via SRC media) to the Dev. The Dev derives from UTAID, the activation key and transmits it along with its identifier(s) and other activation parameters to the provision server in order to complete the activation process (Figures 12/14, 15A-18). The Dev then registers and is thus recognized by the network, and from then on it is able to communicate with the handset and other registered mobile devices. During the activation process, the handset also transmits its phone number (automatically or entered by user) to the Dev, which later will send back (via cellular) to said handset, a confirmation message after it has been able to connect to the network. The handset (or any mobile device) phone number is preferably encoded, as part of the cellular (or other wireless long distance network) transmit packet(s) during the communication with the Dev, which only responds back if said phone number has been stored/recorded in its memory. As soon as the Dev receives the confirmation acknowledgement from the handset, it sends back an Initialization icon (1290/1490 in screen 1280/1480 of Fig. 12/14, containing its assigned phone number), which the user will execute to start his/her handset and the Dev initialization process (Fig. 19/20), allowing said handset to use said Dev's phone number in its communication with said Dev.

[00136] According to one aspect of the invention (Fig. 19/20), the user executes the just received Initialization icon (1290/1490 of Fig. 12/14) in his/her handset's inbox (screen 1280/1480 of Fig. 12/14) from the Dev 106, after said Dev 106 received a confirmation (executed by the Success icon 1276/1476 in screen 1270/1470 of Fig. 12/14) from the user. The handset 102 then navigates to screen 1902/2002 where the user can enter the required information. He/she then enters requested parameters, such as: the user's chosen account security password 1914/2014 and 1916/2016 (for added security), his/her handset own chosen password 1918/2018, email address (for password recovery), vehicle identification, home address, and emergency phone numbers (such as 911 in North America or other numbers depending on geographical and national locations), which all will be transmitted by the handset to the Dev for processing and storage. During the initialization, the handset also obtains and stores the Dev's phone number (1226) which is used by its application in their communication, as is known to those of ordinary skill in the art.

[00137] According to one aspect of the invention (Fig. 21A), a new handset 102 can be added (registered) into the Dev 106, by a registered handset 102; and will be able to control said Dev 106 just as said registered handset without any limitation.

[00138] According to one aspect of the invention (Fig. 21B), a new handset 102 can be added (registered) into the Dev 106, by a registered handset 102; and will have limited function in controlling said Dev 106.

[00139] According to one aspect of the invention (Fig. 22), the just newly added handset 102 receives from the Dev, the application download link and messages, instructing its owner to follow its instruction, in order for said handset to operate and communicate with the Dev, which will also notify the owner of the registering handset 102 when said newly handset completes its task.

[00140] According to one aspect of the invention (Fig. 23), a registered handset can be removed (deregistered) from the Dev by another registered handset.

[00141] According to one aspect of the invention (Fig. 24A), the Dev executes the password recovery process after the user failed to enter a matching password after three attempts. The Dev transmits the password recovery command to the Email Server, which will email the recovered password to said user.

[00142] According to one aspect of the invention (Fig. 24B), the user uses the handset to configure the Dev, in order to change, remove and/or update certain information, such as: vehicle license plate(s), house address, passwords, account number(s), email addresses, and emergency center phone numbers and the like.

[00143] According to one aspect of the invention (Fig. 24C), the user uses the handset to retrieve the device information from the Dev.

[00144] According to one aspect of the invention (Fig. 25), the user uses the new handset to register said handset into the Dev. The registration command requires the user to enter information, such as: the correct account security password, new handset's phone numbers (twice), handset passwords (twice), and Dev's phone number (which the new handset uses to transmit the command to, and will save Dev's phone number into its memory, when it receives the confirmation response to its registration from said Dev). The Dev verifies the account security password, it then checks to see both the handset phone number entries and its chosen password entries, each entered twice, are identical. If all the information is correct, the Dev will send the confirmation response and its device information to the handset; and from then on, they both can communicate with each other. During the registration process, the Dev will also transmit alert messages to other registered handset(s), if there are any in its memory, to inform the user(s) of such registration.

[00145] According to one aspect of the invention (Fig. 26), the user attempts to activate or register a new handset into the Dev, using the activation button 202 (of Fig. 2/3/4). If the Dev does not have any cellular service at the time, it will start the activation process as described previously. Otherwise the Dev will inform the registering handset user that the right application is needed to run the process. The user then either downloads the application online (if the handset does not contain the application), or run the application (if the handset contains said software). (The Dev also checks to see if it has any registered handset's phone number in its memory. If it does not contain any [meaning it has not been activated with the aid of a handset], a SIM card must be plugged into its

slot [270 in Fig. 2/3/4], it will allow the user to initialize by letting him/her to enter the security password for the account, the phone number of his/her registering handset and the chosen password for said handset). When the Dev receives the registration command and its data from the handset, as illustrated previously (in screen 2502 of Fig. 25), it verifies and processes the command and the data; it also alerts the other handset(s) of the attempted action (if there is any). During the registration process, if any alerted handset sends back a "Not Ok" message 2662, the registration is immediately aborted; or if the Dev receives an OK 2658, then the registration can start immediately without the account security password entries or verification. For added protection, the account security password is required for the user of the alerted handset before he/she is able to allow or not allow such process to take place.

[00146] According to one aspect of the invention (Fig. 27), the user uses the handset to update to the latest version of the application of the handset 102, and of the Dev 106. The handset obtains the Dev's current version app information from said Dev, and its latest version and the Dev's latest version from the App Server 108. When the user decides to update to the latest version, he/she just executes the update icon allowing the handset to receive the copy of the latest version app from the App Sever. The handset then sends the Dev's app update URL (or Dev's latest version app) along with update command to the Dev, and then the handset and the Dev, each updates its own latest version app (or alternatively, the handset 102 receives the Dev's update app from the App Server 108 and then transmits it to the Dev 106).

[00147] According to one aspect of the invention (Fig. 28/29), when it is time for the user to switch to another service provider, he/she goes through a similar activation process again, in order for the Dev 106 to be able to connect to the network of the new service provider. The user signs up and obtains a new UTAID from the new service provider, and preferably should (via his/her handset) activate the Dev 106 while it is still connecting to the current service provider network. The user therefore can do the activation anywhere (instead of having to be in the vicinity of the Dev 106 in order to communicate with it using the SRC media as the case in previous activation process in Figures 11/13 and 12/14)) since the handset still can communicate with the Dev 106 via the cellular network. As soon as the Dev 106 is activated and able to register, and then connected into the new network, its service to the previous network can be disconnected, and from then on the Dev 106 communicates with other handsets (mobile devices) in the new network. The Dev's device information file contains the same programmed data; in other words, there is no need for the user to reinitialize or reconfigure the Dev. Preferably the only difference is the new account number and possibly the Dev 106 has been assigned a different number. The handset 102 updates the Dev's phone number (regardless of it being a different number or not), and uses it from now on in its communication with the Dev 106. The Dev 106 also preferably sends command(s) to the other handset(s) so the user(s) of said handset(s) can also update the Dev's phone number.

[00148] According to one aspect of the invention (Fig. 30), the user uses the handset's Auto Control and Monitor menu to communicate with the Dev 106, in order to control the vehicle's electrical-mechanical components, such as: starting its ignition, locking/unlocking its doors, turning the alarm on/off, and the like, or to check the vehicle accessory status.

[00149] According to one aspect of the invention (Figures 31 and 32), the user uses the handset's GPS icon in the Auto Control and Monitor menu to communicate with the Dev 106, in order to enter the location address inputs into the vehicle GPS device, or retrieve the stored entries from GPS memory.

[00150] According to one aspect of the invention (Figures 33-37), the user uses the handset's Toll Fee Pay Account menu to communicate with the Dev 106, in order to set up the toll fee payment account on said Dev which will process, pay the required fee when demanded and record the transaction in its memory. The Dev 106 also transmits the transaction activities to the handset when the corresponding icon is executed on said handset 102.

[00151] According to one aspect of the invention (Fig. 38), the user uses the handset's vehicle Locator icon in the Control and Monitor menu to communicate with the Dev 106, in order to locate the current location of the vehicle. The Dev 106 then translates and transmits the current location command to the GPS, and passes the current GPS location information back to the handset 102.

[00152] According to one aspect of the invention (Fig. 39), the user uses his/her handset' Handset Locator icon in the Control and Monitor menu to communicate with the Dev106, in locating a missing registered handset. The Dev 106 transmits back its listed registered handsets 102, which the user can choose from, in order for the Dev 106 to locate said handset 102.

[00153] According to one aspect of the invention (Fig. 40), the user uses the handset's Route Tracking and Speedo- Alert Program/Status icons in the Auto Control and Monitor menu to communicate with the Dev 106, in order to set up a certain speed limit recording history with the alert option and/or vehicle's route tracking history. The Dev 106 then interacts with the speedometer and the GPS to build up the history of when and where, the speed limit takes place, or just plain route tracking (where its track sampling time is programmable in minute time) which user can review later on with said handset. The user can also fill in, if needed, the network server destination for the off-Dev storage.

[00154] According to one aspect of the invention (Fig. 41A), the Dev 106 transmits a message preferably with video (or streaming video) data to the user's handset informing him/her that a certain event has happened to his/her vehicle, such as: a break-in. The user will be able to know the nature of the event, time and date and location, the event took place, and the registered handset phone numbers which have been alerted.

[00155] According to one aspect of the invention (Fig. 41B), the Dev 106 transmits a message preferably with video (or streaming video) data to the user's handset informing him/her that a certain event has happened to his/her vehicle, such as: a child or pet might have been left inside said parked vehicle. The user will be able to view the accompanied videos, and then takes appropriate actions with the handset, which transmits them to the Dev 106, such as: ignoring because of false alarm or confirming it by either taking one of a combination of these immediate and temporary measures: unlock the car door, lower down car windows, sound the horn, turn on the car alarm, turn heat or air on, flash a light, call emergency center, or that the driver in on his/her way to the car.

[00156] According to one aspect of the invention (Fig. 42), the user uses the handset's Engine Status icon in the Auto App menu to communicate with the Dev 106, in order to view the vehicle engine status remotely.

[00157] According to one aspect of the invention (Fig. 43), the user uses the handset's Alarm Configure icon in the Home Control and Monitor menu to communicate with the Dev 106, in order to configure the alarm I/O, such as: door and window entries, motion detectors, alarm speakers and horns, and cameras in more descriptive terms (instead of plain numeric values), such as: Door/Window Entry #1 into BR2 (bedroom #2 window), Motion input #1 into Hall (motion detector), Camera #5 into Back yard (camera), when he/she is at home, away, or far away from home.

[00158] According to one aspect of the invention (Fig. 44), the user uses the handset's Status/Monitor icon in the Home Control and Monitor menu to communicate with the Dev 106, in order to monitor and view various windows, motion detectors and cameras in the house, when he/she is at home, away, or far away from home.

[00159] According to one aspect of the invention (Fig. 45), the user uses the handset's Program/Control icon in the Home Security menu to communicate with the Dev 106, in order to program and arm the house alarm system, when he/she is at home, away, or far away from home.

[00160] According to one aspect of the invention (Fig. 46), the Dev 106 transmits a message, preferably with video (or streaming video) data, to the user's handset informing him/her a certain event has happened to his/her house, such as: a break-in. The user then can view and find out through the handset where and when (which entries and time) the event took place, when he/she is away, or far away from home.

[00161] According to one aspect of the invention (Fig. 47), the Dev 106 transmits a message, preferably with video (or streaming video) data, to the user's handset informing him/her a certain event has happened in the camera monitoring device, such as: detection of a moving object outside his/her house, when the owner is at home, away, or far away from home.

[00162] According to one aspect of the invention (Figures 48-51), the user uses the handset's Appliance Add icon in the Home Appliances menu to communicate with the Dev 106, in order to discover or find out the presence of house-hold devices. The handset then has them connected and transferred their software applications to the Dev 106, and then to the handset; or have them provided the URLs (web links), which allow the user to download the software applications to his/her handset which also transmit them to the Dev, or the Dev can download automatically the app from said URLs. The user can then run these apps to control these said devices remotely, when he/she is at home, away, or far away from home.

[00163] According to one aspect of the invention (Fig. 52), the user uses the handset's Appliance Remove icon in the Home Appliances menu to communicate with the Dev 106, in order to remove a certain house-hold device or devices which are no longer in use, when he/she is at home, away, or far away from home.

[00164] According to one aspect of the invention (Fig. 53), both the user's handset 102 and the Dev 106 communicate with household devices via the SRC networks, while he/she is at home.

[00165] According to one aspect of the invention (Fig. 54), the user's handset 102 communicates with both the Dev 106 and the household devices via the SRC network, while he/she is at home (the communication between the Dev and the household appliances is maintained but not active because of the presence of the handset, meaning the Dev will not pass the handset's commands to said household appliances).

[00166] According to one aspect of the invention (Fig. 55A), the user uses the handset's Cable Box/TV icon in the Home Appliances menu to communicate with the Dev 106, in order to program, record, and view the cable and television programs, when he/she is at home, away, or far away from home.

[00167] According to one aspect of the invention (Fig. 55B), the user uses the handset's Garage Opener icon in the Home Appliances menu or in the Home App menu to communicate with the Dev 106, in order to open or close the garage door(s). The Dev also lets user know if the garage is closed or opened, when he/she is at home, away, or far away from home.

[00168] According to one aspect of the invention (Fig. 56A), the user uses the handset's Heat/AC icon in the Home Appliances menu to communicate with the Dev 106, in order to program the central air unit, such as: when and at what degree to turn it on and at what degree to turn it off, to control in real-time, and view its status at any moment, when he/she is at home, away, or far away from home.

[00169] According to one aspect of the invention (Fig. 56B), the user uses the handset's Door Lock icon in the Home Appliances menu or in the Home App menu to communicate with the

Dev 106, in order to lock or unlock the main door entry, when he/she is at home, away, or far away from home.

[00170] According to one aspect of the invention (Fig. 57), the user uses the handset's Sprinkler icon in the Home Appliances menu to communicate with the Dev 106, in order to program the landscape sprinkler, such as: on which day(s) of the week, at what time and for how long, and which station(s) to turn the sprinkler system on to water the landscape (garden, and house plants and the like). The sprinkler can also be turned on or off at any moment by the user via the handset at home, away, or far away from home.

[00171] According to one aspect of the invention (Figures 58 and 59), the user uses the handset's Electric Meter icon in the Home Appliances menu to communicate with the Dev 106, in order to set up the monthly electricity payment account, so the Dev 106 will acquire the electricity meter reading every month, and then transmits it to the utility company which will receive the payment automatically or bill the user who will then pay it via his/her handset, when he/she is at home, away, or far away from home.

[00172] According to one aspect of the invention (Fig. 60A), the user uses the handset's Help Alert icon in the Home Appliances menu to communicate with the Dev 106, in order to monitor and communicate with the wearer of the Help Alert device via his/her handset, when he/she is far away from the premises.

[00173] According to one aspect of the invention (Fig. 60B), the user uses the handset's Door Bell & Intercom icon in the Home Appliances menu to communicate with the Dev 106, which connects to the intercom letting the user answer (via the handset) when someone rings the door bell. This feature allows the owner away from home to answer the door just like being at home.

[00174] According to one aspect of the invention (Fig. 61), the user uses the handset's Smart Pet Door icon in the Home Appliances menu to communicate with the Dev 106, in order to program and set up the Smart Pet Door system for the pets' daily needs, and to control its components in real-time, when he/she is at home, away, or far away from home.

[00175] According to one aspect of the invention (Fig. 62), Dev 106 integrating in the robotic application, allows a plurality of users to program, control, direct, command, and monitor its functions in its surrounding environment, while at the same time, be informed of any expected and unexpected events relating to its application.

[00176] Fig. 1 illustrates a preferred example of embodiment 100 of the present invention. It presents the wireless network 118 where all devices have access to and use to communicate with one another. Network 118 is commonly known as a cellular network or the type of wireless network (such as wide area cellular network – GSM network, CDMA network, WCDMA network, TD-

SCDMA network, NAMPS network and/or networks operating in accordance with any derivatives – GPRS, EDGE, CDMA2000, LTE, TD-LTE – based on GSM/EDGE and UMTS/HSPA, 3GPP, 4G LTE among other similar and future medium, such as: satellite network or a hybrid network consisting many types of media - wire, wireless, terrestrial and satellite) provided by the service provider(s). The invented device/appliance or Dev (for short) 106 is the present invention communicating with the handset 102 which also can be a smart phone, tablet PC, laptop PC, iPad-like device, PDA (Personal Digital Assistant), or any portable, mobile electronic device through SRC media 104 (Short Range Communication) which it uses during an activation process or when they are within said SRC network range. The Dev 106 is shown either residing in an automobile 120, a residential house (or business premises) 122 or a general robotic device (equipment) 124. The Cellular Service Provider or Service Provider 112 is the provider of cellular communication service to the Dev 106 thus recognizing and allowing it to communicate with other cellular devices through wireless network 118. Before the Service Provider 112 can recognize the Dev 106, the Dev 106 has to be activated. The activation process involves the exchanges of pre-usage/pre-programmed and/or specific unique issued information between the Dev 106 and the Service Provider 112 itself or a combination of its network computers/servers [such as MSC (Message Switching Center), VLR (Visitor Location Register), HLR (Home Location Register), AuC (Authenticity Center), Activation Server, and other backend systems as are known to those of ordinary skill in the art] , which are proprietary in nature to the service provider but known in this invention simply as Provision Server 114. The Dev 106 contains some of the parameters for activation in its internal memory storage. Some of them the Dev 106 obtained by downloading from the service provider 112 and/or the Provision Server 114 via the handset 102. The App Server 108 can be either provided by the Dev 106 manufacturer (not shown in Fig. 1) and/or by the Service Provider 112 operator (also not shown in Fig. 1 in cooperation with the Dev 106 manufacturer). The App Server 108 in latter case can be part of the Service Provider 112 intranet network just as shown in the backend connection 120 between the Provision Server 114 and the Service Provider 112.

[00177] Fig. 1 also shows BTS (Base Transceiver Stations) or The Towers 110 (as illustration herein, the communication between the various devices going to the Service Provider 112 but actually goes through one or more Towers 110 first). The information from one device goes through one or more towers 110 and then is transmitted to one of the regional Service Provider 112. The Service Provider 112 then again passes said information to one or more towers 110 where it finally reaches the destination server/computer.

[00178] All these components, such as: Towers 110, Service Provider 112, and Provision Server 114, and the like can also be referred to as Public Land Mobile Network (PLMN). So when Provision Server 114 or Service Provider 112 is referred to in the herein examples, it also involves

the function of the whole PLMN with the main task falling into said mentioned component (Provision Server or Service Provider). The Email Server 116 acts as an email server to email password recovery to the user's email address, when requested by the Dev 106 in case the user has problems entering the required password.

[00179] Figures 2- 4 illustrate preferred examples of embodiments 200, 300 and 400 of the present invention in terms of hardware block diagrams as are known to those of ordinary skill in the art. They present the Dev 106 integrating and interfacing into the car control and monitor system as represented by illustrations 200 in Fig. 2, the house control and monitor system 300 in Fig. 3, and the general robotic control and monitor system 400 in Fig. 4. The principle components of the Dev 106 are the CPU 248, its associated cellular phone circuitry 246, and its RF interface circuitry (RF Transceiver 244, RF Amp 234 and Antenna 232). An example of the CPU and its associated circuitry, or chipset is X-GOLD 101 single-chip by Intel Corp., NEON Cortex-A9 licensed by ARM, and others, such as: Qualcomm and many, as are known to those of ordinary skill in the art.

[00180] Block diagrams 200, 300 and 400 also include the wireless LAN controllers (which may also referred to as Wi-Fi or WIFI communication over one of more wireless local area network WLAN) and its associate circuitry 256, 254, 252 and 242, the volatile and non-volatile memory storage 264 (flash, SDRAM, RAM, EEPROM, …), clock system 236, I/O interface 238/338/438, Real Time Clock 240 and power and battery backup 250. They also include one or more of the SRC (Short Range Communication) devices, such as: NFC 258, Bluetooth 260, wireless/wire USB 262, and other wireless radio frequency (RF) technology (not shown). It also contains non-volatile memory storage areas for NAM 268, SIM 266, ModSIM 266A parameter storage, and slot 270 for SIM card. The NAM 268, SIM 266 and ModSIM parameter storages preferably can be incorporated into the Memory Storage 264, which is also storage for program code, application software, data, and OS firmware as are known by those of ordinary skill in the art. Embodiment 200 includes the Hands-free Speaker, Microphone, and voice activated circuitry 230 which can also reside in embodiments 300 and 400. The Hands-free Speaker, Microphone, and voice activated circuitry application 532 can also reside in embodiment 600 while embodiment 400 offers a plurality of cellular handset interface circuitry 439, 436, 434, and 432.

[00181] Fig. 2 also includes some inputs and outputs (I/O) which are very useful and life-saving, such as when the driver runs into an accident, where he/she may not have the mental or physical capability to take immediate actions to deal with the circumstances. The Input Dial & Talk button 204 offers a convenient way, when the driver does not happen to have the handset in his/her possession, to get in touch with a family member (registered handset 102) when the occasion requires.

[00182] - Air Bag (226): In the case when there is an accident, which caused big impact to the car and/or inflated its Air Bag (226 in Fig. 2), the Dev 106 transmits alert emergency messages

with the vehicle location to the Emergency Center (not shown) and to registered handsets at least one time (i.e., 911 in US and Canada, China 110 or similarly depending on national and geographical locations as mentioned earlier in the text). The Dev 106 also dials Emergency Center, and turns on the Hands-Free Microphone and Speaker (230 in Fig. 2), so the driver can communicate with the Emergency Center operator. If no response comes back from the Emergency Center within a short period of time (i.e., one minute or two; in other words there is possibly no cellular service available at the accident location), the Dev 106 will transmit emergency messages with the vehicle location to the Emergency Center (not shown) via satellite network if programmed to do so (not shown) or via a hybrid network consisting many types of media - wire, wireless, terrestrial and satellite as are known to those of ordinary skill in the art. If the Dev 106 still gets no response, after its message transmission, from the Emergency Center, whatsoever, it will transmit a satellite emergency command to the GPS (3182 in Fig. 31), which in turn preferably transmits it to the Emergency Center, along with its GPS location (not shown) via satellite.

[00183] - Emergency Button (229a): Preferably located inside the vehicle, when pushed (multiple times in a row) will transmit an electrical signal to the Dev 106 which will transmit the emergency messages with the current GPS location to the other registered handsets 102 and the Emergency Center (not shown). The Dev 106 also dials the Emergency Center and turns on the Hands-Free Microphone and Speaker (230) to allow the driver of the vehicle to communicate with the Emergency Center personnel. The Dev 106 also dials a registered handset and (if it answers) connects to the Hands-Free Microphone and Speaker (230) to allow the driver of the vehicle to communicate with the user (i.e.; family member) of said handset.

[00184] – Dial & Talk Button (204): Also allows the driver of the vehicle to communicate with a registered handset 102 user in case he/she does not have the handset in his/her possession or said handset does not function properly at the time.

[00185] Figures 2 and 3 also illustrate the communication between the handset 102A and the Dev 106 via the SRC network 104, such as: during the activation process (Figures 8, 9, 11/13, 12/14), or when they are within their short range communication (SRC) medium, and via the cellular (or other wireless) network 118 during normal operation.

[00186] Figures 5 and 6 illustrate preferred examples of embodiments 500 and 600 of the present invention in terms of software block diagrams as are known to those of ordinary skill in the art. Illustration 502 represents the Auto Application and illustration 602 represents the Home Application. Each of these two preferably contains two principle software blocks:

[00187] - Dev Base 552/652 along with core OS 540 (such as iOS, Google's Android mobile OS) forms the basic kernel. The Dev base 552/652 preferably consists of the Dev ID Parameter 542/642 (contains manufacturer name and production date, S/N number, model number,

plant location), the Download layer/module 544 (used to download the updated version of Op App module 506/606 when the current version of its software application needs to be updated), the Cellular and Wireless LAN layer/module 546 (cellular and wireless LAN device driver and management module), the NAM (Name Assignment Module) 548/648 and the SIM (Subscriber Identity Module) 550/650 which contain all NAM and SIM related information parameters, such as: ESN, IMSI, etc.

[00188] - Dev App 504/604 runs the application software allowing the Dev 106 to communicate with other wireless devices - decode and execute the program/control commands and the status/monitor commands received from the handset 102. The Dev App 504/604 preferably consists of two modules:

[00189] - Handset Information module 560 (common for both automobile and home applications - consists of the handset 102 information such as: user's handset phone number, account number, passwords, other handsets' phone numbers, email addresses, etc.).

[00190] - Op App module 506/606 preferably consists of the Command Communication layer/module 508/608 which receives the commands from and transmits the statuses to the handset 102, the Status and Monitor layer/module 510/610 which decodes and executes the status and monitor commands from the handset 102, the Event layer/module 512/612 which detects the changes in Dev's I/O and events, the Program and Control layer/module 518/618 which decodes and executes the program and control commands from the handset 102, the Dev Activate/De-activate layer/module 514/614 which decodes and executes the activation/de-activation commands from the handset 102, the Handset App Update layer/module 516/616 which decodes and executes the handset information update commands from the handset 102, the Handset Registration layer/module 522/622 which decodes and executes the handset registration commands from the handset 102, the Dev Configure layer/module 524/624 which decodes and executes the Dev configuration commands from the handset 102, the Add and Remove layer/module 526/626 which decodes and executes the add and remove handsets and parameters commands from the handset 102, the Car/Home (business) Dev Info 520/620 which fetches the Dev information to the handset 102, the Auto/Home Alarm Application module 562/662 which executes and runs the alarm application, the Auto/Home App Download 564/664 which decodes and executes the application download from the handset 102, the Handset Locating layer/module 534/634 which search for a missing registered handset, and the I/O Management layer/module 528/628 which allows the Dev 106 communicate with the I/O peripherals 201/301/401.

[00191] Car Op App module 506 and Home Op App module 606 preferably contain some other modules which are only applicable to each own functions. In the case of the car application, the Op App module 506 preferably contains the Account Payment setup layer/module 530, the Hands-free Audio I/O layer 532 (used for voice triggered Dev activation) that allows the Dev 106 to

communicate in hands-free mode, with the driver during toll collector fee transaction or commands the Dev 106 to dial and connect to an emergency center, thus allowing the driver to communicate in hands-free with the emergency personnel. In the case of the home application, the module 606 preferably contains the Home Appliance layer/module 630 which discovers the household appliances/equipments, downloads their online applications or provides their download links to handset 102); then stores, executes the HH App 632 as commanded by the handset 102 (Household Appliances icon 1344 Fig. 13) in communication with a plurality of household appliances/equipments.

[00192] A pre-programmed version of Op App 506/606 already resides in the Dev's memory and an updated version of it can be downloaded during the activation 950/1050 (Fig. 9/10) if required or by the user executing the Handset and Dev App Update icon 1164/1364 (Fig. 11/13)

[00193] Dev App 504/604 preferably contains the communication and application functions interacting with the resident (or on-device) functions and the OS kernel which provides a uniform interface to the CPU and its environment. The kernel manages the CPU resource by allocating task (RTOS) for each function, such as: Command Communication layer/module, IPC (Inter-Process Communication between multiple tasks or Process-Cooperation), memory management, file system (FS), I/O device management, network management (cellular, LAN and other wireless networks), and associated drivers (all are not shown).

[00194] Figures 7A and 7B illustrate preferred examples of embodiments 700A and 700B of the present invention in terms of software block diagrams residing on the registered handset(s) 102. Illustration 702A is the counter part of 502 in Fig. 5 and illustration 702B is the counter part of 602 in Fig. 6 as are known to those of ordinary skill in the art.

[00195] Both the Handset Application 704A of the handset 102 in Fig. 7A and the Dev App 504 of the Dev 106 in Fig. 5 are used to communicate to each another. For each module in the Operation layer 706A of Fig. 7A, there is an equivalent counterpart module in the Op App 506 of Fig. 5. An example is when the user wants to see the car device information. The user browses through the handset 102 to the Auto Dev Facility Menu 1150 which preferably contains the Dev Info icon 1166, which when executed, makes the handset 102 navigate to the Auto Device Information screen 2410C (Fig. 24C). All the actions/functions have been preferably decoded and executed by the Command Communication layer/module 708A and the Car Dev Information module 714A; which also communicate with other resident (on-device) modules residing on the handset 102 including displaying screens by the "screen display module" (not shown) and sending messages/commands to the Dev 106, and receiving messages/responses from the Dev 106 through the "transceiver module" (not shown) as are known to those of ordinary skill in the art.

[00196] The handset 102 transmits the "car Dev information" message/command to the Dev 106. The command/message is then received and decoded by the Command Communication layer/module 508 and executed by the Car Dev Info module 520 of Dev 106 in Fig. 5. The Dev 106 then transmits the requested data back to the handset 102 which receives and displays the information as shown on the Auto Device Information screen 2410C (Fig. 24C).

[00197] Similarly, both the Handset Application 704B of the handset 102 in Fig. 7B and the Dev Application 604 of Dev 106 in Fig. 6 are used to communicate with each another. For each module in the Operation layer 706B of Fig. 7B, there is an equivalent counterpart module in the Op App 606 of Fig. 6.

[00198] An example is when an unauthorized entry/break-in to the house as indicated in illustration 4632 through Bedroom 2 (BR2 4638) in Fig. 46 (one of the inputs of the Entry detections 308 in Fig. 3) produces an alarm which sends a signal to the Dev 106 and is handled by the Event layer/module 612 in Fig. 6. The Event layer/module 612 decodes the break-in, which is one of the inputs of the Entry detections 308 Fig. 3 into BR2 (Bed Room 2) window and passes the information to the Command Communication layer/module 608 Fig. 6 which transmits it along with a message (or messages) to the handset 102 alerting its user of an break-in event. At handset 102, the Command Communication layer/module (708B in Fig. 7B) receives and decodes the message and passes it and its data to the Event layer/module 716B which executes and retains data in its memory ready to be displayed (as indicated by illustrations 4632, 4652 and 4660 in Fig. 46) when the user views the displayed message(s) after navigating through several display screens (as indicated by illustrations 4602, 4606, 4612 and 4622 in Fig. 46) as are known by those of skill in the art.

[00199] Figures 8, 9 and 10 illustrate preferred examples of embodiments 800, 900, and 1000 of the present invention in the handset 102 having the activation and application software downloaded into its memory storage from the App Server 108.

[00200] Before being able to communicate with the Dev 106, the handset 102 has to have compatible software application in its Memory/Storage area 264 Fig. 2/3/4. While the user attempts to have the Dev 106 activated by pushing the activation button (located somewhere near the garage button on the lower side of the interior rear view mirror, in the case of the automobile application; or using the voice activated circuitry (230 of Fig. 2) while inside the car; or an activation button inside the enclosure in the case of the home application), the newly Dev 106 (has not been activated nor registered) sends the activation software request message/command step 802 to the handset 102 via SRC (Short Range Communication) 104. When no response or unrecognized response comes back from the handset 102, the Dev 106 sends another message step 804 to the handset 102 inbox, indicating no associate software existing in the handset 102 (step 820 in Fig. 8, which is shown in

more detail as in handset display screen 902/1002 in Fig. 9/10). The user then screen touches the web address link (URL) 906/1006 (Fig. 9/10), which makes the handset 102 send the application menu download request step 806 to the App Server 108 (Fig. 8). The App Server 108 then transmits back the requested information step 808 to the handset 102 as shown in the handset display 822 presented in more detail in screen 920/1020 (Fig. 9/10).

[00201] Screen 920/1020 presents the Vehicle/Home Control & Alarm application systems 924/1024 supporting some of the most popular OS (Operating System) based handsets 102, such as: Android (926/1026), iOS (928/1028), Windows (930/1030), and others (932/1032). These are some of the well-known OS in the U.S. and majority of the world, but the Dev 106 and its application software in the present invention will also support still being developed and yet to be invented OS anywhere in the world. The running software in Application Download Menu 922/1022 preferably auto-detects in this exemplary embodiment that handset 102 is Android based and presents the self-download link (URL) 934/1034 so the right OS based App download request (step 810 of Fig. 8) is self-transmitted by the handset 102 to the App Server 108 (when the timer expires – i.e., 10 seconds). The App Server 108 then transmits the requested application (step 812 of Fig. 8) to the handset 102 which displays it on screen 824 which is shown in more detail as in several screens 940/1040, 960/1060 and 980/1080 (Fig. 9/10).

[00202] Screen 940/1040 shows the application being downloaded 944/1044, its model or serial number 942/1042, and message to the user to check the tool box 948/1048 for the presence of the software. The user then flips to screen 960/1060 and selects (e.g., executes) the Auto/ Home Application 962/1064 which takes to screen 980/1080, which shows the icon 982/1082 representing the just downloaded software. During its own application download, the handset 102 also preferably displays the updating status of Dev application software 950/1050, if there is any update requirement from the App Server 108 to the Dev 106. During the handset's own application download (step 814), the Dev's application may need to be updated from the App Server to the Dev (step 816).

[00203] User can also preferably without receiving the message from the Dev 106 in his handset's inbox 902/102, goes online and types in the right address 906/1006 to download the activation and application into his/her handset 102.

[00204] Fig. 11/13 illustrates a preferred example of embodiment 1100/1300 of the present invention for auto/home application. It illustrates what first preferably needs to be done after the activation and application 1104/1304 has been downloaded into the handset 102. The handset 102 starts at screen 1102/1302 which shows the Auto/Home App 1104/1304 has been completely downloaded into the handset 102 after the user flips through screens 902/1002, 920/1020, 940/1040, 960/1060, and 980/1080 then executes the appropriate link and icons regarding the auto/home application download. Screen 980/1080 is repeated as screen 1102/1302 containing the Auto/Home

App icon 1104/1304. When said icon 1104/1304 is executed by the user, it will make the handset 102 navigate to screen 1120/1320 showing the Auto/Home App Menu 1122/1322.

[00205] Now the user has the Dev application software in his/her handset 102, he/she will have to activate (Activate 1154/1354) the Dev 106 in order for his/her handset 102 to be able to communicate with said Dev 106; and he/she (and later additional user) can use the handset 102 to program, control, monitor the Dev 106, and be alerted by said Dev 106 of what happens. The activation of the Dev 106 preferably only needs to be done once (in the beginning when the user uses the Dev 106 for the first time) by the user with the first handset 102 - unless the service is disconnected or the user switches to another service provider (then activation is needed again as described in Figures 28 and 29).

[00206] The Dev 106 will be able to communicate with the handset 102 (the one helping it to be activated into the network – handset #1) as soon as it is finished with the activation, since it contains the phone number of the said handset 102.

[00207] When the user selects the Auto/Home Dev Facilities icon 1124/1324 making the handset navigate to the Auto/Home Dev Facilities menu1152/1352, where the user then selects the Activate icon 1154/1354 that starts the process of having the Dev 106 activated into the service provider network.

[00208] Illustration 1180/1380 shows some of the most popular cellular service providers in the USA - such AT&T Wireless, Verizon Wireless, Sprint, T-Mobile, US Cellular, Metro PCS, Virgin Mobile, and Boost.

[00209] If the user is in Mainland China, the cellular service providers would be China Mobile, China Unicom, China Telecom, China Tietong. (*)

[00210] (*) In Taiwan, the cellular service providers would be Far EasTone Telecommunications Co Ltd, Asia Pacific Telecom, LDTA/Chunghwa Telecom, VIBO Telecom, Taiwan Mobile Co. Ltd.

[00211] In Hong Kong, the cellular service providers would be CSL Limited, CITIC Telecom 1616, Truphone Limited, China Motion Telecom, and China-Hong Kong Telecom.

[00212] In Japan, the cellular service providers would be NTT DoCoMo, au, SoftBank Mobile, Willcom, EMOBILE, KDDI Corporation. In Korea, the cellular service providers would be KT, SK Telecom, LG Telecom and Korea Cable Telecom (t-plus), Eco-mobile.

[00213] In India, the cellular service providers would be Andhra Pradesh, Assam, Bihar, Chennai, Delhi & NCR, Gujarat, Haryana, Himachal, Himachal Pradesh, Jammu & Kashmir, Kerala, Maharashtra & Goa, Mumbai, North East, Orissa, Punjab, Tamil Nadu, Uttar Pradesh, West Bengal,

[00214] In Canada, the cellular service providers would be Telus Mobility, Airtel Wireless, EastLink, Bell Mobility, ICE Wireless, Rogers Communications, SaskTel Mobility and Virgin Mobile Canada.

[00215] In Mexico, the cellular service providers would be Nextel Mexico, America Movil/Mextel, Movistar – Telefonica Moviles, lusacell. In Brazil, the cellular service providers would be NII Holdings, Inc., Telecom Italia Mobile, Claro, Vivo S.A., Sercomtel Celular, Brasil Telecom GSM and CTBC Celular S.A.

[00216] In the EU, the cellular service providers would be France Telecom, Globalstar Europt, Vivendi, RFF, Iliad, Bouygues Telecom, Transatel, Omea Telecom, El Telecom (France), T-Mobile Deutschland GmbH, Vodafone D2 GmbH, E-Plus Mobilfunk, O2 GmbH & Co. OHG, Arcor AG & Co, sipgate Wireless, Mobilecom Multimedia, Group 3G UMTS, Siemens AG, … (Germany), Telcom Italia SpA, Vodafone Omnitel N.V., Rete Ferroviaria Italiana, Wind Telecomunicazioni SpA, Hutchison 3G (Italy), Vodafone Spain, France Telecom Espana SA, Xfera Moviles SA, Telefonica Moviles Espana, BT Group, … (Spain), BT Group, Mundio Mobile Limited, Telefonica Europe, Jersey Airtel Limited, Cable & Wireless Worldwide, Network Rail Infrastructure Ltd, Vodafone, … (UK).

[00217] In Russia, the cellular service providers would be Mobile TeleSystems, MegaFon OJSC, New Telephone Company, JSC Uralsvyazinform, Tele2, Central Telecommunication Company, SkyLink/MTS/the Moscow Cellular communication.

[00218] (Source Wikipedia)

[00219] Fig. 12/14 illustrates a preferred activation example of embodiment 1200/1400 of the present invention for auto/home application. It presents the Dev Vehicle/Home activation screen 1202/1402, where the handset 102 navigates to, after the Activate icon 1154/1354 (Fig. 11/13) is executed. This screen starts the activation process by letting user enter required information in order to have the Dev 106 activated into the service provider's network. Before the Dev 106 can connect to the network, so it can make calls and communicate data with other cellular and/or wireless devices, it needs to be recognized by the service provider, its user/owner subscribes to and thus activation is required.

[00220] The present invention takes advantage of the advance and progress made by the service provider, providing OTA (Over The Air) activation procedure where "not yet register mobile device (Dev 106)" can make one time connection to its network in order to be connected/logged in, exchange the activation/provision and registration information parameters between the mobile device (i.e., Dev 106), and the service provider equipments/servers. The service provider, after the successful activation process, recognizes the Dev 106 and from then on the Dev

106 is connected to the service provider's network where it can communicate voice, messages, video, and the like with other wireless devices.

[00221] The present invention illustrates the following preferred exemplary steps for the Dev 106 activation:

[00222] The user applies, signs up, and chooses a service plan with the service provider. The user, after being approved, preferably receives from the service provider an IP address, user ID, an activation password and through his/her handset 102 obtains an encrypted UTAID (Unique Temporary Activation Identifier) which as mentioned earlier also preferably contains an activation type/methodology (NAM, SIM, ModSIM or other) and the activation key. The handset 102 starts the activation process by transmitting the UTAID and the user account information to the Dev 106. The Dev 106 then processes the data and separates the activation type from the UTAID, decodes the activation type and begins the activation accordingly (either NAM, SIM, ModSIM or any other activation methodology). The Dev 106 then transmits the activation key, Dev ID parameters along with the accompanying activation data to the service provider 112 or the provision server 114 when it is temporarily allowed into the service provider's network. The activation key and data are then routed to the OTA activation processor (or responsible servers) by the service provider/provision server/computer which authenticates them for activation processing and finally registers the Dev 106 into its network. The Dev 106 also derives its security/encryption key from the UTAID for the encryption of its communication data to other devices.

[00223] The above steps are illustrated in figures 12 and 14:

[00224] The user enters the service provider's IP address 1208/1408 (as shown in 1224/1424), activation User ID 1210/1410 (as shown in 1226/1426), activation password 1212/1412 (as shown in 1228/1428), and his/her handset phone number 1214/1414 (as shown in 1229/1429), using screen keyboard 1235/1435; then executes Ok icon 1230/1430.

[00225] Handset 102 passes the information the user entered on screen 1220/1420 to the service provider/provision server 114, and in turn receives from the server, the subscriber's account information 1242/1442, name 1244/1444, along with UTAID 1246/1446 as shown in progress on screen 1236/1436.

[00226] Handset 102 then connects to the Dev 106 and communicates with it via SRC 104 (since Dev 106 has not been able to connect to the network 118 yet) transmitting its phone number 1254/1454, user account information 1256/1456, UTAID 1258/1458, the activation command 1260/1460, and it then waits for the Dev 106 to complete its activation 1262/1462. When the Dev 106 completes its activation, it recycles its power (or does a power-on reset 249 Fig. 2/3/4), and then registers into the network. The Dev 106 completes the activation successfully as soon as it receives the confirmation message from the service provider 1268/1468 within a predetermined time out

period. The user is notified of the activation completion message from the Dev 106 in the inbox 1274/1474 and executes the Success icon 1276/1476 to complete the activation process. After the Dev 106 has been activated successfully into the network as mentioned above, it is preferably that the Dev 106 sends the confirmation message 1274/1474 to the handset 102 for the user to respond. After the Dev 106 receives the confirmation response from the user, (when he/she executes the Success icon 1276/1476,) it then transmits an Initialization icon 1290/1490 and messages 1292/1492 to his/her handset 's inbox so he/she can start the initialization process in setting up all the user's information and the handset's parameters into Dev's memory.

[00227] Figures 15A-18 show more in detail of the handset screens 1220/1420, 1236/1436, 1250/1450 and 1270/1470, the interaction between the handset 102, Dev 106, and the Provision Server/Provider 114.

[00228] The present invention presents three methods of activation, such as: NAM (Name Assignment Module), SIM (Subscriber Identity Module) and ModSIM (Modified SIM). The present invention also supports the systems and methods of activation not yet known to the inventor, still under development and/or not yet developed as technology advances and keeps on improving, and the Dev 106 can be specifically designed to work with any cellular service providers to comply with their specification and requirement.

[00229] Figures 15A and 15B illustrate preferred activation examples of embodiment 1500A and 1500B of the present invention in having the Dev 106 activated in the Name Assignment Module (NAM) storage memory area which is already pre-programmed with an ESN/MEID/IMEI value.

[00230] It starts out at step 1502A/1502B (which is equivalent to screen 1220/1420 in Fig. 12/14), where the user enters the handset's phone number, the service provider/provision server IP address, user's activation ID, the activation password, and executes the command Ok icon 1230/1430. The handset 102 then transmits the activation request and activation password 1240/1440 (Fig. 12/14) and 1504A/1504B, then receives the UTAID from the service provider/provision server 1246/1446 and 1506A/1506B. The handset 102 transmits its phone number, user's account information, and the UTAID to the Dev 106 in steps 1254/1454, 1256/1456, and 1508A/1508B.

[00231] The Dev 106 preferably starts the OTA activation by transmitting the activation key and ESN/MEID/EMEI (Electronic Serial Number / Mobile Equipment Identifier / International Mobile Equipment Identifier) 1510A/1510B. The Service Provider / Provision Server 112/114 receives, processes and verifies the activation key is correct and is able to associate the activation key with the user's account information in its server database 1512A/1512B. The Provision Server

114 then preferably transmits the assigned phone number, all other parameters**, and the activation acknowledgement 1514A/1514B to the Dev 106.

[00232] (**The remaining NAM parameter are the System ID, Access Overload Class, Group ID Mark, Initial Paging Channel, Lock Code, local use flag, A/B system selection, MIN mark flag . . .)

[00233] The Dev 106 then stores the NAM parameters into its NAM storage memory area 1516A/1516B and the handset 102 phone numbers and the user's account information into its Handset Information memory area 1518A/1518B. The Dev 106 then recycles its power (or does a power-on reset 249 in Fig. 2/3/4) and then registers into the network 1519A/1519B as are known to those of ordinary skill in the art. The activation is successful when it receives confirmation acknowledgement 1520A/1520B from the service provider 112; in other words it is able to connect to the network.

[00234] During the activation process, the Dev 106 preferably communicates (via SRC 104) its progress status with the handset 102 as shown previously on screen 1250/1450, step 1511A, and finally via the cellular network 118 the confirmation text message 1522A/1522B also as shown on screen 1292/1492 along with Dev Initialization icon 1290/1490. The user preferably then executes said icon to start the Dev initialization process on his/her handset 102 (as shown in Figures 19 and 20), in order for said handset 102 to communicate and utilize all the Dev's functions and capabilities. If the user fails to do the initialization right away, preferably the Dev 106 will periodically sends the same initialization message and icon to the user's handset until it receives the confirmation response from said user.

[00235] Figures 16A and 16B illustrate preferred activation examples of embodiment 1600A and 1600B of the present invention in having the Dev 106 activated in the Subscriber Identity Module (SIM) storage memory area.

[00236] The Dev 106 is not like the typical mobile handset which along with its SIM module is issued or manufactured by the cellular service provider or its affiliated third parties. These mobile handsets already have the IMEI (International Mobile Equipment Identity) recorded into the handsets' memory, IMSI (International Mobile Subscriber Identity) programmed into the SIM modules, a Ki (authentication key), encryption key, possibly an ICCID, and thus are associated with said cellular service provider; and therefore can be easily activated into the service provider network, at initial power-up. The SIM module also functions as a storage device and thus contains personal information, such as: user phone directory, text messages, pictures, etc.

[00237] The Dev 106 on the other hand is not tied to any cellular service provider and thus will be designed to support preferably by way of software downloading and/or updating in order to work with any cellular service provider.

[00238] The Dev 106 is designed each with its own unique IMEI and a SIM storage memory area containing a minimum amount of preprogrammed parameters such as a dummy IMSI (or optionally IMSI derived in the UTAID issued by the service provider during pre-activation). This would allow any service provider to supply the remaining parameters to store into its SIM memory during the activation process. The user therefore, can choose, pick, and change service provider at any moment. Thus the Dev's SIM contains a minimum amount of pre-activation parameters as in this exemplary embodiment, an IMEI or a SN (serial number so it can be associated with the Dev 106), an IMSI value which it uses during the activation for identification. And of course, the activation key as was mentioned earlier, so the service provider can associate it with the user/subscriber.

[00239] It starts out similarly as described in steps 1502A/1502B, 1504A/1504B, 1506A/1506B and 1508A/1508B in Fig. 15A/15B.

[00240] The Dev 106 then continues the OTA activation by transmitting the activation key, IMEI, and dummy IMSI 1610A/1610B. The service provider/provision server 112/114 receives, processes, and verifies that the activation key is valid and it is able to associate the activation key with the user's account information in its server database 1612A/1612B. The server then transmits the SIM parameters preferably, such as: the assigned phone number (or MSISDN – Mobile Subscriber ISDN number), IMSI, TMSI (Temporary IMSI), Ki (Authentication key), and the activation acknowledgement 1614A/1614B to the Dev 106.

[00241] The Dev 106 then stores the SIM parameters into its SIM storage memory area 1616A/1616B, the handset 102 phone numbers and the user's account information into its Handset Information memory area 1618A/1618B. The Dev 106 then recycles its power (or does a power-on reset in Fig. 2/3/4) and then registers into the network 1619A/1619B, as are known to those of ordinary skill in the art. The activation is successful when it receives a confirmation acknowledgement 1620A/1620B from the service provider 112; in other words it is able to connect to the network.

[00242] During the activation process, the Dev 106 preferably communicates via SRC 104 its progress status with the handset 102 as shown previously on screen 1250/1450 and step 1611A, and finally via the cellular network 118 the confirmation text message 1622A/1622B, (also as 1292/1492, shown on inbox screen 1280/1480) along with Dev Initialization icon 1290/1490. The user preferably then executes said icon 1290/1490 to start the Dev initialization process on his/her handset 102 (as shown in Figures 19 and 20) in order for said handset 102 to communicate and utilize all the Dev's functions and capabilities. If the user fails to do the initialization right away, preferably the Dev 106 will periodically sends the same initialization message and icon to the user's handset until it receives the confirmation response from said user.

[00243] Figures 17 and 18 illustrate preferred activation examples of embodiment 1700 and 1800 of the present invention in having the Dev 106 activated in the Modified Subscriber Identity Module (ModSIM) storage memory area.

[00244] The ModSIM activation is similar to the SIM's but is simpler. The Dev 106 transmits only its ID parameters and the activation key (derived from the UTAID) to the Provision Server which receives, processes and associates said ID parameters with said Dev and said activation key with the subscriber. The Provision Server then generates the registration acknowledgement and sends back to the Dev, its (ODA) assigned telephone number, TMSI and the Ki.

[00245] The Dev 106 starts out similarly as described in steps 1502A/1502B, 1504A/1504B, 1506A/1506B and 1508A/1508B in Fig. 15A/15B.

[00246] The Dev 106 then continues the OTA activation by transmitting the activation key, its ID parameters (Dev's S/N, part number, manufacturer's name) 1710/1810. The service provider/provision server 112/114 receives, processes, and verifies that the activation key is valid, and it is able to associate said activation key with the user's account information in its server database 1712/1812. The server then transmits the ModSIM parameters preferably, such as: the assigned phone number, TMSI (Temporary IMSI), Ki (Authentication key), and the activation acknowledgement 1714/1814 to the Dev 106.

[00247] The Dev then stores the ModSIM parameters into its ModSIM storage memory area 1716/1816, the handset 102 phone numbers and the user's account information into its Handset Information memory area 1718/1818. The Dev 106 then recycles its power (or does a power-on reset in Fig. 2/3/4), and then registers into the network 1719/1819, as are known to those of ordinary skill in the art. The activation is successful when it receives a confirmation acknowledgement 1720/1820 from the service provider 112; in other words it is able to connect to the network.

[00248] During the activation process, the Dev 106 preferably communicates (via SRC 104) its progress status with the handset 102 as shown previously on screen 1250/1450 and step 1711; and finally via the cellular network 118 the confirmation text message 1722/1822; (also as 1292/1492 shown on inbox screen 1280/1480) along with Dev Initialization icon 1290/1490. The user preferably then executes said icon 1290/1490 to start the Dev initialization process on his/her handset 102 (as shown in Figures 19 and 20) in order for said handset 102 to communicate and utilize all the Dev's functions and capabilities. If the user fails to do the initialization right away, preferably the Dev 106 will periodically sends the same initialization message and icon to the user's handset until it receives the confirmation response from said user.

[00249] The Dev 106 in the home application (as represented by the hardware and software block diagrams in Figures 3 and 6) is a stationary device. In other words, it normally does not need

to do roaming. There preferably exists a mechanism or a method such as a bit/flag in the subscriber account, so the service provider can distinguish it from a typical mobile device which does roaming; and therefore few service provider's resources are allocated to support it, which in turn can lower the service cost to users/customers in the home application. The Dev 106 (in home application unlike in vehicle and robotic applications), in turn, does not have to broadcast its presence periodically, as in this method, since its registration (identity data) stays (resides) with the same MSC/VLR in the service provider's network.

[00250] Figures 19 and 20 illustrate preferred application examples of embodiments 1900 and 2000 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to initialize his/her personal information and handset parameters into the Dev 106 after said Dev has been successfully activated and registered into a cellular network.

[00251] The user starts by executing the Initialization icon 1290/1490 (he/she received in the inbox, screen 1280/1480 of Fig. 12/14) that makes the handset 102 navigates to the handset's Auto/Home Device Initialization screen 1902/2002. Next, the user enters his/her chosen account security passwords (1914/2014 and 1916/2016), handset chosen passwords 1918/2018, then executes 1906/2006 that makes the handset 102 transmit the command and information (also in steps 1976/2076 and 1978/2078 of flow diagram 1970/2070) to the Dev 106 which processes the command and verifies that the two passwords, which each entered twice are identical (as routine practice for identification). The Dev 106 then sends back the requested information which the handset 102 displays on screen 1920/2020. It shows the handset's phone number 1924/2024 (that the handset passed to it previously during the activation process) and the handset password, service provider name and account information 1025/2025, Dev phone number 1926/2026, account security password 1923/2023 and user name (1925/2025). The user needs to fill out the remaining information and upon completion it is presented as shown in screen 1930/2030.

[00252] In screen 1930/2030 (also as shown in step 2082), the user enters car make and model, License Plate 1934 (for Auto Dev) or house address 2034 (for Home Dev), account security password 1936/2036, registered phone numbers 1937/2037 and its password, account name and service provider account number 1938/2038, Dev phone number 1940/2040, email address 1942/2042 for password recovery, emergency center phone number 1946/2046, and a plurality of other required information (not shown for clarity purpose and ease of presentation as are known to those of ordinary skill in the art). The user then executes the Exe icon 1954/2054 making the handset 102 store the Dev's phone number 1984/2084 into its memory and transmit the command and information (shown in step 1986/2086) to the Dev 106 which processes and saves them into its memory 1988/2088. The Dev 106 then transmits 1990/2090 back the information 1992/2092 as shown in screen 1930a/2030a, which the user can re-edit again 1952a/2052a or finishes the initialization process by executing 1950a/2050a.

[00253] The Police and Emergency phone number 1946/2046 (in US and Canada 911 step 1960/2060 - Mainland China 110 and 119, Hong Kong 999 - EU 112 – Taiwan, Japan, South Korea, France 119, India 100 and 101, Mexico 066 and 068, Brazil 190 and 193) will be called and sent voice and text messages by the Dev 106 when the air bag 226 (Fig. 2) is inflated or its house is on fire (smoke alarm) 304 (Fig. 3), as well as to other registered handsets 102. The Email addresses 1942/2042 are for the password recovery when the user forgets the account security password. The Dev 106 then sends the password and email address to the Email Server 116 and has it emailed to the stored email address 1942a/2042a for the user to recover his/her password. The Dev phone number 1926/2026 (phone number 916-122-9876/916-122-9877) is used and stored (in step 1984/2084) by the handset application software into the handset memory so the handset application uses the number to communicate with the Dev 106.

[00254] Fig. 21A illustrates a preferred application example of embodiment 2100A of the present invention. This exemplary embodiment presents preferred steps taken by the user in his/her handset to add (register) a new handset 102 into the Dev 106.

[00255] The user can add a new handset 102, which will be registered into the Dev 106. After the addition (registration) the new handset 102 will have all the controlling, programming, and monitoring capability as the registered handset 102.

[00256] The user executes the Add Handset icon 1172/1372 in screen 1150/1350 (Fig. 11/13), making his/her handset navigate to the Adding New Handset menu as shown on its screen 2102A/2152A, which prompts the user for the account security password entry. The user enters the account security password 2108A or 2158A and executes the Ok icon, making the handset transmit the command and data to the Dev 106 which verifies and process the data. If the account security password matches, the Dev 106 then sends back the vehicle/home information 2110A/2160A and prompts the user for the new handset chosen password 2112A/2162A. The user then enters the new handset chosen password 2113A/2163A. For the auto application, a single handset category 2114A is required for user's new phone number input. While for the home application, three categories, such as: family member phone entry 2164A, household help (i.e., maid service) phone entry 2165A, and friend or temp member phone entry 2167A; out of which the user only chooses one to enter the new handset phone number. In this exemplary embodiment, let us assume the user enters his/her family member's handset phone number 2164A and then executes the Ok icon 2116A/2166A making the handset 102 transmit the command and data to the Dev 106. The Dev 106 verifies and processes then transmits back the data to the handset 102, which displays them in screen 2120A/2170A for the user's verification. The user then executes the Confirm icon 2134A/2184A which makes the handset 102 transmit the confirmation back to the Dev 106, which processes and updates its device information file in memory, and sends it back to the handset 102 which stores it in its own memory and displays it in its screen 2140A/2190A. The user can always retrieve and view

or request the up-to-date device information as described later in Fig. 24C. The Dev 106 also sends instruction messages with the application download link and the Sign-In icon 2214 (which contains its phone number), as shown on screen 2202 of Fig. 22, to the added handset 102 whose user can start the signing-in as illustrated in Fig. 22.

[00257] Fig. 21B illustrates a preferred application example of embodiment 2100B of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to add (register) in a new handset 102 into the Dev 106 in the restricted or temporary mode.

[00258] It presents a case where the user either has entered a household member handset's phone number 2165A (in screen 2152A of Fig. 21A), which takes his/her handset to screen 2102B, which contains the just entered handset's phone number for household help 2115B. Or the user has entered a friend (temp) handset's phone number 2167A (in screen 2152A of Fig. 21A) which takes his/her handset to screen 2152B, which contains the just entered handset's phone number for friend (temp) 2167B. The user then executes Ok icon 2116B/2166B making the handset 102 transmit the command and data to the Dev 106. The Dev 106 verifies and processes, then transmits back the data to the handset 102 which displays them in screen 2120B/2170B for user's verification. Screen 2120B presents the added handset is in restricted mode while screen 2170B presents the added handset is in temporary mode. The user then executes the Confirm icon 2134B/2184B, which makes the handset 102 transmit the confirmation back to the Dev 106, which processes and updates its device information file in the memory, and sends it back to the handset 102, which also preferably stores it in its own memory. The user can always retrieve, view, or request the up-to-date device information (as described later in Fig. 24C). The Dev 106 also sends the instruction messages with the application download link and the Sign-In icon 2214 (which contains its phone number), as shown on screen 2202 of Fig. 22, to the added handset 102 whose user can start the signing-in as illustrated in Fig. 22.

[00259] Temporary registered handset 102, such as: the one owned by a friend, a guest or a neighbor who has the temporary access to the house, is preferably programmed with a starting date (2167B1) and time (not shown), ending date (2167B2) and time (not shown), and its access privilege to the house is as a normal registered handset's 102. It has no capability of registering another handset 102 into said Dev 106 or no capability of activating the Dev 106 into a new network. It will be automatically removed (deregistered) from the Dev 106 on its expiration date (2167B2).

[00260] Household help member's handset 102 is preferably restricted in its functionality to only be able to turn on or turn off the house security alarm for entry or exit into the house or the premises, entering and exiting on a certain time and day of the week (not shown). It will not be able to command the Dev 106 to control, observe or monitor anything else; and to have no capability of registering another handset 102 into the Dev 106.

[00261] This embodiment preferably allows a user of the Dev 106, away from home (near or far), or on business trip or on vacation somewhere, to remotely add (register) his/her friend's handset 102, using his/her own registered handset 102, to the Dev 106. This allows the friend to use his/her own handset 102 to enter and exit to stay at the user's house, for any programmable duration. The user preferably can also even keep track of the time and date of the ins and outs of said friend (not shown), or a household help member (not shown) by executing the List Handset In & Out Activity icon 1342 in screen 1320 of Fig. 13. The household help member or the friend can preferably always remove from his/her handset 102, the software application associated with the Dev 106 when it is no longer needed.

[00262] Fig. 22 illustrates a preferred application example of embodiment 2200 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her newly added handset 102 to sign in said handset 102 into the Dev 106.

[00263] The user of the recently added (registered) handset 102 receives (step 2242 in flow diagram 2240) in its inbox (screen 2202) a notification 2204 from the Dev106 that he/she needs to download the application 2210, and then signs in 2212 in order for his/her handset 102 to work with the Dev 106. The user first executes the application URL (2210) for the app download, also is shown in step 2244 (download link 2210 whose app downloading steps were described previously in screens 920/1020, 940/1040, 960/1060, and 980/1080 of Fig. 9/10). After the application has been downloaded, in step 2246 (assuming his/her handset does not contain such app; otherwise the user just signs in), the user then executes the Sign In icon 2214 (also shown in step 2248) which navigates the handset 102 to screen 2220 where the user enters his/her correct handset password 2226 (which is the same password the user of the adding /registering handset had assigned 2113A/2163A on screen 2102A/2152A of Figures 21A or 2113B/2163B on screen 2102B/2152B of Fig. 21B). The user finally executes (Execute icon 2228) allowing the handset 102 to store the Dev's phone number into its memory 2250 (in graph 2240) and transmit the acknowledgement to the Dev 106. The Dev receives the acknowledgement 2252 and then transmits (step 2254) the notification (2262) to the user of the registering handset 102r (in flow chart 2240) as shown in screen 2260. From now on, the sign-in handset 102 and the Dev 106 can communicate with each other (2256).

[00264] Fig. 23 illustrates a preferred application example of embodiment 2300 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to remove a registered handset 102 from the Dev 106.

[00265] The user executes the Remove Handset icon 1176/1376 in screen 1150/1350 of Fig. 11/13, making his/her handset navigate to the Remove Handset menu as shown on its screen 2302/2352, which prompts the user for the account security password entry. The user enters the

account security password 2308/2358 and then executes the Ok icon 2316/2366 making the handset 102 transmit the command and data to the Dev 106 which verifies and processes the data. If the account security password is correct, the Dev 106 transmits back the Dev's auto/home information 2310/2360 and its registered handset phone numbers 2312/2362, then prompts the user for the phone number of the handset 102 being removed 2314/2364. The user enters the being removed handset's phone number 2314/2364 then executes the Ok icon 2316/2366 making the handset 102 transmit the command and data to the Dev 106. The Dev 106 verifies and processes the data, then transmits them back to user's handset 102 (screen 2320/2370) for confirmation 2328/2378 and 2330/2380. The user then confirms 2334/2384, making the handset 102 transmit the confirmation to the Dev 106 which verifies, processes and update its device information, and sends it back to the handset 102 (2340/2390) showing that the handset 102 has been removed 2346/2396.

[00266] Fig. 24A illustrates a preferred example of embodiment 2400A of the present invention. This exemplary embodiment presents preferred program flow of the Dev 106 password recovery when the user fails to enter to the correct password more than the allowed attempts (i.e., three attempts).

[00267] It illustrates a password recovery mechanism when the user fails to enter the correct password, and thus will be able to receive it back in his/her email account from the email server. An example where password recovery can happen is when a user wants to view or edit the Auto/Home Device Configuration command as represented by icon 1156/1356 of Fig. 11/13.

[00268] After the user executes the Auto/Home Device Configure icon (1156/1356 of Fig. 11/13), making his/her handset 102 transmit the command to the Dev 106 which processes said command and sends the response back to said handset 102 which displays the Auto/Home Device Configure command as shown on its screen 2402A/2422A. It requires the account security password entry 2408A/2428A from the user and if he/she fails after three times 2410A/2430A (also in step 2472A of flow diagram 2470A), the Dev 106 enters the email recovery process by sending the password request command 2474A to the handset 102, which prompts 2410A/2430A the user for his/her email address 2412A/2432A. The user enters the email address, and then executes the Exe icon 2414A/2434A, making the handset 102 transmit the command to the Dev 106 which receives and processes (step 2478A). If the email address is verified 2480A and does not match, the Dev 106 sends "Email address does not match" message 2484A to handset 102 and stop 2486A. If Email address matches, the Dev 106 transmits the password recovery command along with the user's email address 2482A, and the password to the mail Server 116 for password recovery. The user can then check his/her email (2452A of screen 2450A) and retrieve the password (2456A).

[00269] Figure 24B illustrates a preferred application example of embodiment and 2400B of the present invention. This exemplary embodiment presents preferred steps taken by a user in

his/her handset 102 to configure the Dev 106 with any changes in personal and or handset information.

[00270] It presents the continuation of screen 2402A/2422A, where in this case the user entered the correct account security password 2408A/2428A which was transmitted by the handset 102 to the Dev 106 as described previously in Fig. 24A. The Dev 106 transmits back 2464B (in diagram 2460B) its device configuration data to the handset 102 which displays it on screen 2402B/2422B. Some preferable information (not all) is shown, such as: vehicle ID information (A1) / home address (B1), account security password (A2/B2), registered handset phone numbers and its passwords (A3/B3), user name and account number (A4/B4), Dev phone number (A5/B5), email address (A6/B6), and emergency center phone number A7/B7. The user preferably can edit to change information on screen 2402A/2422A (also shown in step 2466B) any information but the registered handsets' phone numbers (A3/B3) and Dev's phone number (A5/B5). Let us assume that the user edit changes (step 2466B) by adding a second email address 2404B/2424B and executes Exe icon 2408B/2428B making the handset 102 transmit the command and data to the Dev 106 (step 2468B). The Dev 106 then processes the data and sends it back (step 2472B) to the handset 102 for user confirmation (screen 2412B/2432B and step 2470B) showing a second email address (2ndowner@any.com) has been added (2414B/2434B) into the configuration/device file. The user then confirms 2418B/2438B making the handset 102 transmit the confirmed data back (step 2474B) to the Dev 106 which saves it in its memory (step 2476B).

[00271] Fig. 24C illustrates a preferred application example of embodiment 2400C of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to retrieve and view the Dev106's device information.

[00272] The user executes the Dev Info icon 1166/1366 in the Auto/Home Dev Facility Menu 1150/1350 (Fig. 11/13), making his/her handset 102 transmit the device information query command to the Dev 106 which processes said command and sends the response back to said handset 102, which displays the Auto/Home Device Information as shown on its screen 2410C/2440C. It shows the Dev type Car ID information/Home address 2416C/2446C, account security password 2418C/2448C, registered phone numbers 2420C/2450C and passwords, account name and number 2422C/2452C, Dev's phone number 2424C/2454C, email addresses 2426C/2456C, and Emergency center phone number 2428C/2458C,

[00273] Fig. 25 illustrates a preferred example of embodiment 2500 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her new handset 102 to register said handset 102 to the Dev106.

[00274] This feature allows the user to register a new handset 102 if he/she lost his/her only registered handset. Let us suppose that the user lost his/her old handset (phone number 916-987-

6500 in 2410C/2440C) and bought a new one (phone number 916-987-0000). The user then registers the new handset 102 into the Dev 106. This feature thus allows a new handset 102 to be registered into the Dev 106 in case the old registered one is no longer available. With the newly registered handset 102, the user can use it to remove (deregister) the lost handset 102 as was previously described in Fig 23. Also as mentioned earlier, he/she needs to download the application (and activation) online in order to run the application and uses the related commands/icons to register his/her handset 102 into the Dev. He or she does not have to be in the vicinity (within the SRC range) of the Dev 106 since it already registered with the network. The requirement is that the user knows the Dev's phone number and its security password in order for his/her handset 102 to transmit the command and data to the Dev 106 to begin the registration. The person who has the possession of the lost handset, if it is the case, will be notified of the registration as shown in step 2592, and on the handset's screen 2650 (of Fig. 26) but will not be able to prevent it since he/she does not have the account security password to enter as shown at 2666 (Fig. 26).

[00275] The user executes the Handset Register icon 1158/1358 in Fig 11/13, making his/her handset navigate to the Handset Registration menu as shown on its screen 2502. In area 2506, the user enters the Dev phone number 2508, the account security password 2510, the handset phone number twice (2512 and 2514) and the chosen handset password twice (2516). The user then executes the Exe icon 2520 making the handset 102 transmit the command and data to the Dev 106 which receives and processes said information (2572 in chart 2570).

[00276] From here on, the inventor will skip, (on occasion,) the handset screen display messages (2510) which prompt back and forth the communication between the handset 102 and the Dev 106 for the required account security password entries and retries. He also will skip, (on occasion,) the handset screen display messages, such as: the phone numbers not matched and the reentries, or the chosen handset passwords not matched and the reentries, (for ease of presentation,) as are known to those of ordinary skill in the art.

[00277] While the Dev's requirement for account security password and handset password might be overlapped for certain common functions, each type of password is required (for the user's protection) in order for the Dev to perform its separate operations. They (functions requiring the account security password) are for the Dev's structure functions such as: handset registration, handset addition or removal, device configuration, device information, handset locator, toll fee payment setup, route and speed tracking, home alarm configuration, home appliances/equipments addition and removal, and the like. And the handset password is for the Dev's operation functions such as: vehicle/home control, program, monitor and view, engine status, home appliances/equipments operations, vehicle locator, and the like.

[00278] Flow chart 2570 shows the program flow of the Dev 106 when it executes the Registration command transmitted by the handset (screen 2502). It starts at step 2572 when it

receives the command and the data, then verifies that if the account security password (PW) is correct 2574. When the account security password is correct, the Dev 106 checks to see if the handset phone numbers entered two times 2512 and 2514 are identical and so are the chosen handset passwords 2516 (in step 2582). The Dev 106, at the same time, transmits the registration process status to the handset (screen 2532, to keep the user informed). If they all are, the Dev 106 proceeds to process the command and stores all information (including the handset's phone number step 2586) into its memory. It then sends a confirmation command or the Auto/Home Dev Information 2540/2540a (in step 2590) to the handset 102 to confirm its completion 2558/2558a. When the account security password does not match, the Dev 106 transmits the message "PW not Matched" (step 2576) to the handset 102 and lets it attempt 3 times (step 2580) and if it fails, the Dev 106 goes to password recovery 2588 and also sends messages to other registered handsets 102 informing them of the action (step 2592). This feature allows users to be informed if there is any illegal registration from an unauthorized source. If the handset phone numbers or handset's chosen password entries are not identical, the Dev 106 goes to step (step 2584) requiring the user to re-enter the information.

[00279] Fig. 26 illustrates a preferred example of embodiment 2600 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her new handset 102 to register said handset 102 into Dev 106 via the SRC network.

[00280] Chart 2602 presents a new handset 102 attempting to activate/register with the Dev 106, and the screen display 2650 of a registered handset 102 receiving the alert of said attempted activation/registration. The activation/registration starts at 2604 when the Dev activation button is pushed. The Dev 106 checks to see if its current account is active 2606; and if the account is not active (either has not been activated, or has been deactivated or has not been able to register into the network for the last 30 days, for example), it sends the inquiry message to the activating/registering handset 102 (2608). If the Dev 106, within some short amount of time, is getting no response back 2610, it sends messages 2614 to said handset 102 indicating that said handset 102 user needs to download the application (app) software to activate and communicate with the Dev 106 (these steps have already been presented in Figures 8 and 9/10). If in step 2610 the Dev 106 gets the proper response back from the handset 102, then the activation starts 2612 (as illustrated in Figures 11/13, 12/14, 15A-18 which already presented one or the plurality of ways of activating the Dev 106). All the communication between the Dev 106 and the activating/registering handset 102 in this figure uses SRC (Short Range Communication), such as: either Bluetooth, wireless USB, NFC, WI-FI, infrared, wireless LAN, wireless radio frequency (RF) technology, or countless short-wave communication as are known to those of ordinary skill in the art and it is as shown in 104 Fig. 1.

[00281] If the Dev 106's account is active (in other words, it is registering/connecting to the network), it sends messages "You need the right software to run this application" (2616) to the

registering handset 102. The user either downloads the application (app) online 2618 (by typing in the URL of the App Server 906/1006 on his/her handset's screen, and hits the screen keyboard return, as shown previously on screens 920/1020, 940/1040, 960/1060 and 980/1080 of Figure 9/10), if his/her handset 102 does not contain the software. Or the user just runs his/her handset's existing application 2620 (as shown previously on the handset screen 2502 of Fig. 25 after its user executed the Handset Register icon 1158/1358 in Fig 11/13).

[00282] At step 2621, the Dev 106 checks to see if any registered phone numbers exist in its memory. If no registered phone numbers exist in its memory, while the Dev 106 is being active, meaning it is containing a SIM card module (270 of Fig 2/3/4) in its slot (and that was the reason it did not have to go through the normal activation process, as illustrated in Figures 11/13 to 12/14, and 15A to 18 in order to be able to register into a network). At step 2623, (thanks to the presence of the SIM card,) the Dev 106 is connecting to the network, but a first handset's phone number has to be registered into said Dev's memory in order for these two devices to communicate with each other. The Dev 106 prompts the user of the new handset for his/her chosen security passwords (2623) and verifies if their entries are identical step 2625. If the security password entries are identical, the Dev 106 prompts for the handset phone number entries and its chosen handset password entries at step 2627, then proceeds to verify them at step 2640.

[00283] At step 2624, (there are registered phone numbers in the Dev's memory, meaning the Dev 106 went through the normal activation and registration process,) the Dev 106 receives the handset registration command, account security password, handset numbers and chosen handset passwords from the registering handset 102. The Dev also alerts (step 2622) by sending messages 2654 to the owner of the registered handset 102 of this attempted registration (as shown on his/her handset screen 2650).

[00284] At screen 2650, the owner of the alerted handset 102 can see the nature of the alert 2652, the message 2654, time and date 2656, the registering handset/mobile phone number 2660. The owner can speed up the registering process by entering the correct password 2666 in order to be able to select Ok icon 2658 to allow it, or No icon 2662 to stop it (the password is required here preferably to make sure that he/she is the real owner of the handset). This makes his/her handset 102 transmit the command to the Dev 106, which receives it either in 2626 or in 2644 (chart 2602).

[00285] Back in chart 2602, the Dev 106 verifies if the account security password (indicated by 1936a/2036a in screen 1930a/2030a of Fig. 19/20) is ok. From this point on and thereafter, if the Dev 106 receives the "OK" command in step 2626 from one of the handsets 102 (executed by 2658 icon in screen 2650), it proceeds to verifies the handset phone number and its password entries (they were both entered twice to prevent typing mistakes) to see if they identical 2640 (without going through the account security password entry verification 2630). If the Dev 106 receives a "No OK" step 2644 from one of the handsets 102 (executed by 2662 in screen 2650), it will stop the process

right away step 2636. Nevertheless, if the Dev 106 receives no messages from a registered user, it proceeds to verify the account security password 2630 (since the owner might have lost his/her only handset 102 and wanted to register a new one). If the password is not ok, the Dev 106 prompts for another entry 2628. If the entry still fails at the third attempt 2632, the Dev 106 proceeds to the password recovery process step 2634 (described in Fig. 24A) and finally to goes to stop (step 2636). If the account security password passes, the Dev goes to handset phone number entry and handset password entry verification step 2640 to verify if their twice entries and identical. If their twice entries are not identical, it prompts for re-entry step 2638; or if they are, it proceeds to allow the handset 102 to start the registration 2642; as already described in Fig. 25.

[00286] Fig. 27 illustrates a preferred example of embodiment 2700 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to update said handset 102 and the Dev 106 applications.

[00287] The user executes the Handset and Dev App Update icon 1164/1364 of Fig. 11/13, making his/her handset navigate to the Handset and Dev App Update command as shown on its screen 2702. The handset prompts the user to enter the account security password (this embodiment assumes the handset already retained/stored the URL of the App Server for the convenience of the user, otherwise it will also prompt the user for the App Server' URL 906/1006 of Fig. 9/10). When the password 2704 matches (otherwise the Dev 106 proceeds to password recovery as in Fig. 24A) with the one in its memory, the handset 102 navigates to screen 2712 and transmits the app version query command to the Dev 106 (step 2762) and the App Server 108 (step 2764) which both send back the version information steps 2772, 2774 and 2776 respectively as displayed by the handset 102 in screen 2716: the handset current ver. 2718/2768, handset latest ver. 2720/2774a, Dev current ver. 2722/2772a and Dev latest ver. 2724/2776a. When the user wants to update to the latest app version 2726 and executes the Exe icon 2730, making the handset 102 transmit the app download command to the App Server 108 (step 2780), and receives (step 2782) the downloaded copies of the latest application (2782a) from the App Server 108. The handset 102 then transmits the Dev's latest version app (2784a) and the app update command to the Dev 106 (step 2784). When the Dev 106 receives the command and the latest version app, it updates its application to the latest version app 2786 and then sends back to the handset 102 the acknowledgement 2788. Next the handset 102 updates its application to the latest version 2790. The updated information of both the handset 102 and the Dev 106 is displayed by the handset 102 in screen 2740. Alternatively, the Dev 106 can download the latest version app directly from the App Server 108 when it receives the app update command from the handset 102.

[00288] Fig. 28/29 illustrates a preferred application example of embodiment 2800/2900 of the present invention. This exemplary embodiment presents preferred steps taken by a user in

his/her handset 102 to activate his/her currently registered Dev 106 into the network of a new cellular provider when he/she decides to switch to said provider.

[00289] This embodiment shows when the user decides to switch the cellular service of the Dev 106 to a different (second) cellular service provider, he/she has to have the Dev 106 activated into the new network. It is preferable that the user has his/her Dev 106 activated into the new (second) service provider's network before he/she has the Dev 106 disconnected from the existing (first) service provider's network. In other words, the Dev 106 should still have access to the current network while the user is having it (Dev 106) activated into a second network. As soon as the Dev activation into the new network is completed, the user can have the Dev 106 disconnected from the current (first) service provider's network. This allows the user to use the handset 102 in communicating with the Dev 106 during activation via cellular network instead of via the SRC 104 medium (in other words, he/she can activate the Dev 106 anywhere instead of having to be in the vicinity of the Dev 106 as done previously).

[00290] The activation process begins, after the user executes the Activate icon 1154/1354 of the Auto/Home Dev Facility Menu 1150/1350 (Fig. 11/13), making his/her handset navigate to the Vehicle/Home Activation menu, as shown its screen 2802/2902. The rest of the activation procedure is identical as shown in Fig. 28/29, which is nearly identical to Fig. 12/14 with the exception that the Dev 106 already contained handset's phone numbers 2814/2914; whereas the user had to enter it 1214/1414 in screen 1202/1402 of Fig. 12/14. As soon as the Dev is activated and able to register and connect into the new network with the user confirming command success to the Dev 106 (by executing the Success icon 2876/2976), the Dev 106 sends its Device Information (screen 2880) containing its phone number, which the handset stores and uses from then on in its communication with the Dev 106. The Dev's cellular service to the current network can then be disconnected and from here on the Dev 106 communicates with other mobile devices (handsets) 102 in the new network. The Dev's information file (screen 2880) contains the same programmed data. In other words, there is no need for the user to reinitialize or reconfigure the Dev 106. Preferably the only difference is the new account number 2884/2984 (plus the name of the new service provider) and possibly the Dev has been assigned a different phone number 2882/2982. The Dev also preferably sends command(s) to the other handset(s) as shown in the forms of the icon 2892/2992 in the inbox(es) (screen 2890/2990) along with messages 2894/2994 informing the user(s) to update his/her (their) handset(s) with the Dev's (new) number.

[00291] Fig. 30 illustrates a preferred application example of embodiment 3000 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to program, retrieve, view and monitor the Dev Auto Control and Monitor system.

[00292] The user executes the Auto Control & Monitor icon 1132 in the Auto App Menu 1120 of Fig. 11, making his/her handset navigate to the Auto Control and Monitor Menu as shown

on its screen 3002. The Auto Control and Monitor Menu 3004 presents the user with the Control icon 3014 which the user uses to control the vehicle accessories (screen 3050), such as: to turn the alarm on/off 3052, to lock/unlock doors 3054, to sound the horn 3056, to turn the ignition on/off 3058 and the emergency lights 3060. The Status icon 3018, which the user uses to view the status of the vehicle at the moment, is shown in handset screen 3020/3036. The Monitor icon 3006 is the input of the cameras (216 of Fig. 2) in the vehicle which the user can use to monitor real time of what's happening around and inside the vehicle (as shown in screens 4180B and 4190B of Fig. 4100B).

[00293] Chart diagram 3070 shows the interaction between the handset 102 and the Dev 106 as discussed in screen 3050. Take for example when Alarm icon 3052 is selected (screen touched) by the user, the handset 102 sends the alarm "toggle command" to the Dev 106 (In this example, the inventor adds the Service Provider 112 to show that as always, the Dev 106 has to have access to the network in order to communicate with the handset 102 and other devices) as shown in step 3072 of graph 3070 via the cellular network when the handset 102 is not in the vicinity within the Dev 106's SRC medium range. On the other hand, when both the Dev 106 and the handset 102 are within their SRC medium range, they preferably select to communicate with each other via the SRC communication network, which can be faster and preferably just as secure since built-in protection, such as: the handset's phone number has been encapsulated into the data streams and, if necessary, the owner's account security password has been also preferably encrypted.

[00294] If the Alarm was on before the Dev 106 receives the command from the handset 102, it will toggle and send the "Alarm is OFF" 3053 shown in step 3073. Step 3072 corresponds to the icon Alarm selection 3052; step 3073 corresponds to the message "is OFF" 3053. Step 3074 corresponds to the icon Doors selection 3054; step 3075 corresponds to the message "Are locked" 3055. Step 3076 corresponds to the icon Horn selection 3056; step 3077 corresponds to the message "Sounding" 3057. Step 3078 corresponds to the icon Ignition selection 3058; step 3079 corresponds to the message "Engine OFF" 2359. Step 3080 corresponds to the icon Emergency Lights selection 3060; step 3081 corresponds to the message "are OFF" 3061.

[00295] Fig. 31 illustrates a preferred application example of embodiment 3100 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to retrieve, view, and enter information into the Dev GPS system.

[00296] The user executes the GPS icon 3008 (Fig. 30), making his/her handset 102 transmit the command to the Dev 106, which in turns processes said command and passes it to the GPS 3182, receives the response from said GPS 3182, processes said response and passes it back to the handset 102, which displays the Auto GPS menu, as shown on its screen 3102. It shows the Auto GPS menu 3104 comprising the GPS address Destination Entry 3108, the Destination Retrieval

3106, and the Recent Entries icons 3110. The GPS Destination Entry and the Destination Retrieval allow the user to enter and retrieve the GPS location addresses without seating at the driver's seat.

[00297] To enter the location addresses to the GPS, the user first selects the Destination Entry icon 3108, making the handset 102 navigate to screen 3120. The user then enters City 3124, State 3126, Street and Address 3128 using keyboard 3132 for data inputs. When the user enters the name of the city 3146, the handset 102 transmits the information preferably in real-time (IM) to the Dev 106 which passes the information to the GPS 3182 which in turn responds with a pop up hint screen 3150 (when the number of characters, making the city name narrows to dozen or less of potential matched names) via the Dev 106 as presented in screen 3140. After all the address information is done, executing the Save icon 3170 will make the handset 102 send the information and the command to the Dev 106 which passes it to the GPS 3182 to save all the information in screen 3160 to the GPS memory.

[00298] Graph 3180 shows the interaction between the handset 102, the Dev 106 and the GPS 3182 (Service Provider 112 is omitted here for ease of presentation). In graph 3180, the Dev 106 acts like a conduit, translating and passing the information back and forth between the handset 102 and the GPS 3182. Step 3184 corresponds to passing the city name 3166 from the handset 102 to the Dev 106 and to the GPS 3182. Step 3186 is the corresponding the response from the GPS 3182 to the Dev 106 and then to the handset 102. Step 3188 corresponds to passing the State name 3164 from the handset 102 to the Dev 106 and to the GPS 3182. Step 3190 (if any) is the corresponding response from the GPS. Step 3192 corresponds to passing the Street and Address 3162 from the handset 102 to the Dev 106 and to the GPS 3182. Step 3194 (if any) is the corresponding response from the GPS 3182. Step 3196 corresponds to the command Save icon 3170 from the handset 102 to the Dev 106 and to the GPS 3182. And finally step 3198 (if any) is the corresponding response from the GPS 3182. Alternatively, steps 3184, 3188, 3192 and 3196 can be combined into one single step (or all the GPS information in one packet) to the Dev 106 and gets a single response back 3198 from the Dev 106. The steps and ways presented in the present invention are one or more of many applications which accomplish the same goal and should not be limited as the only way as are known to those of ordinary skill in the art.

[00299] Fig. 32 illustrates a preferred application example of embodiment 3200 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to retrieve, view, and enter the graphical information into the Dev GPS system.

[00300] The handset's screen display 3120 is repeated here to show an alternative way for the GPS entry using the drag and drop icon 3130. The user can use his/her handset 102 to Google search an address location 3204 and gets the search results 3206 and 3210. He/she then just copies and drags the information in 3208 over, then drops it into the icon 3130 which the handset 102 decodes and translates into Street and Address 3246, City 3242, and State 3244. The user then

selects the Save icon 3252 to have the handset 102 transmitted the information to the Dev 106 which passes it over to the GPS 3182 as demonstrated in flow diagram 3180 of Fig. 31.

[00301] Fig. 33 illustrates a preferred application example of embodiment 3300 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to program, set up pay account and view the activity listing of the Dev Toll Fee Payment system.

[00302] The user executes the Toll Fee Pay Account icon 1134 ( Fig. 11), making his/her handset 102 transmit the command to the Dev 106 which processes said command and sends the response back to said handset 102, which displays the Toll Fee Pay Account menu as shown on its screen 3302. It shows the Toll Fee Pay Account menu 3304 with the Account Pay Setup 3310 (used to set up a toll fee pay account), Account Pay Cancel 3312 (used to cancel an existing toll fee pay account), Account Activities 3306 (to display various existing toll fee pay accounts and activities), and On Demand Toll Pay Acc Setup 3314 (to pay on demand from any toll fee collector on/from this account). Of course the driver 3752 can always elect to pay in cash. Screen 3320 and 3350 show examples of how the setup is done. Just as mentioned in the preceding and proceeding figures of this invention, examples such as these are not the only one resolution since there exist many ways to accomplish the respective applications, as are known to those of ordinary skill in the art.

[00303] Screen 3320 is the result of the user selecting the Account Pay Setup 3310 which the handset 102 navigates to after transmitting the command to the Dev 106 which responds back with the Account Pay Setup 3322. The user fills out with the Payee's web page link address 3324 in the payee's Account Pay Setup 3322 and then selects the Exe icon 3326 which the handset 102 executes and opens the Payee's webpage being displayed on screen 3330. This is where the user completes the required information, such as: his/her Bank Name 3334, Account Number 3336, Account Type 3338, and Account Name & Address 3340. He/she then selects the Exe icon 3348 which makes the handset 102 transmit the information to the payee's computer/server (not shown) to process the account payment information. When the Payee' computer/server (not shown) responds back the completion (screen 3350), it shows the Payee's name 3356 and its name code 3370, the amount it will charge 3358, the payment code 3362, the payer code 3364, and the payer's payment information 3366 and 3368. The user then executes the Ok icon 3372 making the handset transmit the confirmation to payee's computer/server, and the command (including the completion data screen 3350) to the Dev 106 which processes and saves the required payment setup data in its memory. The Dev 106 preferably transmits back the completion and confirmation to the handset (not shown). Other personal information, such as: user's phone number (not shown), and the like might be required, as are known to those of ordinary skill in the art.

[00304] Screen 3380 showing the Account Pay Activities allows the use to view past account activities, when the user selects the icon 3306 which the handset 102 navigates to after

transmitting the command to the Dev 106 which responds back with the information as shown. It shows Payee's name 3384, individual payments 3386 and 3390 and total monthly payments 3388 and 3392.

[00305] Fig. 34 illustrates a preferred example of embodiment 3400 of the present invention. It shows a general view of the pay toll stations where cars 3410, 3412 and 3414 with the Devs 106 under their hoods completing the toll fee transaction with toll collectors/transceivers 3402, 3404 and 3406. The medium 3408 is preferably WiFi or SRC 104 (Short Range Communication) devices, such as: NFC 258, Bluetooth 260, wireless/wire USB 262 and other wireless radio frequency (RF) technology. The transaction data is preferably encrypted as agreed between the Dev 106 and the payee's computer/server (not shown) during setup as mentioned in 3320, 3330 and 3350 in Fig. 33.

[00306] Figures 35 and 36 illustrate preferred examples of embodiments 3500 and 3600 of the present invention. They show the transactions taking place between the Devs 106 (residing in cars 3410, 3412 and 3414) and the Toll Collector 3402, 3404 and3406 as illustrated in Fig. 34.

[00307] As the car 3410 approaches within communicating distance of the Toll Collector 3402, the Dev 106 (in car 3410) receives data signal "Toll Collector Payment" as shown in step 3502/3602 from the Toll Collector 3402. As the Dev 106 receives the Company Name Code "9753296" 3370 of Fig. 33 and again shown in step 3602 of Fig. 36 from the Toll Collector 3402, it verifies that code "9753296" matches with one in its pay account 3370 in screen 3350 of Fig. 33. It then sends back the acknowledgement with the Payer Code "67890" (the payer transaction identifier) in 3364 (Fig. 33) and in step 3504/3604 to the Toll Collector 3402. It then receives the Payment Code (the transaction identifier) "56781234" in 3362 (Fig. 33) and again shown in step 3506/3606. The next two steps complete the transaction with the Dev 106 sending the owner's name and its pay account information in steps 3508/3608 to the Toll Collector 3402 and the Dev 106 receiving the charging payment amount in steps 3510/3610 from the Toll Collector 3402. In steps 3512/3612, the Dev 106 stores the payment with the time stamp in its memory storage after the transaction is completed. Steps 3501A, 3501B, 3501C and 3501D just show normal activities going on between the Dev 106 and the Service Provider 112 (so it can be connected to other registered handsets) while the toll collecting is taking place which use a different transmission medium.

[00308] Fig. 37 illustrates a preferred example of embodiment 3700 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to program and set up the pay account for on-demand payment of the Dev Toll Payment system.

[00309] The user executes the On Demand Toll Pay Acc. Setup icon 3314 in Fig. 33, making his/her handset 102 transmit the command to the Dev 106, which processes said command

and sends the response back to said handset 102, which displays the On Demand Toll Pay Account Setup as shown on its screen 3702.

[00310] It shows an alternative way of how to set up another type of toll payment. It also shows how the Dev 106 conducts and allows the transaction to take place when the toll payment is demanded by any toll payment collector with the voice acknowledgement or no voice acknowledgement from the driver 3752. The user fills out in screens 3702 the information, such as: user's Bank Name 3708, Account Number 3710, Account Type 3712, Account Name & Address 3714, acknowledgement "yes" or "no" for the non-voice acknowledgement selection 3716 of the audio input (voice confirmation) from the driver 3752 and the result is as shown in 3720. The user then selects the Exe icon 3738, making the handset 102 transmit the command and all the information to the Dev 106 which responds back with its processed information as shown on the handset screen 3740 "Voice Activate Toll Pay Executing! Please wait!" 3742. When the Dev 106 is done, it transmits the setup information to the handset's screen as shown in 3744, then the user executes Done icon 3746 to complete the account set up.

[00311] Flow diagram 3750 shows the transaction taking place between the Dev 106, the Toll Collector 3402 and the Driver 3752, while the chart 3770 shows the Dev 106's programming flow. It starts out in step 3753, showing the Dev 106 verifying that some amount of driving time has already taken place before the toll collection can take place just to prevent fraud (where toll collection cannot possibly happen when the car has been stationary for quite some time). In step 3754 (also shown in step 3774), the Dev 106 receives the "toll payment demand" from a toll collector 3402. The Dev 106 then outputs an audio (via speaker) 3756 (also shown in step 3776) letting the driver know the toll fee and gets the "Yes" acknowledgement 3758 (3778) from the Driver 3752. The Dev 106 then sends the account name, account number and address to Toll Collector 3402 (steps 3760 and 3780) and receives payment acknowledgement (steps 3762 and 3782) from the Toll Collector. The Dev 106 then announces the transaction completion (steps 3764 and 3784) to the driver, and finally stores the transaction record in its memory in (steps 3766 and 3786).

[00312] Fig. 38 illustrates a preferred example of embodiment 3800 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to locate his/her vehicle (controlled by the Dev 106) remotely via his/her handset.

[00313] The user executes the Locator icon 3016 in Fig. 30, making his/her handset 102 transmit the command to the Dev 106, which processes said command and sends the response back to said handset 102, which displays the Vehicle Locator command as shown on its screen 3802. It shows the Vehicle Locator command 3804 which lets the user find the vehicle's (Dev 106) current GPS location. The user fills in the required account security password 3806, and the handset 102 transmits it to the Dev 106 after the Execute icon 3808 is selected. The Dev 106 receives the

password 3806 and the command (also shown in step 3852 of chart 3850). The Dev 106 then verifies if the security password matches with the one stored in its memory, and if it does, the Dev 106 translates the command to the GPS's command format, and then sends it to the GPS 3182 (step 3854). The GPS 3182 transmits the response back to the Dev (step 3856) which translates said response and sends it to the handset 102 (step 3858) which displays the information as shown on screen 3820. Screen 3820 shows where the car is located at that moment 3822 and the graphic icon 3824, when expanded will show the detailed map 3832 as shown on screen 3830.

[00314] Fig. 39 illustrates a preferred example of embodiment 3900 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset 102 to locate a missing registered handset 102 via his/her registered handset.

[00315] The user executes the Handset Locator icon 1170/1370 (Fig. 11/13), making his/her handset 102 transmit the command to the Dev 106, which processes said command and sends the response back to said handset 102, which displays the Handset Locator command as shown on its screen 3902. After the user enters the right security password 3908 and selects the Execute icon 3914 making the inquiry handset 102 send the command and the password to the Dev 106. The Dev 106 receives and processes (as shown in step 3952 of flow chart 3950) and sends back the currently registered handsets 3910 (step 3954). In this example, the user decides to search for the missing handset 102 (phone number 916-987-6500) by highlighting it 3912 in area 3906, then selecting Exe icon 3914 again, making the inquiry handset 102 (for example, whose phone number is either 916-987-6543 or 408-234-5678) transmit the handset locator command and the required data to Dev 106. The Dev 106 processes the data, then transmits the handset locator command to the missing handset 102 (phone number 916-987-6500) in step 3956, and also transmits back its searching its status 3922 to the inquiry handset 102, as shown on screen 3920. When the Dev 106 receives the GPS position of the missing handset 102 from said handset (3958), it sends the information 3960 back to the inquiry handset 102, which displays its location 3926 accompanied by the icon 3928. The inquiry handset 102 displays the graphic location of the missing handset 102 (3932 of screen 3930) after the icon 3928 is executed (expanded).

[00316] This embodiment restricts the Dev in searching and locating only its registered handsets 102, for practical and security reason. Application and operation software residing and operating in handsets (as well as in the Dev 106) preferably can also be designed and modified in the App Server (for downloading and updating into handsets 102 and Devs 106), which can render this embodiment application more general and universal; and it will allow the users of smart handsets 102 to locate their missing smart handsets 102 via another smart handset 102 as long as the missing handsets still utilize their old phone numbers.

[00317] Furthermore, there exists a unique identifier associated with each smart handset (such as - handset/device ID parameters 542/642), which is transmitted and stored in the cellular

phone service provider database when said handset got activated and registered in said cellular service provider. Therefore, there exists a method when a missing handset can be traced by a search engine (i.e., software residing in the cellular service provider's computers/servers) with the aid of said missing handset's unique identifier provided by a handset 102 or a PC (computer) to the cellular service provider's computers/servers. And from said identifier, the missing handset's current (new or different phone number) can be translated (looked up) by said computers/servers, and thus said missing handset can be located.

[00318] Fig. 40 illustrates a preferred example of embodiment 4000 of the present invention. This exemplary embodiment preferably allows a user to program and set up the vehicle route tracking, and maximum speed limit at when and where, so the Dev 106 will record the data. The user then, can review the data and if the alert option is selected, he/she will be informed though his/her handset, when the maximum speed occurs. The data can also be stored into the company storage system for long term keeping.

[00319] The user executes the Route Tracking & Speedo-Alert icon 3010 (Fig. 30), making the handset 102 transmit the command (step 4076 in Chart 4070) to the Dev 106, which processes said command and sends the response back to said handset 102 (step 4078), which displays the Route Tracking and Speedo-Alert Program & Setup as shown on its screen 4002. It shows the Speedo-Alert and route tracking as being off (disabled) 4020 and 4021. In area 4006, entries such as: Mph (Mile per hour) or Kph (Kilometer per hour) 4408, network storage server destination – storage system where the Dev 106 stores the speed data (4010), over-speed-limit alert or no alert selection to the user's handset (4012), Speedo-Alert being on 4018 or off 4020, and the route tracking being off 4021 or on 4022. When the tracking is turned on 4022, the user can enter how many in minutes (4023) the tracking is sampled by the Dev, which obtains the time and date from the RTC 240 (Fig. 2), the speed from the Speedo-meter 4074 and the location from the GPS 3182. The user then enters data which are illustrated in screen 4032 where, for example, the user sets: the maximum speed limit at 70 Mph (4038), storage server destination 4040, no immediate alert 4044 to user's handset 102, Speedo-Alert being On 4048, and the route tracking On 4052 with the sample every 5 minutes 4053; then completes the programming by executing the Exe icon 4056, making the handset 102 send the command and information to the Dev 106 (step 4080 in Chart 4070).

[00320] The Dev then communicates the maximum speed (step 4082) to the Speedo-meter 4074. From now on (until the Speedo-Alert being turned off 4020 and 4050), whenever the vehicle is in motion, the Dev 106 gets interrupted by the Speedometer 4074 as soon as the speed goes over the speed threshold or under the speed threshold in step 4084. The Dev 106 keeps track of the time and day of the interruptions (via RTC 240 of Fig. 2), and obtains the GPS locations by communicating and acquiring them (step 4086) from the GPS 3182. The handset user, therefore, can retrieve and view the record of over-speed-limit, its duration, and the locations. This preferred

embodiment is very useful, when the principal user of the vehicle Dev 106 wants to find out the driving habit of other drivers who may be driving too fast. It can also apply to the car rental, taxi, trucking companies and the like which can keep track of the driving route of their vehicles, by having the Dev's tracking turned on (4052). This allows the Dev to take one tracking sample every 5 minutes (as is in this case) by obtaining the speed from the Speedo-meter 4074 (step 4092 of Chart 7070a) and the location from the GPS 3182 (step 4094). The tracking record be can viewed later by the user (step 4096) or downloaded at the end of the day into the Storage Server 4072 (step 4098) for company's bookkeeping, as are known to those of ordinary skill in the art.

[00321] Handset 102 (whose user programmed the Dev 106) is able to view the over maximum speed history (as shown in screen 4060) by executing the Speed-alert Listing icon 3012 (in screen 3002 of Fig. 30). This feature allows the Dev 106 to build up a history of where, when, and how long each duration, the vehicle exceeded its programmed speed limit. It displays the vehicle license plate 4066, speed limits, time, date, and its duration 4068.

[00322] Route Tracking Listing 4051 allows the user or the company to view (by executing Route Tracking Listing icon 3013 in screen 3002 of Fig. 30,) the daily routing of the vehicle when its tracking is enabled 4022/4052. It shows the driving record of the vehicle, such as: license ID 4057, the date 4059, time 4061, location 4069, and speed 4065, which can be useful when the user/owner wants to know how his/her vehicle is being used (or just the driving record of his/her vehicle).

[00323] Fig. 41A illustrates a preferred example of embodiment 4100A of the present invention. This exemplary embodiment presents preferred screen displays of the user receiving an alert in his/her handset, when an unexpected or unauthorized event happens to his/her vehicle.

[00324] The Dev 106 sends to the handset 102, a message in the handset's inbox 4102A which notifies the user that an unauthorized event happened to his/her vehicle, such as: a break-in, collision, or its removal from its parked location. The user navigates the handset 102 to the Tools screen 4114A, and selects Security Auto 4116A to find out the auto alert 4122A from the Dev 106. When the auto alert icon 4124A is executed by the user, the handset 102 navigates to screen 4130A, which contains the event information, the Dev 106 just transmitted along and among others with the alert message 4110A. Screen 4130A information includes the cause - the Break in 4134A, date and time 4136A, the location 4138A, if the car is being moved or not 4140A. It also lists the phone numbers of the registered handsets having been alerted 4142A. The icon 4144A lets the user see the graphical map where the event took place 4164A as shown in screen 4162A.

[00325] Fig. 41B illustrates a preferred example of embodiment 4100B of the present invention. This exemplary embodiment presents preferred screen displays of the user receiving an alert in his/her handset when a potentially life threatening or event may occur in his/her vehicle.

[00326] The Dev 106 sends to the handset 102, a message in the handset's inbox 4104B, which notifies the user that an abnormal and potentially dangerous situation, such as a child or pet accidentally left in his/her parking vehicle for a certain period of time. The user then can, when he/she views the message 4112B along with the Video icons 4114B and 4116B, make the appropriate decision. Video icons 4114B and 4116B let the user see the inside view of his/her vehicle 4180B and 4190B through the car interior camera, so he/she knows for sure if the situation is real or not. If there is neither a child nor a pet left in the vehicle, the user then executes the Ignore icon 4120B, which will be transmitted by the handset 102 to the Dev 106; therefore the Dev 106 stops alerting or stops sending messages (or may alert several more times every 5 minutes before completely stopping). If there is a child or a pet accidentally left inside, then the user executes the Confirm icon 4118B for confirming the alert in the alerting screen 4110B, which will be transmitted by the handset 102 to the Dev 106, which sends back the immediate actions to be taken (screen 4130B) by the user in his/her handset 102. Screen 4130B lists actions, such as: unlock the car door 4132B, lower down car windows 4134B, sound the horn 4136B, turn on the car alarm 4138B, turn the heater on 4140B, turn the A/C on 4142B, flash a light 4144B, call emergency center 4146B, and the driver is on his/her way 4148B. When the user/driver, in this example, selects the Lower down car windows and the "I am on my way" icons (4134B and 4148B) which will be transmitted by the handset 102 to the Dev 106, which sends back the statuses of said actions 4154B and 4168B being taken as shown on screen 4150b

[00327] Fig. 42 illustrates a preferred example of embodiment 4200 of the present invention. It presents steps taken to monitor the vehicle engine status and the Dev's responses when the Panic icon or vehicle emergency button is pushed.

[00328] It illustrates the Engine Status Menu 4222 when a user executes the Engine Status icon 4210, making the handset 102 send the corresponding command to the Dev 106, which communicates with the Engine Conditions I/O 205 (Fig. 2), and reads back its engine status and passes the information back to the handset 102, as displayed in screen 4220. The handset 102 displays the vehicle engine and accessory conditions 4222 which it receives from the Dev 106.

[00329] Fuel Level icon 4224 indicates how much fuel is in the tank (not shown).

[00330] Electrical icon 4226 shows the vehicle's electrical condition (not shown).

[00331] Oil Level icon 4228 indicates if any oil needs to be added (not shown).

[00332] Tire Condition icon 4232 informs user of the tire pressure and thread thickness (not shown).

[00333] Last Service icon 4234 displays the date of the most recent service of the vehicle (not shown).

[00334] Brakes icon 4236 indicates brake-pads and if they need to be replaced (not shown).

[00335] Lights icon 4238 tells the user(s) which lights are out or not working (not shown).

[00336] When the Panic icon 4214 is selected, it makes the handset 102 transmit the command to Dev 106, which will turn on the car Alarm Speaker (220 Fig. 2) and the emergency lights immediately. The Dev 106 also sends back their statuses to the handset 102 which displays the Alarm Speaker and emergency light as being ON (not shown). The Panic icon 4214 preferable functions like a toggle input. In other words, if it is selected again, the handset 102 will transmit the command to the Dev 106, which will then turn off the car Alarm Speaker (220 in Fig. 2) and emergency lights; and also send back their statuses to the handset 102 which will display the statuses as being OFF (not shown).

[00337] Fig. 43 illustrates a preferred application example of embodiment 4300 of the present invention. It presents steps taken to configure the various input and output connections of the Home Alarm System controlled by the Dev 106 via a handset 102 into more descriptive terms.

[00338] The handset 102 navigates to screen 4302, showing the Home Control and Monitor menu 4304 after the user screen-flips to the Home App Menu 1320 and selects the Home Control & Monitor icon 1326 (in Fig. 13). The handset 102 then navigates to screen 4320 when the user selects the Alarm Configure icon 4306, which makes the handset 102 send the command to the Dev 106 which sends back the configuration information as shown on said screen 4320. Screen 4320 presents the factory default home alarm security system configuration, showing the Door/window entries (4324), Motion Inputs 4328, Loud Speakers/Horns 4330 and Cameras 4332, which are all in numeric terms. The user then uses finger movement by slightly touching on the display to move screen up/down, left/right or uses icons to scroll up 4334, down 4384, left 4344, right 4352 to get to the configured information. When Door/windows entry #1 icon (4326) is selected for configuration, the handset 102 navigates to screen 4340 as it sends command and receives information back from the Dev 106. Using keyboard 4348, the user can edit the entry into a descriptive name in 4342, such as Entry 1 into Main (main entry), in order to make it more recognizable; and the final result is as shown in screens 4360, 4370 and 4380. (T symbol allows some timer delay in disabling the alarm when designated entry is used.)

[00339] Fig. 44 illustrates a preferred application example of embodiment 4400 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to monitor and view his/her home environment (controlled by the Dev 106) via his/her handset.

[00340] The user executes the Status/Monitor icon 4310 (Fig. 43), making his/her handset 102 transmit the command to the Dev 106, which processes said command and sends the response back to said handset 102, which displays the Home security Status/Monitor information, as shown

on its screen 4402. The user can check the status by selecting/highlighting individual icon/entry as shown in 4422 with pop up screen 4424 saying the MB (Master Bedroom) window is opened or the Hall icon 4434 (Motion) detector is off 4432. The user can also monitor in real-time camera inputs by selecting the Kitch icon 4446, which displays it in the pop up kitchen window 4444. The Back Yard icon 4454 and its pop up window 4452 can be expanded, by the user touching the screen 4452 which the handset 102 displays as shown in full screen 4474 or closing it by executing close area 4456.

[00341] Fig. 45 illustrates a preferred application example of embodiment 4500 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to program, control and monitor his/her home security system (controlled by the Dev 106) remotely via his/her handset.

[00342] The handset 102 navigates to screen 4502 when the Program/Control icon 4308 (Fig. 43) is executed by the user, making the handset 102 transmit the command to the Dev 106, which sends back the control information to the handset 102 which displays it on 4502. This feature allows the user to use either the keyboard control key 4506 or keypad control key 4536; so either the keyboard 4508 or keypad 4546 can be used to control and program the Dev 106 for the home security functions. Screen 4502 shows that the home security system is off and not ready 4504. The user can find out more by pushing the Program icon 4548, which makes the handset 102 display the cause “Master Bedroom … opened” 4534 after it gets the information back from the Dev 106. The Dev 106 can bypass the Master bedroom entry when the user selects the bypass icon (command) 4568, which causes the handset 102 to display Bypass choices 4564 among which, box 4566 is selected, to bypass the Master Bedroom which makes the handset 102 send said command to the Dev 106. The user can finally turn the alarm on using his/her handset 102 by selecting the Camera Motion Alert icon 4570 and the Activate Alarm Away icon 4574, which make the handset 102 navigate to screen 4580, showing the alarm is on and away (all interior motion detection is on) plus Camera Motion detection 4582. The user can always disarm (turn the alarm off) by using either the OFF icon 4556 or the On/Off icon 1336/1338 (Fig. 13). The Camera Motion Alert icon 4570, (when enabled,) will alert user when there are any changes in any camera/video inputs 312 (Fig. 3), while the Camera Motion Sound icon 4572 also let the user make sound to scare off potential intruders. The Dev 106 will send a message and the videos of the camera input changes 4570 to user’s handset 102 to alert of any activity outside of the house (as shown in Fig. 47). The Camera Motion Alert 4570 is used in cases where the owner wants to know when a truck is making a delivery, a gardener taking care of the landscape or a neighbor stopping by picking up the mail, while Camera Motion Sound 4572 will also make sound to defer any unwanted guests, while the family is being away.

[00343] Fig. 46 illustrates a preferred example of embodiment 4600 of the present invention. This exemplary embodiment presents preferred screen displays when user receives an alert in his/her handset, when an unexpected or unauthorized event happened to his/her home.

[00344] The handset 102 navigates to screen 4602 informing the user of a message and alert information data from the Dev 106 in the inbox 4606. The user scrolls to screen Tools 4612 and selects Security Home 4614 to find out said information in the home alert, screen 4622, from the Dev 106. When the home alert icon 4624 is executed by the user, the handset navigates to screen 4632 which contains event information the Dev 106 just sent along and among others with the alert message 4606. It shows BR2 (Bedroom 2) 4638 is where the break-in happened and Hall and LR (Living Room) motion detectors 4640 also detected it. Screen 4652 shows the pop-up icon 4656 when the BR2 icon 4638 is selected, detailing the time and date. Screen 4660 shows the pop-up icon 4664 when either the SPK 1 or SPK2 icon 4642 is selected, detailing the time the alarm sounded 4668, and the alerted phone numbers (4672) the alarm sent messages to.

[00345] Fig. 47 illustrates a preferred example of embodiment 4700 of the present invention. This exemplary embodiment presents preferred screen displays when user receives an alert in his/her handset when a video camera detects changes around his/her house.

[00346] The handset 102 navigates to screen 4710 informing the user of message 4712 and alert information data (video) 4722 from the Dev 106 in the inbox 4720. The user finds out by executing the House icon 4724 which contains several camera shots, showing screen changes, when user flips/scrolls through - from screen 4730 (taken 6/14/13 at 10:23AM) to screen 4740 with an object 4744 (taken 6/14/13 at 10:24AM) 4742. This alert takes place when the user turned the alarm on with the Camera Motion Alert icon 4570 enabled as previously done in Fig. 45.

[00347] Figures 48 and 49 illustrate a preferred application example of embodiments 4800 and 4900 of the present invention. The exemplary embodiment 4800 presents preferred steps taken by a user in his/her handset to add household appliances/equipments into the Dev's Home Control and Monitor System, while the exemplary embodiment 4900 presents the communication interaction of these devices within the SRC network (except Wi-Fi).

[00348] The user executes the Household Appliances icon 1344 (Fig. 13), making his/her handset 102 transmit the command to the Dev 106, which processes said command and sends the response back to said handset 102, which displays the Household Appliances menu, as shown on its screen 4802. The Home Appliances menu 4804 lets the user add (4806) home appliances/equipments or accessories that he/she can control remotely using the handset 102, or remove 4808 them when they are no longer in use, when he/she is at home or away from home.

[00349] The user executes the Appliance Add icon 4806 which makes the handset 102 send the command to the Dev 106, which processes and transmits back the appliances/equipments it

discovers on screen 4810. This feature allows the handset 102 to command the Dev 106 either to ignore 4828 or connect 4829 the Entry Door Lock 4814, Help Alert 4816, Heating and Air conditioning 4818, Cable Box 4820, Garage Opener 4822, Lawn Sprinkler 4824, Electric Meter 4826 and Door Bell & Intercom 4827, by selecting and checking appropriate boxes as shown in Home Appliances Discovery screen 4830. The user then executes Exe icon 4848, making the handset 102 send the command to the Dev 106, which processes and transmits back the corresponding software applications: Door Lock 4854, Help Alert 4856, Heat/Air 4858, Cable Box/TV 4860, Garage Opener 4862, Sprinkler controller 4864, Electric Meter 4866, and Door Bell & Intercom 4868, from said appliances as shown in the Home Appliances screen 4850. The user then executes the Done icon 4868a which makes the handset 102 navigate back to screen 4802, being shown as screen 4851. In screen 4851, the Home Appliances menu 4853, comprises the eight newly additional household appliances controlling icons: Door Lock 4859, Help Alert 4861, Heat/Air 4863, Cable Box/TV 4865, Garage Opener 4867, Sprinkler controller 4869, Electric Meter 4871 and Door Bell & Intercom 4873. The Door Lock 1332, Unlock 1334 and the Garage Opener icons 1340 are also copied by the Dev's Home App 604 into the Home App Menu 1322 to make it more convenient (it requires fewer screen steps) for the user to navigate to, when he/she needs to use said function.

[00350] Chart diagram 4870 and Fig. 49 show the interaction between the handset 102, the Dev 106 and all the appliances – Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, and Door Bell & Intercom 4886 (and the like, such as: Water Meter, Heating and Cooking Gas Meter). It starts at step 4881 when the Dev 106 communicates with the handset 102, after it receives the Home Appliances Connecting command from the handset 102 and after the user executes the feature as shown in screen 4830.

[00351] The Dev 106 connects and communicates with the Door Lock step 4883 (also shown as the communication link/medium 4883 in Fig. 49), and receives its software application step 4883A which the Dev 106 also passes its copy to the handset step 4883B, showing in the form of the icon 4854 (DA).

[00352] The Dev 106 connects and communicates with the Help Alert step 4885 (also shown as the communication link/medium 4885 in Fig. 49), and receives its software application step 4885A which the Dev 106 also passes its copy to the handset step 4885B, showing in the form of the icon 4856 (HA).

[00353] The Dev 106 connects and communicates with the AC/Heat controller step 4887 (also shown as the communication link/medium 4887 in Fig. 49), and receives its software application step 4887A which the Dev 106 also passes its copy to the handset step 4887B, showing in the form of the icon 4858 (AA).

[00354] The Dev 106 connects and communicates with the Cable Box/TV step 4889 (also shown as the communication link/medium 4889 in Fig. 49), and receives its software application step 4889A which the Dev 106 also passes its copy to the handset step 4889B, showing in the form of the icon 4860 (CA).

[00355] The Dev 106 connects and communicates with the Garage Opener step 4891 (also shown as the communication link/medium 4891 in Fig. 49), and receives its software application step 4891A which the Dev 106 also passes its copy to the handset step 4891B, showing in the form of the icon 4862 (GA).

[00356] The Dev 106 connects and communicates with the Sprinkler step 4893 (also shown as the communication link/medium 4893 in Fig. 49), and receives its software application step 4893A which the Dev 106 also passes its copy to the handset step 4893B, showing in the form of the icon 4864 (SA).

[00357] The Dev 106 connects and communicates with the Electric Meter step 4895 (also shown as the communication link/medium 4895 in Fig. 49), and receives its software application step 4895A which the Dev 106 also passes its copy to the handset step 4895B, showing in the form of the icon 4866 (EA).

[00358] It is preferably that the Electric Meter 4884 is embedded or equipped with an identifier (such as S/N, location address) in its communication with any wireless device and also during the Dev's home appliances discovery phase (not shown in screen 4810) so it can be distinguished by the user from the ones of his/her neighbors.

[00359] The Dev 106 connects and communicates with the Door Bell & Intercom step 4897 (also shown as the communication link/medium 4897 in Fig. 49), and receives its software application step 4897A which the Dev 106 also passes its copy to the handset step 4897B, showing in the form of the icon 4868 (BA).

[00360] The communication medium, in this case, between the Dev 106 and the appliances (Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, and Door Bell & Intercom 4886), is in SRC (Short Range Communication) network 104; while the communication between the Dev 106 and the handset 102 can be either through SRC or cellular network 118.

[00361] Alternatively, the software applications which were transmitted previously from the household appliances to the Dev 106 and to the handset 102 (in graph 4870), such as: Icons: DA 4854, HA 4856, AA 4858, CA 4860, GA 4862, SA 4864, EA 4866, and BA 4868 preferably can be the URLs (app download address links or hyperlinks), which the user then uses to download the appropriate online applications into his/her handset 102, which then transmits them to the Dev 106.

[00362] The user can also download the household applications online, using App Download icon 4809/4875 on handset display screen 4802/4851.

[00363] Similarly identical steps preferably can be applied to the Integrated Smart Pet Door (its Door 6190, Speakers 6192, and Cameras 6194), and a plurality of other household appliances/equipments, by the handset via the Dev 106, to discover and connect to said appliances/equipments, and receive the applications or hyperlinks from these devices. The handset user then will be able to program, control, and monitor these household appliances/equipments via his/her handset 102.

[00364] Figures 50 and 51 illustrate a preferred application example of embodiments 5000 and 5100 of the present invention. The exemplary embodiment 5000 presents preferred steps taken by a user in his/her handset to add household appliances/equipments into the Dev's Home Control and Monitor system while the exemplary embodiment 5100 presents the communication interaction of these devices within the Wi-Fi network.

[00365] The user executes the Household Appliances icon 1344 (Fig. 13), making his/her handset 102 transmit the command to the Dev 106, which processes said command and sends the response back to said handset 102, which displays the Household Appliances menu, as shown on its screen 5002. The Home Appliances menu 5004 lets the user add 5006 home appliances/equipments or accessories that he/she can control remotely using the handset 102 or remove 5008 them when they no longer in use, when he/she is at home or away from home.

[00366] The user executes the Appliance Add icon 5006 which makes the handset 102 send the command to the Dev 106 which processes and transmits back the appliances/equipments it discovers on screen 5010. This feature allows the handset 102 to command the Dev 106 to either ignore 5028 or connect 5029 the Entry Door Lock 5014, Help Alert 5016, Heating and Air conditioning 5018, Cable Box 5020, Garage Opener 5022, Lawn Sprinkler 5024, Electric Meter 5026, and Door Bell & Intercom 5027 by selecting and checking appropriate boxes as shown in Home Appliances Connecting screen 5030. The user then executes Exe icon 5048, making the handset 102 send the command to the Dev 106, which processes and transmits back the corresponding software applications: Door Lock 5054, Help Alert 5056, Heat/Air 5058, Cable Box/TV 5060, Garage Opener 5062, Sprinkler controller 5064, Electric Meter 5066, and Door Bell & Intercom 5068, from said appliances as shown in the Home Appliances screen 5050. The user then executes the Done icon 5068a which makes the handset 102 navigate back to screen 5002, being shown as screen 5051. In screen 5051, the Home Appliances menu 5053, comprises the eight newly additional household appliances controlling icons: Door Lock 5059, Help Alert 5061, Heat/Air 5063, Cable Box/TV 5065, Garage Opener 5067, Sprinkler controller 5069, Electric Meter 5071 and Door Bell & Intercom 5073. The Door Lock 1332, Unlock 1334, and the Garage Opener

icons 1340 are also copied by the Dev's Home App 604 into the Home App Menu 1322 to make it more convenient (it requires fewer screen steps) for the user to navigate to, when he/she needs to use said function.

[00367] Chart diagram 5070 and Fig. 51 show the interaction between the handset 102, the Dev 106 and all the appliances – Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, and Door Bell & Intercom 4886 (and the like, such as: Water Meter, Heating and Cooking Gas Meter …). It starts at step 5081 when the Dev 106 communicates with the handset 102 after it receives the Home Appliances Connecting command from the handset 102 and after the user executes the feature as shown in screen 5030.

[00368] The Dev 106 connects and communicates with the Door Lock step 5083 (also shown as the communication link/medium 5083 in Fig. 51), and receives its software application step 5083A which the Dev 106 also passes its copy to the handset step 5083B, showing in the form of the icon 5054 (DA).

[00369] The Dev 106 connects and communicates with the Help Alert step 5085 (also shown as the communication link/medium 5085 in Fig. 51), and receives its software application step 5085A which the Dev 106 also passes its copy to the handset step 5085B, showing in the form of the icon 5056 (HA).

[00370] The Dev 106 connects and communicates with the AC/Heat controller step 5087 (also shown as communication link/medium 5087 in Fig. 51), and receives its software application step 5087A which the Dev 106 also passes its copy to the handset 102 step 5087B, showing in the form of the icon 5058 (AA).

[00371] The Dev 106 connects and communicates with the Cable Box/TV step 5089 (also shown as the communication link/medium 5089 in Fig. 51), and receives its software application step 5089A which the Dev 106 also passes its copy to the handset step 5089B, showing in the form of the icon 5060 (CA).

[00372] The Dev 106 connects and communicates with the Garage Opener step 5091 (also shown as the communication link/medium 5091 in Fig. 51), and receives its software application step 5091A which the Dev 106 also passes its copy to the handset step 5091B, showing in the form of the icon 5062 (GA).

[00373] The Dev 106 connects and communicates with the Sprinkler step 5093 (also shown as the communication link/medium 5093 in Fig. 51), and receives its software application step 5093A which the Dev 106 also passes its copy to the handset step 5093B, showing in the form of the icon 5064 (SA).

[00374] The Dev 106 connects and communicates with the Electric Meter step 5095 (also shown as the communication link/medium 5095 in Fig. 51), and receives its software application step 5095A which the Dev 106 also passes its copy to the handset step 5095B, showing in the form of the icon 5066 (EA).

[00375] It is preferably that the Electric Meter 4884 is embedded or equipped with an identifier (such as S/N, location address) in its communication with any wireless device and also during the Dev's home appliances discovery phase (not shown in screen 5110) so it can be distinguished by the user from the ones of his/her neighbors.

[00376] The Dev 106 connects and communicates with the Door Bell & Intercom step 5097 (also shown as the communication link/medium 5097 in Fig. 51), and receives its software application step 5097A which the Dev 106 also passes its copy to the handset step 5097B, showing in the form of the icon 5068 (BA).

[00377] The communication medium, in this case, between the Dev 106 and the appliances (Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, and Door Bell & Intercom 4886), is in Wi-Fi (wire/wireless LAN) network 104; while the communication between the Dev 106 and the handset 102 can be either through Wi-Fi or through cellular network 118.

[00378] Alternatively, the software applications which were transmitted previously from the household appliances to the Dev 106 and to the handset 102 (in graph 5070), such as: Icons: DA 5054, HA 5056, AA 5058, CA 5060, GA 5062, SA 5064, EA 5066, and BA 5068 preferably can be the URLs (app download address links or hyperlinks), which the user then uses to download the appropriate online applications into his/her handset 102, which then transmits them to the Dev 106.

[00379] The user can also download the household application online using the App Download icon 5009/5075 on the handset display screen 5002/5051.

[00380] Similarly identical steps preferably can be applied to the Integrated Smart Pet Door (its Door 6190, Speakers 6192 and Cameras 6194), and a plurality of other household appliances/equipments, by the handset via the Dev 106, to discover and connect to said appliances/equipments, and receive the applications or hyperlinks from the devices. The handset user then will be able to program, control, and monitor these household appliances/equipments via his/her handset 102.

[00381] Fig. 52 illustrates a preferred application example of embodiment 5200 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to remove a household appliance/equipment from the Dev's Home Control and Monitor system

[00382] This feature allows user to remove appliance devices from the menu as selected by highlighting the Appliance Remove icon 5057, which makes the handset 102 navigate to screen Home Device Removal 5202. The user then can select devices to be removed by screen touching appropriate remove boxes such as: Door Lock 5206, Help Alert 5208, Heating and A/C 5210, Cable Box 5212, Garage Door Opener 5214, Sprinkler 5216, Electric Meter 5218, and Door Bell & Intercom 5220. The handset screen "Home Device Removal" 5230 shows Device #6 - Sprinkler 5244 (Toro-356) being selected to be removed. When user executes the Exe icon 5250, making the handset 102 transmit the command to the Dev 106 and wait for the Dev's completion response. When the handset 102 receives the response back from the Dev 106, it means the lawn sprinkler (application software) has been removed from the Dev 106. The handset 102 then removes the sprinkler application software from its memory. The Home Appliances menu 5282 shows its updated content with the sprinkler no longer the listed as a house-hold device. (The handset software preferably will not remove the device software application until the Dev 106 completes its removal function – thus prevent partial removal of the application software and maintain synchronization between the Dev 106 and the handset 102).

[00383] Fig. 53 illustrates a preferred application example of embodiment 5300 of the present invention. The exemplary embodiment 5300 presents the communication interaction when both the handset and the Dev communicate with the household appliances/equipments within the SRC network (except Wi-Fi).

[00384] It illustrates the interaction between the handset 102, the Dev 106, and various house-hold appliances/equipments: Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, Door Bell & Intercom 4886 (plus the Integrated Smart Pet Door 6190, its Speaker 6192 and its Camera 6194, and the plurality of other devices with supporting apps not shown) when the user is at home. The Dev 106 and the handset 102 detect and communicate with each other via SRC 5303 and therefore the handset 102 also communicates directly to all the above house-hold appliances and control them via SRC media: Door Lock 5304, Help Alert 5306, AC/Heat controller 5308, Cable Box/TV 5310, Garage Opener 5312, Sprinkler 5314, Electric Meter 5316 and Door Bell & Intercom 5318 while (previously) the Dev 106 also communicated with them: Door Lock 4883, Help Alert 4885, AC/Heat controller 4887, Cable Box/TV 4889, Garage Opener 4891, Sprinkler 4893, Electric Meter 4895 and Door Bell & Intercom 4897 (Figures 48, 49 and 53).

[00385] Fig. 54 illustrates a preferred application example of embodiment 5400 of the present invention. The exemplary embodiment 5400 presents the communication interaction when only the handset communicates actively with the household appliances/equipments within the SRC network (except Wi-Fi).

[00386] It illustrates the interaction between the handset 102 and various house-hold appliances/equipments: Door Lock 4872, Help Alert 4874, AC/Heat controller 4876, Cable Box/TV 4878, Garage Opener 4880, Sprinkler 4882, Electric Meter 4884, Door Bell & Intercom 4886 (and multiple other devices with supporting software not shown) when the user is at home. The Dev 106 and the handset 102 detect and communicate with each other via SRC 5303 but the Dev 106 ceases communicating with the household appliances because it detects the presence of the handset within its SRC medium. It only responds to the commands from the handset 102 if it detects no responses from the corresponding household appliances for said commands.

[00387] Fig. 55A illustrates a preferred example of embodiment 5500A of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to program, control, record, and view the Cable Box/TV of the Dev's Home Control and Monitor system.

[00388] When the Cable Box/TV icon 4865/5065 in the Home Appliances menu 4851/5051 (Fig. 48/50) is executed, the handset 102 transmits the command to the Dev 106, which in turns processes said command and passes it to the Cable/Satellite TV 4878 (Fig. 48), receives the response from said Cable/Satellite TV 4878, and processes said response and passes it back to the handset 102, which displays the information, as shown on its screen 5502.

[00389] Remote control 5516 and Channel surfing screen 5504 are controlled by CA software 4860/5060 in Fig. 48/50, which has been transmitted from the Cable/Satellite TV 4878 (or downloaded from the web), with one copy in the Dev 106 and one in the handset 102. Every selection (icon highlighted/screen button touched) in 5504 and 5516 makes the handset 102 transmit commands to the Dev 106, which in turn, transmits them to the Cable/Satellite TV 4878, and if any response required, will be transmitted back from the Cable/Satellite TV 4878 via the Dev 106, to the handset 102, which displays it on screen 5502. The news (News icon 5510) on channel 4 KYON can be watched on screen by touching it as shown or highlighting and then by touching the OK icon 5520.

[00390] When the Record icon 5518 is selected, the handset 102 sends commands to Cable/Satellite TV 4878 via the Dev 106, which passes back the response from the Cable/Satellite TV 4878 to the handset 102, which displays it as Recorded Programs (screen 5530). Remote control 5518 reduced in size 5518A, since at that moment it is not needed. The user can watch recorded program such as: Cops icon 5536, as shown by highlighting it and selecting (executing) the Play icon 5540 in the action menu 5538.

[00391] Fig. 55B illustrates a preferred example of embodiment 5500B of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to open or close the Garage Opener of the Dev's Home Control and Monitor system.

[00392] The handset 102 navigates to screen 5560 when the user hovers over the handset's Garage Opener icon 4867/5067 for a second or more (until the handset 102 changes screen) presenting remotely the status of the Garage Door Opener 5560. The user then can open/close the garage when he/she is far away from home, and also knows if it is opened or closed as displayed on screen 5562.

[00393] Button control 5570 and the display 5562 are controlled by GA software (4862/5062 in Fig. 48/50) which has been transmitted from the Garage Opener 4880 (or downloaded from the web), with one copy into the Dev 106 and one into the handset 102.

[00394] On the other hand, the user can open/close the garage door (short range via SRC) by slight touching the Garage Opener icon 4867/5067, or by touching the icon1340 to open or close the garage, just like the regular garage opener.

[00395] Fig. 56A illustrates a preferred example of embodiment 5600A of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to program, control, and view the Central Heating and Air Conditioner of the Dev's Home Control and Monitor system.

[00396] When the handset Heat/Air icon 4863/5063 in Home Appliances 4851/5051 (Fig. 48/50) is executed, the handset 102 transmits the command to the Dev 106, which in turns processes said command and passes it to the Heat/Air system 4876 (Fig. 48/50), receives the response from said Heat/Air system 4876, and processes said response and passes it back to the handset 102, which displays the information, as shown on its screen 5602.

[00397] Keypad control 5606 and display status 5604 are controlled by AA software 4858/5058 in Fig. 48/50 which has been transmitted from the Heat/Air 4876 (or downloaded from the web), with one copy into the Dev 106 and one into the handset 102. Every selection (icon highlighted/screen button touched) in 5606 (5608, 5610 and 5612) makes the handset 102 transmit command to the Dev 106, which in turn transmits it to the Heating/Air conditioner 4876 and if any response required, will be transmitted back from the Heating/Air conditioner 4876 via the Dev 106 to the handset 102 which displays it on screen 5602. The screen 5604 shows the H/A fan is on, in automatic mode, and the house is at 72 degrees F. The handset 102 navigates to screen 5630, when the user programs the heater (by keying in Prog icon 5614, Heat icon 5620, Time icon 5616, keypad icon 5612 and Set icon 5618) to turn on Heat/Air Conditioner 4876 from 10AM to 6PM to 78 Degrees F, as are known to those of ordinary skill in the art.

[00398] Fig. 56B illustrates a preferred example of embodiment 5600B of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to open or close the House Entry of the Dev's Home Control and Monitor system.

[00399] When the handset Door Lock icon 4859/5059 in Home Appliances 4851/5051 (Fig. 48/50) is executed, the handset 102 transmits the command to the Dev 106, which in turns processes said command and passes it to the Door Lock 4872 (Fig. 48/50), receives the response from said Door Lock 4872, and processes said response and passes it back to the handset 102, which displays the information, as shown on its screen 5650.

[00400] Screen 5650 shows the status of the door lock every time icon 5656 is touched; it toggles between unlocked (message 5654) and locked (message 5664). Screen touch control icon 5656/5666 and the display screen 5652/5662 are controlled by DA software 4854/5054 in Fig. 48/50 which has been transmitted from the Door Lock 4872 (or downloaded from the web), with one copy into the Dev 106 and one into the handset 102.

[00401] Fig. 57 illustrates a preferred example of embodiment 5700 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to program, set up and view the indoor/outdoor watering control of the Dev's Home Control and Monitor system.

[00402] When the handset Sprinkler icon 4869/5069 in Home Appliances 4851/5051 (Fig. 48/50) is executed, the handset 102 transmits the command to the Dev 106, which in turns processes said command and passes it to the Sprinkler 4882 (Fig. 48/50), receives the response from said Sprinkler 4882, and processes said response and passes it back to the handset 102, which displays the information, as shown on its screen 5702.

[00403] Keypad control 5706 and the display 5704 are controlled by SA software 4864/5064 in Fig. 48/50 which has been transmitted from the Sprinkler 4882 (or downloaded from the web), with one copy into the Dev 106 and one into the handset 102. Every selection (icon highlighted/screen button touched) in 5706 (5708, 5710 and 5712), makes the handset 102 transmit command to the Dev 106 which in turn transmits it to the Lawn Sprinkler controller 4882 and if any response required will be transmitted back from the Lawn Sprinkler controller 4882 to the Dev 106 and from the Dev 106 to the handset 102 which appears on its display screen 5702. The handset 102 navigates to screen 5730 when the user programs to turn the sprinkler system on starting at 8AM duration 60 minutes; to screen 5750 on Monday, Wednesday and Friday 5752; and to screen 5770 for stations 1, 2 and 3 (screen 5772).

[00404] Figures 58 and 59 illustrate preferred examples of embodiments 5800 and 5900 of the present invention. The exemplary embodiment 5800 presents preferred steps taken by a user in his/her handset to set up the payment account, view the meter reading, and program the Electric Meter of the Dev's Home Control and Monitor system.

[00405] When the user executes the Electric Meter icon 4871/5071 in Home Appliances 4851/5051, which makes the handset 102 navigate to Electric Meter Menu 5804, as shown on its

screen 5802. The Electric Meter Menu 5804 contains Account Setup 5810, which when programmed, allows the interaction between the Dev 106, the handset 102, the electric meter 4884, and the utility company 5982. The user then can pay the electricity bill online using the handset 102 or the utility company 5982 will be paid automatically every month. Meter Reading 5806 and Account Payment 5808 let user view current electric meter reading and past account billings (screen 5954). The Pay online icon 5812 lets user pay any account outstanding and the Monthly Usage Inf. Icon 5814 let user view past account usage activity 5822.

[00406] The user selects the Account Setup icon 5810 which makes the handset 102 navigate to screen 5820 showing the Account Application Setup 5822. It requires the user to fill out user's name 5826, address 5828, handset phone number 5830 and Utility's web address 5832 (Utility web address 5832 preferably came pre-filled with electric meter application EA 4866/5066 in Fig 48/50; otherwise user obtains it from the said company either by phone, text message, downloading or any other means). The handset screen 5820a shows the required information filled by the user, who then executes the Exe icon 5834a, which makes handset 102 transmit the information 5824a to the Utility Company 5982 (also as shown in step 5984, flow diagram 5980). The Utility Company 5982 processes the application data, and then transmits back (step 5985) to the user's handset 102, the partially filled Account Payment Setup information 5844, as shown in the handset screen 5840. Window 5844 shows the Utility Company name 5846, the user/customer assigned account number 5848, the Electric Meter S/N 5850 (Serial Number or identification number since each meter is used to measure electricity usage and hooked to its corresponding residence/business address. It is for device identification during its communication with the Dev since there might be a plurality of devices in close proximity i.e., apartment or high rise building) and the utility company payment web address (URL) 5852.

[00407] Field 5844 also shows customer's name, address, and phone number 5854 and 5856 (filled out previously in screen 5820a). The user fills out the remainder information, such as: Bank Name 5858, Payer's Bank Account Number 5860 and type of payment 5862. When the user finishes as shown in screen 5840a, with the Auto Pay icon 5863a unchecked, and executes Exe icon 5864 which makes the handset 102 transmit back (step 5986) to the Utility Company 5982 the information as shown in field 5844a. The handset 102 also transmits a copy of it 5844a to the Dev 106 as shown in step 5987 and the Dev 106 in turn communicates with the Electric Meter 4884 as shown in step 5988 using the S/N 5850a to make sure it communicates with and reading from the right device. The Dev 106 also uses the utility company URL 5852a to send the month electricity reading to the utility company 5982 account payment department. Auto payment box 5863 (checked) allows user to pay automatically every month.

[00408] On the first of each month (reading from RTC 240), the Dev 106 communicates and reads (step 5990) the electricity usage from the Electric Meter 4884 and transmits the reading

information 5920 (screen 5902) as shown in step 5991 to the Utility Co. 5982. The utility company 5982 processes and sends (step 5992) the bill 5924 to user's handset 102 as shown in screen 5922. The field 5926 outlines the user's monthly electricity usage 5936 and the required payment 5938 for the month 5940. It also shows that the payment information is on file 5942 (URL link to the utility company database server) and can be edited 5950 if there are any changes in the payment information. The payment information also is hyper-linked to the Pay online icon 5946, which when executed by the user, makes the handset 102 transmit the information (step 5993) to the Utility Co. 5982, which transmits back (step 5994) the payment information screen 5954. The user then can make the payment by executing 5968, which makes the handset send the payment command, and receives (step 5995) the confirmation 5970 in the inbox from the Utility Co. 5982.

[00409] The application software allows the Dev 106 to communicate with the Electric Meter 4884 and the handset 102 is controlled by EA software 4866/5066 in Fig. 48/50 which has been transmitted from the Electric Meter 4884 (or alternatively downloaded from App Server whose URL provided by the Electric Meter 4884) with one copy into the Dev 106 and one into the handset 102.

[00410] This embodiment can also be similarly applicable to the Water Meter, Cooking & Heating Gas Meter and the like.

[00411] Fig. 60A illustrates a preferred activation example of embodiment 6000A of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to monitor, and talk with the Help Alert wearer, via the Dev's Home Appliances system remotely.

[00412] It illustrates one aspect of the invention when handset user or help alert wearer needs to communicate with each other. The Dev 106 communicates with Help Alert device 4874, so the user can monitor (via his/her handset) the well being of the person who wears said device. The device 4874 preferably consists of a wireless camera and the voice recognition integrated circuit so the Help Alert 4874 connects to the Dev 106, which transmits a message and rings up the user's handset 102, in order for its wearer to communicate with the handset user. When the device wearer says a sentence, such as: "Hi Dave (i.e., name of handset's user), I want to talk to you", the Help Alert device 4874 transmits the command to the Dev 106, which in turn rings up the user's handset, and also preferably transmits a text message. When the user answers the call, then the conversation takes place. As soon as the user hangs up or if there is no audio variation for 5 minutes, the Dev 106 will stop the audio communication to the Help Alert device 4874.

[00413] When the user selects the Help Alert icon 6061, the handset 102 navigates to screen 6002 where the Help Alert Menu 6004 consists of the Talk icon 6008 and the Monitor icon 6006. When the user selects the Monitor icon 6006, the handset will transmit the command to the Dev 106

which connects to the Help Alert device 4874 camera and transmits back to the handset 102 what the camera sees and thus allows the user to monitor what is in front of the wearer (to monitor the well-being of his/her elder parent for instance). When the user selects the Talk icon 6008, the handset will transmit the command to the Dev 106 which then answers and connects to the Help Alert device 4874 audio, and thus allows the conversation to take place. The Help Alert device 4874 also preferably is able to detect vibration, such as a fall so that it can send commands to the Dev 106, which alerts the user of such an event, and he/she can immediately monitor and talk to the wearer.

[00414] The application software allows the Dev 106 to communicate with the Help Alert 4874 and the handset 102 is controlled by the HA software 4856/5056 in Fig. 48/50, which has been transmitted from the Help Alert 4874 (or alternatively downloaded from App Server whose URL provided by the Help Alert 4874), with one copy in the Dev 106 and one in the handset 102.

[00415] Fig. 60B illustrates a preferred activation example of embodiment 6000B of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset to answer, talk, and monitor the visitor, who rings the door bell and intercom via the Dev's Home Control and Monitor System remotely.

[00416] When a visitor rings the door bell (step 6082 in flow diagram 6080), the Bell & Intercom 4886 transmits command (step 6084) to the Dev 106 which alerts (step 6086) the user via his/her handset screen 6020. The user then scrolls to the inbox 6040 and sees the Door Bell ringing message 6042. The user then executes the Talk icon 6044 (in order to answer to door), which makes the handset 102 navigate to the Door Bell Intercom menu 6052 in screen 6050. This makes the handset 102 establish the cellular connection (step 6088) to the Dev 106, which conducts the audio duplex transmission (6090) with the front door intercom (Door Bell & Intercom 4886 in Fig. 48/50), thus allows the user to talk to the bell ringer, through his/her handset. The Door Bell Intercom menu 6052 allows the user and the visitor to communicate with each other, through the front door speaker and microphone, without the visitor realizing that the user (i.e., the house owner) may not be at home, at the moment. The user can also put the conversation on speaking phone 6054, make it mute 6056, or put it temporarily on hold 6058. This embodiment makes the unexpected visitor believe that somebody is at home, and any intention of breaking into the house therefore hopefully can be avoided.

[00417] The application software which allows the Dev 106 communicate with the Door Bell & Intercom 4886 and the handset 102 is controlled by the BA software 4868/5068 in Fig. 48/50 which has been transmitted from the Door Bell & Intercom 4886 (or alternatively downloaded from the App Server whose URL provided by the Door Bell & Intercom 4886) with one copy into the Dev 106 and one into the handset 102.

[00418] Fig. 61 illustrates a preferred activation example of embodiment 6100 of the present invention. This exemplary embodiment presents preferred steps taken by a user in his/her handset in order to program, set up, and control the Integrated Smart Pet Door (its door, speakers and cameras), via the Dev's Home Control and Monitor System remotely.

[00419] The user sets up the Pet Program and Monitor system by executing the Smart Pet Door icon 6077 (in screen 6051 of Fig. 60), making the handset 102 navigate to the Smart Pet Door Control menu 6102. The Program & Setup icon 6106 will let the user schedule his/her pets' need to go out doing their things and the Command icon 6108 allows the user to command its accessories to do certain task relating to their daily needs in real time.

[00420] The Program and Setup control (screen 6112 after the user executes icon 6106) lets the user schedule (Add schedule icon 6116), such as: schedule #1 (6120) and schedule #2 (6124) showing the time for the pets to go out of the house and back in (6122). It also lets user delete old schedules (Delete schedule icon 6118). The user has the option of recording the scene in order to play back if he/she needs to verify that the schedule meets their needs. This exemplary embodiment shows that the user schedules the pets do go out three times a day, and each lasts 20 minutes (8:00 AM-8:20 AM, 12 PM-12:20 PM and 04:20 PM-04:20 PM). Chart 6160 illustrates the actions taken by the Dev 106 at schedule time. At the starting time (i.e., 8:00AM), the Dev 106 sends the Open Door command to the Pet Door 6190 (step 6166), transmits the audio recording the owner's calling the pets on the speaker 6192 (step 6168) to trick them out of the house and optionally turns on the camera (step 6164). At the end time (i.e., 8:20AM), the Dev 106 transmits the audio recording the owner's calling the pets on the speaker 6192 (step 6168) to induce them back into the house, sends the Close Door command to the Pet Door 6190 (step 6166) and turns off the camera (step 6164).

[00421] The Smart Pet Command menu (screen 6140 after the user executes icon 6108) allows the user to open or close the pet door icon 6144 (steps 6172 and 6174) in real time, and let him/her view its status icon 6145. The user can try calling the pet through the speaker 6192 while holding on Call Pets icon 6146 (also shown in steps 6176 and 6178). He/she can record his/her audio (his/her voice onto the Dev106 ) call icon 6150 calling to the pets, to play it on the speaker, or play it back to listen to it (icon 6148). The user can record the video and play it back (icons 6152 and 6154, and also in steps 6180 and 6182). This allows the owner the peace of mind on the daily needs of his/her pets and there is no urgency about getting home on time, or asks somebody to do the task.

[00422] Similarly the Dev 106 can be programmed to transmit commands to the Smart Pet Feeder (6079 in screen 6051 of Fig. 60A)) and schedule it of the pet feeding time, the right amount of food and alert the handset 102 when the feeder needs to be refilled. Preferably the owner can also program the Dev 106 via the handset 102 to cancel these tasks when they are no longer needed; and

remove their software applications from both the handset 102 and the Dev 106, as previously described in Fig. 52, regarding other house-hold devices.

[00423] Fig. 62 illustrates a preferred activation example of embodiment 6200 of the present invention for robotic application. This exemplary embodiment presents the communication interaction between the Dev 106, and the plurality of other mobile devices in the robotic application, where a plurality of users (handsets) can program, control and monitor said Dev in fulfilling its task.

[00424] It illustrates the operation performed or carried out by the Dev 106 regarding the tasks or functions 6208 through the communication link/connector 6210 connecting to its I/O interface 438 (Fig. 4). The Dev 106 performs the task 6208 using its I/O control 401 (Fig. 4), such as: Lighting Control 410 on behalf of the handset 102 (user) for brightness, Temperature sensors 404 to check the environment reading, Audio I/O 408 for voice/sound, Video I/O 406 for seeing and General I/O 412 for performing and controlling various steps and procedures in order to complete a task. The Video screen 6206 projects images from the video I/O 406 so a third party can observe and participate in. An unregistered handset 6204 (which as mentioned earlier in Fig. 1, can be a smart phone, tablet PC, laptop PC, iPad-like device, PDA [Personal Digital Assistant] or any portable electronic device) user can be invited (registered) by the handset 102 user (through the Device Configure Process in Fig. 19/20) to actively participate in carrying out the task 6208. Connections 6214 and 6216 are preferably cellular 118 and 6212 is preferably wired/wireless LAN but they can also be any wireless network. Task 6208 can be a robotic device on medical surgery, robotic moving, flying and steering devices on rescue operation inside a collapsed building, houses on fire or a rescue operation where human cannot have access to.

[00425] While this invention has been described in terms of several embodiments, there are alterations, modifications, permutations, and substitute equivalents, which fall within the scope of this invention. It should also be noted that there are many alternative ways of implementing the methods and systems of the present invention. It is therefore intended that the following appended claims be interpreted as including all such alterations, modifications, permutations, and substitute equivalents as fall within the true spirit and scope of the present invention.

# CLAIMS

What is claimed is:

1. A computerized method for identifying and registering a new appliance, useful in association with a mobile device associated with an owner, the method comprising:

receiving a one-time and time-limited activation code and data at a new appliance from a mobile device associated with an owner, the one-time and time-limited activation code and data provided to the mobile device by a cellular service provider;

transmitting by the new appliance via a cellular network the one-time and time-limited activation code and ~~a~~ unique appliance identifier to the cellular service provider; and

receiving at the new appliance via the cellular network an assigned phone number and activation acknowledgement from the cellular service provider.

2. The method of claim 1 wherein the activation code is received via at least one of a short range wired communications channel, a short range wireless communications channel and a portable memory module medium.

3. The method of claim 1 wherein the new appliance associates the mobile device previously received the one-time and time-limited the activation code from the cellular service provider which will associate its appliance data parameters with the new appliance and with the mobile device owner.

4. The method of claim 1 wherein the one time and time limited activation code is based on at least one of:

personal information associated with the owner;

a mode of financial payment associated with the owner;

activation data and key assigned by the cellular service provider;

an activation type;

an activation methodology; and

an encryption key.

5. The method of claim 1 wherein the unique appliance identifier includes at least one of an IMSI (International Mobile Subscriber Identity), an ESN (Electronic Serial Number), a MEID (Mobile Equipment Identifier), an IMEI (International Mobile Subscriber Identifier), a SN (Serial Number), a model number and a manufacturer name.

6. The method of claim 1 further comprising receiving and registering a unique identifier associated with the mobile device and thereby limiting communications to the identified mobile device.

7. The method of claim 6 further comprising registering a second mobile device by:

receiving from the registered mobile device the identifier of the second mobile device;

transmitting a registration acknowledgement to the registered mobile device; and

transmitting registration instructional information to the second mobile device.

8. The method of claim 7 further comprising deregistering the second mobile device by:

receiving from the registered mobile device the identifier of the second registered mobile device to be deregistered;

transmitting the deregistration acknowledgement to the registered mobile device;

transmitting deregistration command to the registered second mobile device; and

ceasing communication with deregistered mobile device.

9. The method of claim 6 further comprising registering a second mobile device by:

receiving from the registered mobile device the identifier of the second mobile device;

transmitting a registration acknowledgement to the registered mobile device;

transmitting registration instruction information to the second mobile device; and

restricting the functionality of second mobile device to the entry and exit of the house.

10. The method of claim 6 further comprising registering a second mobile device by:

receiving from the registered mobile device the identifier of the second mobile device;

transmitting a registration acknowledgement to the registered mobile device;

transmitting registration instruction information to the second mobile device;

restricting the functionality of the second mobile device by not allowing it to register a mobile device; and

ceasing communication of the second mobile device on a programmed time and date.

11. The method of claim 1 further comprising receiving from the registered mobile device a unique identifier associated with a second mobile device and providing a download link of an appliance communication application to the second mobile device.

12. The method of claim 1 further comprising soliciting a second mobile device to register with the appliance to enable future communications between the second mobile device and the appliance.

13. The method of claim 12 further comprising deregistering the second mobile device to disable communications between the second mobile device and the appliance.

14. The method of claim 12 further comprising receiving at least one of a user security password and an email address from the second mobile device, thereby enabling the second mobile device to add a user security password and an email address to the appliance associated with the second mobile device.

15. The method of claim 7 further comprising receiving a disable command and a unique identifier associated with the second registered mobile device from the registered mobile device, thereby disabling communications between the appliance and the second registered mobile device.

16. A computerized method for identifying and registering an appliance to a second cellular service provider, useful in association with a mobile device associated with a user, the method comprising:

receiving via a first cellular network, currently used by the appliance, a one-time and time-limited activation code and data at an appliance from the registered mobile device, the one-time and time-limited activation code and data provided to said mobile device by a second cellular service provider;

transmitting by the appliance via the second cellular network the one-time activation code and a unique appliance identifier to the second cellular service provider, thereby initiating an activation of the appliance with the second cellular network provider; and

receiving at the appliance via the second cellular network an activation acknowledgement from the second cellular service provider, thereby confirming the activation of the appliance with the second cellular network provider.

17. The method of claim 16 further comprising transmitting a new appliance identifier to at least one of a plurality of registered mobile devices, thereby informing the at least one of a plurality of registered mobile devices of a new account associated with the new appliance identifier associated with the second cellular service provider.

18. The method of claim 1 further comprising:

receiving a registration soliciting from an unregistered third party mobile device;

sending at least one alert message to at least one registered mobile device;

receiving an positive/negative confirmation from one of the at least registered mobile device;

matching the password from the registered mobile device with one of the at least one authorized password; and

registering/not registering the unregistered third party mobile device.

19. The method of claim 1 further comprising:

receiving a registration soliciting from an unregistered third party mobile device;

sending at least one alert message to at least one registered mobile device;

receiving a matched password from the unregistered third party mobile device; and

registering the unregistered third party mobile device.

20. The method of claim 1 further comprising:

detecting the presence of a SIM module.

21. The method of claim 1 further comprising:

receiving a GPS location request from the registered mobile device; and

sending a current GPS location to registered the mobile device.

22. The method of claim 1 further comprising:

receiving a missing mobile device location request from the registered mobile device; and

sending a current GPS location of the missing mobile device to the registered mobile device.

23. The method of claim 1 further comprising completing a toll payment by using an account associated with a company payment receivable account of the toll taking device set up by the registered mobile device:

receiving a toll-payment demand associated with stored paying account information from the toll taking device;

completing a toll-payment including transmitting the stored toll paying account information associated with the company which owns the toll-taking device **to** a said toll-taking device; and

storing the payment information record in the appliance memory.

24. The method of claim 23 further comprising transmitting a record of the completed toll payment to the registered mobile device.

25. The method of Claim 1 further comprising completing a toll-payment by using an on-demand account associated with the owner of the registered mobile device set up by said mobile device:

receiving toll-payment demand from the toll taking device; and

completing a toll-payment including transmitting the toll paying account information associated with the owner of the mobile device to a toll-taking device.

26. The method of claim 1 further comprising:

receiving an alert from at least one sensor associated with the appliance; and

transmitting the alert to the registered mobile device.

27. The method of claim 26 wherein the at least one sensor includes at least one of a motion detection sensor, an audio sensor, a video sensor, and a thermal sensor.

28. The method of claim 26 further comprising:

detecting when a vehicle associated with the appliance is in stationary position for a duration of time and detecting closed windows and doors;

detecting at least one of moving object and a heat source inside the vehicle; and

transmits a warning message to the registered mobile device

29. The method of claim 28 further comprising receiving a command from the registered mobile device, wherein the command comprising at least one of:

unlocking a door;

rolling down a window;

sounding a horn;

triggering an alarm;

turning on a heater;

turning on an air-conditioner;

flashing a light; and

dial emergency center and enabling the vehicle hands-free micro and speaker.

30. The method of claim 29 further comprising transmitting at least one of a video image and an audio file to the registered mobile device.

31. The method of claim 1 wherein the appliance is associated with a vehicle and the method further comprises receiving at least one GPS location with a programmed speed from the registered mobile device.

32. The method of claim 31 further comprising detecting and storing when the speed of the vehicle exceeds the programmed speed while the vehicle is proximate to the at least one GPS location.

33. The method of claim 32 further comprising transmitting a corresponding alert to the registered mobile device.

34. The method of claim 1 wherein the appliance is associated with a vehicle and the method further comprises receiving at least one GPS location with a programmed timer in minute resolution value from the registered mobile device.

35. The method of claim 34 further comprising recording the route tracking data every time when the timer reaches its programmed value; the route tracking data comprises:

the speed of the vehicle;

the GPS location;

the time;

the date; and

the vehicle's identification.

36. The method of claim 6 further comprising receiving an input status query from the registered mobile device.

37. The method of claim 36 further comprising transmitting the corresponding input status to the registered mobile device.

38. The method of claim 6 further comprising:

receiving a proximity query from the registered mobile device, wherein the proximity query is relative to a physical location;

receiving a connection request and appliance application code from the registered mobile device; and

transmitting the appliance application code or download link to the registered mobile device thereby enabling the registered mobile device to operate the household appliance or house related equipment.

39. The method of claim 38 further comprising receiving a command from the registered mobile device, wherein the command is associated with an entertainment system.

40. The method of claim 6 further comprising receiving a command from the registered mobile device, wherein the command is associated with a vehicle.

41. The method of claim 40 wherein the command is at least one of a door lock or unlock command, a window open or close command, and an air conditioner on or off command.

42. The method of claim 1 further comprising forwarding a command from the registered mobile device to another device, wherein the command is at least one of a security system command, a system, a vehicular command, a surveillance system command.

43. The method of claim 1 further comprising forwarding a command from the registered mobile device to another device, wherein the command is at least one of a home entryway command, an irrigation system command, a HAV (Heating Air-conditioning & Ventilation) system command, an appliance command, an entertainment system command, a power generator command, a solar power system command, a fitness system command, a communication system command, a personal computer command, a home illumination includes lighting system command, a swimming pool or spa command heating command.

44. The method of claim 42 further comprising transmitting a corresponding alert to the registered mobile device.

45. The method of claim 1 further comprising forwarding a command from the registered mobile device to another device associated with the utility service provider, wherein the command is a utility service account payment setup associated with at least one of a electric service, a water service, a gas service, a waste disposal service and a recycling service.

46. The method of claim 1 further comprising forwarding the monthly service bill associated with at least one of an electric service, a water service, a gas service, a waste disposal service and a recycling service to the correspondent associated utility service provider.

47. The method of claim 1 further comprising transmitting a message to the registered mobile device with input event associated with a doorbell and an intercom, and thereby enabling two way communications between the registered mobile device and the doorbell and the intercom.

48. The method of claim 1 further comprising transmitting an email address and a command to an email server for the purpose of emailing a recovered password of the owner of said email address.

49. The method of claim 1 further comprising transmitting an alert message of the location and the nature of the appliance to registered mobile device and to the emergency station when a certain event happens.

50. The method of claim 49 further indicating certain event as being:
an air bag being inflated; or
an impact to the vehicle body.

51. The method of claim 1 further comprising receiving a panic input from the mobile device, the method comprising:
turning on the emergency lights;
transmitting an alert message and the location to the emergency station;
transmitting an alert message and the location to the registered handset; and
providing a two way communications on the vehicle hands-free micro and speaker.

52. The method of claim 1 further comprising:
receiving from mobile device programming a command comprising:
programming recording time;
starting recording video input;
opening pet utility door;
playing audio recorder;
running the RTC for a programmed period of time;
closing pet utility door;
stop recording; and
transmitting message to the mobile device.

53. The method of claim 1 further comprising:
receiving from mobile device programming command comprising:
programming recording time;
starting recording video input;
opening pet utility door;
playing audio recorder;
running the RTC for a programmed period of time;

closing pet utility door;

stop recording;

transmitting message to the mobile device; and

playing back recording.

54. The method of claim 1 further comprising:

receiving from mobile device programming a command comprising:

programming a feeding time;

opening the feeder door;

running the RTC for a programmed period of time; and

closing the feeder door.

55. The method of claim 6 further comprising receiving a command from the one registered mobile device and further receiving a second command from a second registered mobile device wherein the commands are associated with a robotic control device.

56. A computerized appliance useful in association with a mobile device of a user, the appliance configured to:

receive a one-time and time-limited activation code and data from a mobile device associated with an owner, the one-time and time-limited activation code and data provided to the mobile device by a cellular service provider;

transmit via a cellular network the one-time and time-limited activation code and unique appliance identifier to the cellular service provider; and

receive via the cellular network an assigned phone number and activation acknowledgement from the cellular service provider.

57. A computerized method for identifying and registering a new appliance, useful in associated with a mobile device associated with an owner, the method comprising:

transmitting by a mobile device via a cellular network an activation request and associated user ID and password to a cellular service provider;

receiving at the mobile device via the cellular network an activation in process confirmation from the cellular service provider;

receiving at the mobile device via the cellular network the personal and financial payment information associated with the owner from the cellular service provider;

receiving at the mobile device via the cellular network the one-time and time-limited activation code and data from the cellular service provider;

transmitting by the mobile device the one-time and time-limited activation code and data to a new appliance; and

receiving at the mobile device via the cellular network an activation completion notice from the new appliance upon a successful activation of the new appliance.

58. The method of claim 57 wherein the registered mobile device receiving from the appliance messages associated with door bell and intercom informing its owner of a visitor visiting and thus enabling communications between the owner and said visitor.

59. The method of claim 57 wherein the registered mobile device receiving messages soliciting from the appliance so the registered mobile device can receive software application to communicate with the appliance in order to control, program and monitor house hold appliance accessories.

60. The method of claim 57 wherein the registered mobile device receiving messages soliciting from the appliance so the registered mobile device can delete the software application to no longer communicate with the appliance in order to control, program and monitor the household appliance accessories.

61. The method of claim 57 wherein the registered mobile device communicating within the appliance in the short communication medium when the mobile device is within short distance range of said appliance. Furthermore the registered mobile device communicating directly with said household appliance accessories in the short communication medium.

62. The method of claim 57 wherein the mobile device communicating with the appliance in the short range communication medium when the mobile device is within short distance range of said appliance in association with the vehicle control accessories.

63. The method of claim 57 further comprising:

transmitting a proximity query to the appliance;

transmitting the connection request to the appliance; and

receiving the appliance application code or download link from the appliance thereby enable the registered mobile device to operate the household appliance or house related equipment.

64. The method of claim 63 wherein the household appliance or house related equipment associated with a door bell and intercom communicating with the appliance in the short range communication medium comprising:

receiving push button input from a visitor;

sending a command to the appliance;

receive acknowledge from the appliance; and

establishing the two-way communication between the appliance and the visitor.

65. The method of claim 63 wherein the household appliance or house related equipment associated with an integrated smart pet door communicating with the appliance in the short range communication medium comprising:

receiving from the appliance a command comprising at least one the of followings:

recording video input;

opening pet utility door;

playing audio recorder;

closing pet utility door; or

stopping audio recorder.

66. The method of claim 63 wherein the household appliance or house related equipment associated with a smart pet feeder communicating with the appliance in the short range communication medium comprising:

receiving from the appliance a command comprising at least one the of followings:

opening the feeder door; or

closing the feeder door.

67. The method of claim 66 further comprising:

transmitting a feeder refill command to the appliance.


Provision Computer/Server
120
112
Cellular Service Provider
(CSP)
or "Service Provider"
114
116
Email Server
110
Base Transceiver Station
(BTS) or The Tower
118
Wireless Network
108
Dev Application Storage
Server
or "App Server"
102
104
106
PC/Tablet/Smart
Phone
/Handset
or "Handset"
BT/Wireless
USB/NFC/
infrared/wireless
LAN - SRC
(Short Range
Communication)
Program Control &
Monitor Device
(PCMD)
or "Dev"
124
Robotic
Device
100
120
122

FIG. 1

FIG. 2


200
201
202 Activate Button
202a Heating /A C
203 Emergency Lights
204 Dial & Talk Button
205 Engine Conditions
206 Horn
208 GPS
210 Entry Lock/Unlock
212 Entry Detectors
214 Motion Detectors
216 Video inputs
218 Audio I/Os
220 Alarm speaker
222 General I/Os
224 Speedometer
226 Air Bags
228 Brakes
229 Temperature Det.
229a Emergency Button
106
234
230
Antenna 1
232
RF Amp
HF Speaker, microphone & voice activated Circuitry
I/O Interface
240
238
Clock system
236
RTC
Antenna 2
244
242
RF Transceiver
Cellular Controller & Circuitry
248
Power/ Battery backup & Reset Circuitry
249
Analog Front-End
246
CPU
I/Q Transceiver
LAN Controller & Circuitry
ModSIM Storage
SIM Storage
266
250
252
254
256
266A
258
260
262
264
268
NFC
Bluetooth
USB
Memory/ Storage
NAM Storage
SIM Card
270
104
102A
102B
118
Wireless Network

FIG. 3


300
301
202
Activate Button
302
Silent Alarm
303
Panic Button
304
Smoke Detectors
306
Entry Lock/Unlock
308
Entry detections
310
Motion detectors
312
Video inputs
314
Audio I/Os
316
Alarm speakers
318
General I/Os
320
Lighting Control
106
234
236
338
I/O Interface
Antenna 1
232
RF Amp
Clock system
Antenna 2
240
RTC
242
244
RF Transceiver
Cellular Controller & Circuitry
248
250
Power/ Battery backup & Reset Circuitry
Analog Front-End
246
CPU
249
266
252
I/Q Transceiver
LAN Controller & Circuitry
ModSIM Storage
SIM Storage
NAM Storage
254
256
266A
268
258
260
262
264
NFC
Bluetooth
USB
Memory/ Storage
SIM Card
270
104
102A
102B
118
Wireless Network

FIG. 4


400
401
106
Antenna 1
232
Antenna 2
242
Antenna 3
432
234
RF Amp 1
244
RF (1) Transceiver
252
Analog Front-End
254
I/Q Transceiver
434
RF Amp 2
436
RF (2) Transceiver
439
246
Cellular Controller & Circuitry 1
256
LAN Controller & Circuitry
Cellular Controller & Circuitry 2
236
Clock system
438
I/O Interface
Activate Button
202
Temperature Sensors
404
Video I/Os
406
Audio I/Os
408
Lighting Control
410
General I/Os
412
245
ModSIM 1 & 2
248
CPU
249
250
Power/ Battery backup & Reset Circuitry
RTC
240
NAM / SIM Storage 2
442
NAM / SIM Storage 1
440
SIM Card
270
Memory/ Storage
258
NFC
260
Bluetooth
262
USB
264


500
Dev App
Dev Base
Core OS
Dev ID Parameters
Download layer
Cellular & Wireless LAN layer
NAM Parameters
SIM Parameters
Op App
Account Payment setup layer
Hand-Free Audio I/O & voice activated layer
Handset Locating layer
I/O Manage-ment layer
Program & Control layer
Auto App Download
Auto Alarm Application
Engine Status
Handset Information
Car Dev Info
Handset Registration layer
Dev Configure
Add & Remove
Command Communication layer
Status & Monitor layer
Event layer
Dev Activate /De-activate layer
Handset App Update layer
502
504
506
508
510
512
514
516
518
520
522
524
526
528
530
532
534
540
542
544
546
548
550
552
560
562
564
566

FIG. 5


600
602
Command Communication layer
604
Status & Monitor layer
606
Event layer
608
Dev Activate /De-activate layer
610
Handset App Update layer
612
Dev Configure
614
Add & Remove
616
Dev App
618
Program & Control layer
620
Handset Registration layer
622
Home Dev Info
624
Op App
626
I/O Management layer
628
Household Appliances layer
630
Handset Locating layer
632
Home Alarm Application
634
Home App Download
635
DA
HA
AA
CA
GA
SA
EA
BA
PA
FA
HH App
637
Handset Information
560
Core OS
540
Dev ID Parameters
642
Download layer
544
Cellular & Wireless LAN layer
546
NAM Parameters
648
SIM Parameters
650
Dev Base
652
662
664

FIG. 6




FIG. 7A

700A

FIG. 7B

700B




Dev
106
Handset
102
App Server
108
802
804
820
Handset Display
806
808
822
Handset Display
810
812
824
Handset Display
814
816
104
SRC Media
118
Cellular/Wireless
Telecommunication
Medium
800

FIG. 8


902
904
906
908
910
912
914
820
Inbox
Notice - Your Handset has no Associate Software to run this device.
Please Visit – www.xxxdownloadalarmsys.com/veh/ To download the application software.
XXX Control & Alarm System
Manufacture: XXX Alarm Co.
Type/Model:
Car Application System - XXXSV-3
S/N: NV12345
Activation Software V/N v3.4
Application Software V/N v3.7
824
940
942
944
946
948
950
Car Application System XXXSV-3
Application downloading. Please wait.
Download done.
Check your Tools Box !
Please wait.
Updating Dev software.
Waiting for completion
Device App up to date.
960
962
Tools
Calendar
Task
Auto Application
xxx
xxx
980
982
984
Auto App
Car Application v3.7
822
920
922
924
926
928
Application Downloading Menu
Welcome to App Download System !
Vehicle Control & Alarm Application Systems:
Android
iOS
Windows
Others
Your handset is Android based.
Will download App in 10 seconds!
930
932
934
900

FIG. 9


1000
820
822
824
1002
1004
1006
1008
1010
1012
1014
Inbox
Notice - Your Handset has no Associate Software to run this device.
Please Visit – www.xxxdownloadalarmsys.com/hom/ To download the application software.
XXX Control & Alarm System
Manufacture: XXX Alarm Co.
Type/Model:
Home Application System - XXXSH-4
S/N: NH23456
Activation Software v4.5
Application Software v4.8
1020
1022
1024
1026
1028
1030
1032
1034
Application Downloading Menu
Welcome to App Download System !
Home Control & Alarm Application Systems:
Android
iOS
Windows
Others
Your handset is Android based.
Will download App in 10 seconds!
1040
1042
1044
1046
1048
1050
Home Application System XXXSH-4
Application downloading. Please wait.
Download done.
Check your Tools Box !
Please wait.
Updating Dev software.
Waiting for completion
Device App up to date.
1060
1064
Tools
Calendar
Task
Auto Application
Home Application
xxx
1080
1082
1084
Home App
Home Application v4.8

FIG. 10


Auto App
Car Application v3.7
1102
1104
1120
1122
Auto App Menu
Auto Dev Facilities
Control & Monitor
Engine Status
Toll Fee Pay Acc.
Panic
Lock/ Unlock
1124
1126
1128
1132
1134
1136
1100
1150
Auto Dev Facility Menu
1152
Activate
Deactivate
1154
1162
Dev Configure
Handset&Dev App Update
1156
1164
Handset Register
Dev Info
1158
1166
Add Handset
Handset Locator
1172
1170
Remove Handset
Handset Sign In
1176
1174
1180
ATT Wireless
Verizon Wireless
Sprint
T-Mobile
US Cellular
Metro PCS
Virgin Mobile
Boost Mobile

FIG. 11


Vehicle Activation Menu
Dev is being activated !
Activation req. to Server.
Activation password is ok.
Account number: XXX0933
Subscriber: Sol M. Li
Receiving UTAID from service provider.
. . .
Ok
Cancel
Save
1236
1238
1240
1242
1244
1246
Inbox
Previous
Peter
You feed Buster for me
Michelle
I will be home late
John
The lunch still on
1292
Auto device Activation completed.
Open on Icon to initialize the Dev.
1280
1282
1284
1286
1288
1290
Vehicle Activation Menu
Enter Server web address:
www.ABC_act.com/veh/
Enter Activation User ID:
Xxxxx
Enter Activation password:
Xxxxx
Enter Your handset number:
916-987-6543
916-987-6543 (again)
Ok
Cancel
Save
1220
1222
1224
1226
1228
1229
1230
1232
1234
1235
1200
Vehicle Activation Menu
Device is being activated !
Activation is complete.
Activation is DONE.
Check Success icon if you have any messages from the device in your inbox. Please wait for 20 minutes or longer to see if you inbox receives any messages; verify your handset phone number entry if it is correct; otherwise contact your provider customer service & check fail box.
Success
Fail
1270
1272
1274
1276
1278
Vehicle Activation Menu
Device is being activated !
Connecting to the Dev.
Acknowledge from Dev.
Transmitting handset number.
Transmitting Acc. Information.
Transmitting UTAID.
Activating Dev.
Waiting for Dev activation completion.
Device received confirmation from network.
Dev phone: 916-122-9876
Activation completed successfully.
Check your inbox.
1250
1252
1254
1256
1258
1260
1262
1264
1266
1268
1269
Vehicle Activation Menu
Enter Server web address:
Enter Activation User ID:
Enter Activation password:
Enter Your handset number:
Ok
Cancel
1202
1204
1206
1208
1210
1212
1214

FIG. 12


Home
Home Application v4.8
1304
1302
1320
1322
Home App Menu
Home Dev Facilities
Control & Monitor
1324
1326
Door Lock
Alarm On
1332
1336
Door Unlock
Alarm Off
1334
1338
List Handset In &Out Activity
Garage Opener
1342
1340
Household Appliances
1344
1300

FIG. 13


1380
1350
Home Dev Facility Menu
1352
Activate
Deactivate
1362
1354
Dev Configure
Handset&Dev App Update
1364
1356
Handset Register
Dev Info
1366
1358
Add Handset
Handset Locator
1370
1372
Remove Handset
Handset Sign In
1374
1376
ATT Wireless
Verizon Wireless
Sprint
T-Mobile
US Cellular
Metro PCS
Virgin Mobile
Boost Mobile


Home Activation Menu
Device is being activated !
Activation req. to Server.
Activation password is ok.
Account number: XXXX0934
Subscriber: Sol M. Li
Receiving UTAID from service provider.
. . .
Ok
Cancel
Save
1436
1438
1440
1442
1444
1446
Inbox
Bryan
Get me some vitamin at Costco
Vicky
No school for me today
Sam
What's up Doc
1492
Home device Activation completed.
Open on Icon to initialize the Dev.
Previous
1480
1482
1484
1486
1488
1490
Home Activation Menu
Enter Server web address:
www.ABC_act.com/hom/
Enter Activation User ID:
xxxxx
Enter Activation password:
Xxxxx
Enter Your handset number:
916-987-6543
916-987-6543 (again)
Ok
Cancel
Save
1420
1422
1424
1426
1428
1429
1430
1432
1434
1435
Home Activation Menu
Activation is complete.
Activation is DONE.
Check Success icon if you have any messages from the device in your inbox. Please wait for 20 minutes or longer to see if you inbox receives any messages; verify your handset phone number entry if it is correct; otherwise contact your provider customer service & check fail box.
Success
Fail
1470
1472
1474
1476
1478
1400
Home Activation Menu
Enter Server web address:
Enter Activation User ID:
Enter Activation password:
Enter Your handset number:
Ok
Cancel
1402
1404
1406
1408
1410
1412
1414
Home Activation Menu
Device is being activated !
Connecting to the Dev.
Acknowledge from Dev.
Transmitting handset number.
Transmitting Acc. Information.
Transmitting UTAID.
Activating Dev.
Waiting for Dev activation completion.
Device received confirmation from network.
Dev phone: 916-230-1234
Activation completed successfully.
Check your inbox.
1450
1452
1454
1456
1458
1460
1462
1464
1466
1468
1469

FIG. 14


Handset
102
Dev
106
Provision Server
114
User enters Provision Server's activation web page address, User activation ID & Activation Password
1502A
Activation request, User activation ID & Activation Password
1504A
UTAID and User's account information
1506A
Handset's phone number, User's account information and UTAID
1508A
Activation key & ESN/MEID/IMEI
1510A
1512A
Verify activation key, process activation request, & ESN/MEID/IMEI
1511A
1514A
Assigned phone number, SID, Ki, Other NAM parameters & generate Activation Acknowledge
1516A
Store its phone number, SID, Ki & all Parameters into NAM memory Area.
1518A
Store Handset phone number and User's account information into Handset Information memory Area.
1519A
Recycle power & register into the service provider network
Register into the network
1520A
1522A
1520A
104
118
1500A

FIG. 15A


User:
Enter Provision Server's activation web page address, User's activation ID, Activation Password and Handset phone number.
1502B
Handset:
Send Activation Request, User's activation ID and activation password to Provision Server
1504B
Handset:
Receive UTAID (Unique Temporary Activation ID) and User's account information from Provision Server
1506B
Dev:
Receive UTAID, handset's phone number and User's account information from Handset
1508B
Dev:
Send activation key & ESN/MEID/IMEI to Provision Server
1510B
Provision Server:
Verify activation key, process the request & ESN/MEID/IMEI
1512B
1514B
Dev:
Receive assigned phone number, SID, Ki, other NAM parameters & Activation acknowledgement from Provision Server
Dev:
Store its phone number, SID, Ki & all NAM parameters to NAM memory area
1516B
Dev:
Store Handset's phone number and user's account information to Handset info. memory area
1518B
Dev:
Recycle power & register into service provider network
1519B
Dev:
Receive acknowledgement and a confirmation message from Provision Server/Service Provider
1520B
Dev:
Send its phone number & Program Success / Failure to Handset
1522B
Done
1524B
1500B

FIG. 15B


Handset
102
Dev
106
Provision Server
114
User enters Provision Server's activation web page address, User activation ID & Activation Password
1502A
Activation request, User activation ID & Activation Password
1504A
UTAID and User's account information
1506A
Handset's phone number, User's account information and UTAID
1508A
Activation key, IMEI and dummy IMSI
1610A
Verify activation key, process activation request, & all parameters
1612A
1611A
Assigned SIM parameters (MSISDN, IMSI, TMSI), Ki & generate Activation acknowledgement
1614A
Store all SIM parameters and Ki to SIM memory Area.
1616A
Store Handset phone number and User's account information into Handset Information memory Area.
1618A
Recycle power & register into the service provider network
1619A
1600A
Register into the network
1620A
1620A
1622A
104
118

FIG. 16A


User:
Enter Provision Server's activation web page address, User's activation ID, Activation Password and Handset phone number.
1602B
Handset:
Send Activation Request, User's activation ID and activation password to Provision Server
1604B
Handset:
Receive UTAID (Unique Temporary Activation ID) and User's account information from Provision Server
1606B
Dev:
Receive UTAID, handset's phone number and User's account information from Handset
1608B
Dev:
Send activation key, IMEI & dummy IMSI to Provision Server
1610B
Provision Server:
Verify activation key, process the request and all parameters
1612B
1614B
Dev:
Receive MSISDN, IMSI, TMSI, Ki & Activation acknowledgement from Provision Server
Dev:
Store MSISDN, IMSI, TMSI and Ki to SIM memory area
1616B
Dev:
Store Handset's phone number and user's account information to Handset info. memory area
1618B
Dev:
Recycle power & register into service provider network
1619B
Dev:
Receive acknowledgement and a confirmation message from Provision Server/Service Provider
1620B
Dev:
Send its phone number & Program Success / Failure to Handset
1622B
Done
1624B
1600B

FIG. 16B


Handset
102
Dev
106
Provision Server
114
User enters Provision Server's activation web page address, User activation ID & Activation Password
1502A
Activation request, User activation ID & Activation Password
1504A
UTAID and User's account information
1506A
Handset's phone number, User's account information and UTAID
1508A
Activation key and Dev's IDs parameters (S/N, Part Number & Manufacturer's name)
1710
1711
1712
Verify activation key, process activation request, & Dev's ID parameters
1714
Assign Dev's phone number, TMSI, Ki & generate Activation acknowledgement
1716
Store its phone number, TMSI and Ki to ModSIM memory Area.
1718
Store Handset phone number and User's account information into Handset Information memory Area.
1719
Recycle power & register into the service provider network
Register into the network
1720
1722
1720
104
118
1700

FIG. 17


User:
Enter Provision Server's activation web page address, User's activation ID, Activation Password and Handset phone number.
1802
Handset:
Send Activation Request, User's activation ID and activation password to Provision Server
1804
Handset:
Receive UTAID (Unique Temporary Activation ID) and User's account information from Provision Server
1806
Dev:
Receive UTAID, handset's phone number and User's account information from Handset
1808
Dev:
Send activation key, Dev's ID parameters (S/N, Part Number & Manufacturer's name) to Provision Server
1810
Provision Server:
Verify activation key, process the request and Dev's ID parameters
1812
1814
Dev:
Receive its assigned phone number, TMSI, Ki & Activation acknowledgement from Provision Server
Dev:
Store its assigned phone number, TMSI and Ki to ModSIM memory area
1816
Dev:
Store Handset's phone number and user's account information to Handset info. memory area
1818
Dev:
Recycle power & register into service provider network
1819
Dev:
Receive acknowledgement and a confirmation message from Provision Server/Service Provider
1820
Dev:
Send its phone number & Program Success / Failure to Handset
1822
Done
1824
1800

FIG. 18


1970
Dev
106
Handset
102
1976
Security Passwords and chosen Handset Passwords
1978
1982
Enter & Edit Remaining Auto Dev info.
1980
1984
Store Dev's phone number
1986
1992
Auto Dev Initialization Information.
1990
1988
Save Auto Dev Init. Info.
1900
Auto Device Initialization
License Plate: _x
Make: _x
Security Password:: xxxxx
Registered Phone Numbers:
916-987-6543 (password: 1234)
Acc. Name - Sol M. Li
SP_Name - Acc # 6780933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
_x
Police/Emergency _x
1928a
Save
Cancel
Exe
1902 1920
1921
1922
1923
1924
1925
1926
1927
1928
1904
1912
1906
1908
1910
1914
1916
1918
1918
Auto Device Initialization
Enter Chosen Security Password:
_xxxxx
Re-enter Security Password:
_xxxxx
Enter Chosen Handset Password:
_1234
_1234
Execute
Cancel
Auto Device Initialization
License Plate: CA-QFA955
Make: Ford 2011 White Campri
Security Password: xxxxx
Registered Phone Numbers:
916-987-6543 (pw: 1234)
Acc. Name - Sol M. Li
SP_Name - Acc # 6780933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
owner@myacc.com
Police/Emergency 911
1960a
Ok
Edit
1956a
1950a
1952a
1930a
1932a
1934a
1936a
1937a
1938a
1940a
1942a
1946a
Auto Device Initialization
License Plate: CA-QFA955
Make: Ford 2011 White Campri
Security Password: xxxxx
Registered Phone Numbers:
916-987-6543 (pw: 1234)
Acc. Name - Sol M. Li
SP_Name - Acc # 6780933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
_owner@myacc.com
Police/Emergency _911
1960
Save
Cancel
Exe
1956
1950
1952
1954
1930
1932
1934
1936
1937
1938
1940
1942
1946

FIG. 19


Dev
106
2088
Save Home Dev Init. Info.
Handset
102
2076
Security Passwords and chosen Handset Passwords
2078
2080
Enter & Edit Remaining Home Dev info.
2082
2084
Store Dev's phone number
2086
2090
Home Dev Initialization Information.
2092
2070
2000

FIG. 20


Home Device Initialization
Enter Chosen Security Password:
_xxxxxx
Re-enter Security Password:
_xxxxxx
Enter Chosen Handset Password:
_1234
_1234
Execute
Cancel
2002
2004
2006
2008
2010
2012
2014
2016
2018
Home Device Initialization
Home Address:
_x
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6543 (password: 1234)
Acc. Name – Sol M. Li
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
_x
Police/Emergency _x
Save
Cancel
Exe
2020
2021
2022
2023
2024
2025
2026
2027
2028
2028a
2056a
2060a
2030a
2032a
2034a
2036a
2037a
2038a
2040a
2042a
2046a
2050a
2052a
Home Device Initialization
Home Address:
12833 Lantana Av.
Sara, CA. 95070
Security Password: _xxxxxx
Registered Phone Numbers:
916-987-6543 (pw: 1234)
Acc Name - Sol M. Li
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
_owner@myacc.com
Police/Emergency _911
Save
Cancel
Exe
2060
2050
2052
2054
2056
2030
2032
2034
2036
2037
2038
2040
2042
2046


Auto Device Information
License Plate: CA-QFA955
Make: Ford 2011 White Camari
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6543 (password: 1234)
916-987-6500 (password: 3456)
SP_Name - Acc # 8756933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
_owner@myacc.com
Police/Emergency 911
Done
2148A
Home Device Information
Home Address:
12833 Lantana Av.
Sara, CA 95070
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6543 (password: 1234)
916-987-6500 (password: 5678)
SP_Name - Acc # 8756944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
owner@myacc.com
Police/Emergency 911
Done
2198A
2140A
2142A
2144A
2146A
2190A
2192A
2194A
2196A
Adding New Handset - Auto
Notice
New Handset has been added to work with the smart vehicle device:
Vehicle License Plate: CA-QFA955
Make: Ford 2011 White Camari
Please verify the following information, make changes if necessary and confirm:
New Handset phone number:
916-987-6500 (password: 3456)
Cancel
Confirm
2120A
2122A
2124A
2126A
2128A
2130A
2132A
2134A
2136A
Adding New Handset - Home
Notice:
New Handset has been added to work with the smart home device:
Home Address:
12933 Lantana Av.
Sara, CA 95070
Please verify the following information, make changes if necessary and confirm:
New Handset phone number:
916-987-6500 (password: 5678)
Cancel
Confirm
2170A
2172A
2174A
2176A
2178A
2180A
2182A
2184A
2186A
Adding New Handset - Auto
Enter Security Password:
xxxxxx
License Plate: _CA-QFA955
Make: Ford 2011 White Camari
Enter chosen password for new handset:
_3456
_3456
Enter Handset phone number:
916-987-6500
916-987-6500 (second time)
Ok
Cancel
2102A
2104A
2106A
2108A
2110A
2112A
2113A
2114A
2116A
2118A
2119A
Adding New Handset - Home
Enter Security Password:
xxxxxx
Home Address:
12933 Lantana Av.
Sara, CA 95070
Enter chosen password for new handset:
_5678
_5678
Enter the new handset phone number of:
Family member: _916-987-6500
_916-987-6500 (2nd time)
Household help: _x
(newly cited model)
Friend (Temp): _x
Ok
Cancel
2152A
2154A
2156A
2158A
2160A
2162A
2163A
2164A
2165A
2167A
2166A
2168A
2169A
2100A

FIG. 21A


Home Device Information
Home Address:
12833 Lantana Av.
Sara, CA. 95070
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6543 (pw: 1234)
916-987-6500 (pw: 5678)
916-333-4444 (pw: 2233 - restricted mode)
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
owner@myacc.com
2148B
Police/Emergency 911
Done
2140B
2142B
2144B
2146B
2120B
2122B
2124B
2126B
2128B
2130B
2136B
Adding New Handset – Home (restricted mode)
Notice:
New Handset has been added to work with the smart home device:
Home Address:
12933 Lantana Av.
Sara, CA. 95070
Please verify the following information, make changes if necessary and confirm:
New Handset phone number:
916-333-4444 (pw: 2233 - restricted mode)
Cancel
Confirm
2132B
2134B
FIG. 21B
2100B
Home Device Information
Home Address:
12833 Lantana Av.
Sara, CA. 95070
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6543 (pw: 1234)
916-987-6500 (pw: 5678)
916-333-4444 (pw: 2233 – restricted mode)
408-555-2222 (pw: 7799 – temp mode)
Start date: 8/12/14
End date: 8/15/14
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
owner@myacc.com
2198B
Police/Emergency 911
Done
2190B
2192B
2194B
2196B
2170B
2172B
2174B
2176B
2178B
2180B
2181B
2186B
Adding New Handset – Home (temp mode)
Notice:
New Handset has been added to work with the smart home device:
Home Address:
12933 Lantana Av.
Sara, CA. 95070
Please verify the following information, make changes if necessary and confirm:
New Handset phone number:
408-555-2222 (pw: 7799 – temp mode)
Start date: 8/12/14
End date: 8/15/14
Cancel
Confirm
2182B
2184B
2102B
2104B
2106B
2112B
2113B
2114B
2115B
2117B
2119B
Adding New Handset - Home
Enter Security Password:
xxxxxx
Home Address:
12933 Lantana Av.
Sara, CA. 95070
2108B
2110B
Enter chosen password for new handset:
_2233
_2233
Enter the new handset phone number of:
Family member: _
Household help (restricted mode):
_916-333-4444:
_916-333-4444 (2nd time)
Friend (Temp): _x
Cancel
Ok
2116B
2118B
2152B
2154B
2156B
2162B
2163B
2164B
2165B
2167B
2167B1
2167B2
2169B
Adding New Handset - Home
Enter Security Password:
xxxxxx
Home Address:
12933 Lantana Av.
Sara, CA. 95070
Enter chosen password for new handset:
_7799
_7799
2158B
2160B
Enter the new handset phone number of:
Family member: _x
Household help (restricted mode):
_x
Friend (Temp): _408-555-2222
_408-555-2222 (2nd time)
Start Date: (mm/dd/yy) _ 8/12/14
End Date: (mm/dd/yy) _ 8/15/14
Cancel
Ok
2166B
2168B


Inbox
Notice:
Your Handset has been registered to work with the smart device made by:
XXX Control & Alarm System
Manufacture: XXX Alarm Co.
Type/Model:
Car/Home Application System - XXXSV-3
Please do the following two steps:
Step 1 – Visit:
http://ww.xxxalarmsys.com/download/xxx/
To download the application software.
Step 2 – Execute:
Sign In
2202
2204
2206
2208
2210
2212
2214
Handset Sign In
Enter your Handset Password:
_ xxxx
Execute
Cancel
2220
2222
2224
2226
2228
2230
2232
2200

FIG. 22


2240
102r
106
102
108
Handset (adding)
Dev
Handset (signed in)
App Server
2242
2244
2246
2252
Sign in with PW
2248
2254
Store Dc's phone number
2250
2256


2260
2262
Notice:
Handset phone number:
916-123-4567
just signed in !


Auto Device Information
License Plate: CA-QFA955
Make: Ford 2011 White Campri
Security Password: xxxxxx
Registered Phone Numbers:
x
916-987-6500 (password: 3456)
SP_Name - Acc # 6780933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
_owner@myacc.com
Police/Emergency 911
Done
2348
2340
2342
2344
2346
Home Device Information
Home Address:
12833 Lantana Av.
Sara, CA. 95070
Security Password: xxxxxx
Registered Phone Numbers:
x
916-987-6500 (pw: 5678)
916-333-4444 (pw: 2233 – restricted mode)
408-555-2222 (pw: 7799 – temp mode)
Start date: 8/12/14
End date: 8/15/14
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
owner@myacc.com
Police/Emergency 911
Done
2398
2390
2392
2394
2396
2300
Removing Handset - Auto
Notice:
Registered Handset is being removed from the smart vehicle device:
Vehicle License Plate: CA-QFA955
Make: Ford 2011 White Campri
Please verify the following information, make changes if necessary and confirm:
Removed Handset phone number:
916-987-6543 (password: 1234)
Cancel
Confirm
2332
2334
2320
2322
2324
2326
2328
2330
2336
Removing Handset - Home
Notice:
Registered Handset is being removed from the smart home device:
Home Address:
12933 Lantana Av.
Sara, CA. 95070
Please verify the following information, make changes if necessary and confirm:
Removed Handset phone number:
916-987-6543 (password: 1234)
Cancel
Confirm
2382
2384
2370
2372
2374
2376
2378
2380
2386
Remove Handset - Auto
Enter Security Password:
xxxxxx
License Plate: _CA-QFA955
Make: Ford 2011 White Campri
Registered Phone Numbers:
916-987-6543 (password: 1234)
916-987-6500 (password: 3456)
Enter Handset phone number:
916-987-6543
Ok
Cancel
2316
2318
2302
2304
2306
2308
2310
2312
2314
2319
Remove Handset - Home
Enter Security Password:
xxxxxx
Home Address:
12933 Lantana Av.
Sara, CA. 95070
Registered Phone Numbers:
916-987-6543 (pw: 1234)
916-987-6500 (pw: 5678)
916-333-4444 (pw: 2233 – restricted mode)
408-555-2222 (pw: 7799 – temp mode)
Start date: 8/12/14
End date: 8/15/14
Enter Handset phone number:
916-987-6543
Ok
Cancel
2366
2368
2352
2354
2356
2358
2360
2362
2364
2369

FIG. 23


Dev:
Security Password not matched 3 times from handset
2472A
2474A
Dev:
Enter Password Recovery process and send Email Address request command to handset
2476A
Handset:
Prompt user to enter the email address & transmit to Dev
2478A
Dev:
Receive the email address from the handset.
Compare the email address with the ones in its memory
2480A
Email Address matched?
No
Yes
2484A
Dev:
"Email Address does not match" to handset
2486A
Stop
Send user's security password, his/her email address and PW recovery request to Email Server which will email the password back to user
2482A
2470A
2400A
FIG. 24A
Auto Device Configure
Enter Security Password:
-xxxxyy
Wrong Password.
Entries exhausted. Enter you email address so your registered password will be mailed to you.
Email Addr: ..... _ owner@myacc.com
Exe
Cancel
2402A
2404A
2406A
2408A
2410A
2412A
2414A
2416A
2418A
Home Device Configure
Email Inbox (3)
Password recovery Xxxxx
Bank of America
Li, Sol
2450A
2452A
2454A
2456A
2422A
2424A
2426A
2428A
2430A
2432A
2434A
2436A
2438A


Dev
106
Handset
102
2460B
2464B
Device Configuration
2466B
2468B
Edit changes in the configuration
2470B
2472B
Confirmed configuration
2474B
Save device Configuration
2476B
2400B
2414B
Auto Device Configure
License Plate: CA-QFA955
Make: Ford 2011 White Campri
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6500 (pw: 3456)
SP_Name - Acc # 6780933
Auto Security Device Phone Numbers:
916-122-9876
Contact Email Address
_owner@myacc.com
_2ndowner@any.com
Police/Emergency 911
Cancel
Confirm
2412B
2416B
2418B
2402B
2404B
2410B
2408B
2434B
Home Device Configure
Home Address:
12833 Lantana Av.
Sara, CA. 95070
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6500 (5678)
916-333-4444 (pw: 2233 – restricted mode)
SP_Name - Acc # 6780944
Home Security Device Phone Numbers:
916-122-9877
Contact Email Address
owner@myacc.com
2ndowner@any.com
Police/Emergency 911
Cancel
Confirm
2432B
2436B
2438B
2422B
2424B
2430B
2428B
2406B

FIG. 24B




FIG. 24C

2400C


Dev:
Receive Handset Registration command, security password and handset's phone number from handset
2572
Prompt for PW again
2578
3rd attempt?
No
Yes
2580
"PW not matched"
2576
No
PW matched?
Yes
2574
2584
"Verify Phone Numbers or PW" message & prompt for Phone Number or PW Entries again to Handset
No
Handset Ph. Numbers and and Passwords identical?
Yes
2582
Password Recovery
2588
Dev:
Process, store handset's phone number and all information to memory
2586
Dev:
Send Dev Info. & confirmation command to handset
2590
Dev:
Send alert message to registered handsets which have numbers stored in Dev's memory
2592


2570
2530
2532
2536
Handset Registration
Handset to Dev Registration.
Communicating to Dev.
Security Password is Ok.
Handset Number Check is Ok.
Handset Chosen Password Check is Ok.
Receiving registration
Done.
2534
Back
Done
2502
2504
2506
2508
2510
2512
2514
2516
2518
2522
Handset Registration
Dev Phone Number:
916-122-987X
Security Password:
XXXXXX
Your Handset Phone Number:
916-987-0000
Re-enter Handset Phone Number again:
916-987-0000
Chosen Handset Passwords:
_4578
_4578
Cancel
Exe
2520

FIG. 25


2500
Home Dev Information
Home Address:
12833 Lantana Av.
Sara, CA. 95070
2546a
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6500 (pw: 5678)
916-987-0000 (pw: 4578)
916-333-4444 (pw: 2233 – restricted mode)
Home Security Device Phone Numbers:
916-122-9877
Acc Name: Sol M. Li
SP_Name - Acc # 6780944
Contact Email Address
owner@myacc.com
2ndowner@any.com
Police/Emergency 911
2558a
Ok
2540a
2542a
2544a
2548a
2550a
2552a
2554a
2556a


Auto Dev Information
License Plate: CA-QFA955
Make: Ford 2011 White Campri
2546
Security Password: xxxxxx
Registered Phone Numbers:
916-987-6500 (password: 3456)
916-987-0000 (password: 4578)
Auto Security Device Phone Numbers:
916-122-9876
Acc Name: Sol M. Li
SP_Name - Acc # 6780933
Contact Email Address
owner@myacc.com
2ndowner@any.com
Police/Emergency 911
2556
Ok
2558
2540
2542
2544
2548
2550
2552
2554


2602
2604
Activate Button
Account Active ?
Yes
No
2606
2608
Send Inquiry message to the Activating Handset
2610
Right Resp ?
No
Yes
2612
Start Activation
2614
Send App Downloading requirement message to the Activating Handset
2616
Message to Activating Handset: "You need right app software to run this application "
2618
User: Download the app online
2620
Handset: Run the application
Handset Phone Number exists?
No
Yes
2621
2622
Alert: Sending text and voice messages to account holder & handset(s) whose numbers stored in Dev's memory
2624
Receive Handset Register command, security password and handset phone number & handset PW from the Activating Handset
2628
Prompt for security password entry
PW ok ?
2630
Yes
No
2632
3 Times ?
No
Yes
2634
PW recovery
2636
Stop
2644
Receive "Not OK" Authorization from a Registered Handset
Prompt for:
Chosen Security PW entries.
2623
2625
Security PW Entries identical ?
No
Yes
2627
Prompt for:
Handset ph. number entries.
Chosen handset PW entries.
Receive "OK" Authorization from a Registered Handset
2626
Prompt for Ph No. & Handset PW entry verification
2638
Ph No. entries identical? Handset PW entries identical?
No
2640
Yes
2642
Start Handset Registration

FIG. 26


2600
2650
Auto/Home Handset Registration Alert
2652
Attempt by user of
Mobile device .... 915-987-1111
to register into your security device.
2654
2660
Date 04/29/13
Time 1:30 PM
2656
Enter Security Password to allow or not allow the registration:
2664
Password: _
2666
Ok
No
2658
2662


App Server
108
Dev
106
Handset
102
2760
2762
2764
Retrieve & Display HS current ver.
2768
Retrieve Dev current ver.
2770
Display Dev current ver.
2772
2772a
Display HS latest ver.
2774
2774a
Display Dev latest ver.
2776
2776a
Handset & Dev latest applications
2780
2782
2782a
Dev's latest application
2784
2784a
Update new application
2786
Update new application
2788
2790
Handset & Dev App Update
Checking Handset Update.
Handset current version
3.7
Handset latest version
3.9
Checking Device Update.
Device current version
3.5
Device latest version
3.6
Update Handset
yes
no
Update Device
yes
no
Exe
Cancel
2712
2714
2716
2718
2720
2722
2724
2726
2728
2730
2732
2734
2700
Handset & Dev App Update
Enter Security Password:
_ xxxxxx
Execute
Cancel
2702
2704
2706
2708
Handset & Dev App Update
Updating Handset software !
Update Device software !
Please wait !
Device update is complete.
Handset update is complete.
Done
Back
Cancel
2740
2742
2744
2746
2748
2750
2752

FIG. 27


2800
Vehicle Activation Menu
Enter Server web address:
www.DEF_act.com/veh/
Enter Activation User ID:
xxxxx
Enter Activation password:
xxxxx
Your handset number:
916-987-6543
Ok
Cancel
Save
2802
2804
2806
2808
2810
2812
2814
2820
2822
2824
2826
2828
2829
2830
2832
2834
2835
Vehicle Activation Menu
Dev is being activated !
Connecting to provider.
Activation password is ok.
Account number: XXXXX4433
Subscriber: Sol M. Li
Receiving UTAID from
service provider.
Ok
Cancel
Save
2836
2838
2840
2842
2844
2846
Auto Device Information
Auto Security Device Phone Numbers:
916-122-8888
Acc Name: Sol M. Li
SP_Newcarrier - Acc # 6780044433
2880
2882
2884
Inbox
2894
Please update
Dev identifcation
2890
2892
Vehicle Activation Menu
Activation is complete.
Activation is DONE.
Check Success icon if you have any
messages from the device in your
inbox. Please wait for 20 minutes or
longer to see if you inbox receives any
messages; verify your handset phone
number entry if it is correct; otherwise
contact your provider customer service
& check fail box..
Success
fail
2870
2872
2874
2876
2878
Vehicle Activation Menu
Device is being activated !
Connecting to the Dev.
Acknowledge from Dev.
Transmitting handset number.
Transmitting Acc Information.
Transmitting UTAID.
Activating Dev.
Waiting for Dev activation
completion.
Device received confirmation
from network.
Dev phone: 916-122-9876
Activation completed successfully.
Check your inbox.
2850
2852
2854
2856
2858
2860
2862
2864
2866
2868
2869

FIG. 28


Home Activation Menu
Dev is being activated !
Connecting to provider.
Activation password is ok.
Account number: XXXXX0044
Subscriber: Sol M. Li
Receiving UTAID from service provider.
Ok
Cancel
Save
2936
2938
2940
2942
2944
2946
Home Activation Menu
Enter Server web address: www.DEF_act.com/hom/
Enter Activation User ID: xxxxx
Enter Activation password: xxxxx
Your handset number: 916-987-6543
Ok
Cancel
Save
2932 2934
2935
2920
2922
2924
2926
2928
2929
2930
2900
Home Activation Menu
Device is being activated !
Connecting to the Dev.
Acknowledge from Dev.
Transmitting handset number.
Transmitting Acc. Information.
Transmitting UTAID.
Activating Dev.
Waiting for Dev activation completion.
Device received confirmation from network.
Dev phone: 916-122-9877
Activation completed successfully.
Check your inbox.
2950
2952
2954
2956
2958
2960
2962
2964
2966
2968
2969
Home Activation Menu
Activation is complete.
Activation is DONE.
Check Success icon if you have any messages from the device in your inbox. Please wait for 20 minutes or longer to see if you inbox receives any messages; verify your handset phone number entry if it is correct; otherwise contact your provider customer service & check fail box.
Success
Fail
2976
2978
2970
2972
2974
Home Activation Menu
Dev is being activated !
Connecting to provider.
Activation password is ok.
Account number: XXXXX0044
Subscriber: Sol M. Li
Receiving UTAID from service provider.
Ok
Cancel
Save
2902
2904
2906
2908
2910
2912
2914
Home Device Information
Home Security Device Phone Numbers:
916-666-1111
Acc Name: Sol M. Li
SP_Newcarrier - Acc # 6780090055
2980
2982
2984
Inbox
Please update Dev identification
2994
2992
2990

FIG. 29


106
Dev
112
Service Provider
102
Handset
3070
3072
3073
3074
3075
3076
3077
3078
3079
3080
3081
3000
3030
3032
Alarm OFF
Prk Breaks On
Auto Status
Doors Unlocked
Headlights On
Engine Off
3020
3022
3024
3026
3028
3062
Auto Control
3053
is OFF
3055
Are locked
3057
Sounding
3059
Engine OFF
3061
are OFF
Alarm
Doors
Horn
Ignition
Emergency Lights
3050
3052
3054
3056
3058
3060
3002
3004
3006
3008
3010
3012
3013
Auto Control and Monitor
Monitor
GPS
Route Tracking & Speedo-Alert
Speedo-alert Listing
Route Tracking Listing
Control
Status
Locator
3014
3016
3018
3036
3038
Auto Status
Alarm is ON
Doors are Locked
Engine Off
3040
3042
3046
3048
Arm
OFF

FIG. 30


3180
3182
GPS
102
Handset
106
Dev
3184
3186
3188
3190
3192
3194
3196
3198
3100
Auto GPS
Destination Retrieval
Destination Entry
Recent Entries
3102
3104
3106
3108
3110
Auto GPS Entry
City:
State:
Street & Address:
Map Address Drop in
(Drag & drop found address box here)
3120
3122
3124
3126
3128
3130
3132
3140
3142
3144
3146
3148
3150
Auto GPS Entry
City: Jacksonv
State: x
Street & Address: x
Jacksonville
Alabama
Arkansas
Florida
Illinois
North Carolina
New York
Oregon
Texas
Save
Cancel
3152
3154
3156
3160
3162
3164
3166
3168
Auto GPS Entry
City: Jacksonville
State: Arkansas
Street & Address: 1109 West Av.
Save
Cancel
3170
3172

FIG. 31

FIG. 32


3200
3202
3204
12811 Lantana Ave. Saratoga, CA.
12811 Lantana Ave, San Jose, CA 95130 - Zillow
www.zillow.com/homedetails/12811-Lantana-Ave-San-Jose-CA-95130/...
Not for Sale · 2554 sq ft · 4 bed/2 ba · 9954 sq ft lot
It is located at 12811 LANTANA AVE SAN JOSE, California. Cooling Unknown; Parking Unknown; Parking
Unknown; Basement Type Unknown; ... 12843 Lantana Ave Saratoga, Saratoga, CA $986K 4 ...
Lantana Avenue Saratoga, CA home and property info
www.trulia.com › ... › California homes › Saratoga homes › 95070 homes
12811 Lantana Avenue, Saratoga CA This 4 bedroom, 2 bathroom home has 2554 square feet and was built in 2452. 12763 Lantana Avenue, Saratoga CA
Map of 12811 Lantana Ave, Saratoga, CA 95070
bing.com/maps
View large map · Drive to · Drive from
Get directions from
Buckmall Rd
Arleen Way
Tamie Ln
Baylor Ave
Pinedale Dr
Norwich Way
Madox Wa
Chesley Dr
Tilbury D
Jordan Dr
Grimsby Dr
UCKNALL
SUNNYVALE PARK
3206
3208
3210
3120
3122
3124
3126
3128
3130
3240
3242
3244
3246
3248
3250
3252
Auto GPS Entry
City:
State:
Street & Address:
Map Address Drop in
(Drag & drop found address box here)
3132
Auto GPS Entry
City:
Saratoga
State:
California
Street & Address:
12811 Lantana Ave.
Google Map Address Drop in
(Drag & drop found address box here)
Save
Cancel


Toll Fee Pay Account
Account Activities
Account Pay Setup
Account Pay Cancel
On Demand Toll Pay Acc. Setup
3310
3312
3314
3300
Account Pay Setup
Executing ! Please wait !
Your Bank Name:
_ Chase
Bank Account Number:
_ 0222288888
Account Type:
visa ☒ mc ☐ ax ☐ check ☐
Acc Name & Address:
Sol M. Li
110 3rd Av. EK, CA. 95699
Time of Payment
as demanded
Name of Payee Party / Institution:
Bay Bridge Toll Company
@baybridgetoll.com
Save
Cancel
Exe
3328
3330
3332
3334
3336
3338
3340
3342
3343
3344
3346
3348
Account Pay Activities
Bay Bridge Toll Company
Jan 2013
13/01/01 06:56 ..... $6.00
13/01/01 16:05 ..... $5.00
13/01/02 06:30 ..... $6.00
13/01/02 15:59 ..... $5.00
...
Total ..... $231
Feb 2013
13/02/15 06:14 ..... $6.00
13/02/15 16:11 ..... $5.00
...
Total ..... $242
3380
3382
3384
3386
3388
3390
3392
Account Pay Setup
IP address of Payee Party/Institution:
_ baybridgetoll.com/payacc/setup
Exe
3320
3322
3324
3326
3328
Account Pay Setup
Completed !
Account Payment:
Payee's Name:
Bay bridge Toll Company (9753296)
Amount:
As charged ($5.00-$10.00)
Time of Payment:
As demanded
Payment Code
56781234
Payer Code
67890
Payer's Name:
Sol M. Li
Account Number:
xxxxxx-8888
Account Type
Visa
Email: owner@myacc.com
110 3rd Av. EK, CA. 95699
Ok
3350
3352
3354
3356
3358
3360
3362
3364
3366
3368
3370
3372

FIG. 33

FIG. 34




Toll Collector
3402
Dev
106
Service Provider
112
3501A
3502
3504
3501B
3506
3508
3510
3501C
3512
Store the Payment Amount with Time & Date
3501D
118
104
3500

FIG. 35


Dev:
Receive Toll Collect Payment with Company Name Code "9753296" from the Toll Collector
3602
3370
Dev:
Verify that it is correct in the pay account & send back Payer's Code"67890" to the Toll Collector
3604
3364
Dev:
Receive Payment Code "56781234" from the Toll Collector
3606
3362
Dev:
Verify that it is correct & send back Payer's Name, Account Type & Account Number to the Toll Collector
3608
Dev:
Receive Amount of Payment Charge from the Toll Collector
3610
Dev:
Store the Payment Amount with Time & Date
3612
3600

FIG. 36


On Demand Toll Pay
Account Setup
3702
3704
Your Bank Name:
_ x
3706
3708
Bank Account Number:
_ x
3710
Account Type:
visa ☐ mc ☐ ax ☐ cash ☐
3712
Account Name & Address:
–
3714
Voice Activate Output at pay time
"yes" response to pay: ☐
Pay automatically: ☒
3716
3718
3720
On Demand Toll Pay
Account Setup
3722
Your Bank Name:
_ Chase
3724
Bank Account Number:
_ 0222288888
3726
Account Type:
visa ☒ mc ☐ ax ☐ cash ☐
3728
Account Name & Address:
Sol M. Li
110 3rd Av. EK, CA. 95699
3730
3732
Voice Activate Output at pay time
"Yes" response to pay: ☒
Pay automatically: ☐
3733
Save
Cancel
Exe
3734
3736
3738
3740
On Demand Toll Pay
Executing ! Please wait !
3742
Toll Payment as Demand
Account : 0222288888
Type: VISA
Bank: Chase
Pay as Demanded
Activate by Voice "Yes"
3744
Account Name: Sol M. Li
Addr: 110 3rd Av. EK, CA. 95699
Done
Cancel
3746
3748


3750
3752
Driver
106
Dev
3402
Toll Collector
Verify car has been in motion in a good amount of time
3753
3754
3756
"Yes"
3758
3760
3762
3764
3766
Store transaction in memory


3770
3774
Dev:
Receive toll payment from a toll collector
3776
Dev:
Output audio message on toll payment, the amount and the toll collector's name
3778
Dev:
Receive "yes" audio input from the driver
3780
Dev:
Send encrypted acc. number, Name & address to the toll collector
3782
Dev:
Receive payment ack. from the toll collector
3784
Dev:
Output an audio message on the transaction completion to the driver
3786
Dev:
Store payment, toll collector's name, time & date in memory

FIG. 37

3700


Vehicle Locator
3802
3804
Verify your Security Password:
_ xxxxxx
3806
Execute
3808
Cancel
3810
3820
Vehicle Locator
Location:
2200 Warburton Ave
Santa Sara, CA.
3822
map
3824
3800

FIG. 38


3850
3852
3830
3832
3834
Vehicle Locator
Dev:
Receive Vehicle Locator command & matched PW from Handset
3854
Dev:
Send current location query command to GPS
3856
Dev:
Receive current location & map graphic from GPS
3858
Dev:
Send current location & map graphic to Handset


Handset Locator
3902
3904
Verify your Security Password:
_ xxxxxx
Pick one of these handset numbers:
916-987-6543
916-987-6500
408-234-5678
3906
3908
3910
3912
Execute
3914
Cancel
3916
3918
3920
Handset Locator
3922
Please wait! Searching for Handset 916-987-6500.
3924
Found!
3926
Location:
2200 Warburton Ave
Santa Sara, CA.
map
3928
3900

FIG. 39


3930
3932
3934
Handset Locator


3950
3952
Dev:
Receive & process Handset Locator command & matched security password from the inquiry Handset
3954
Dev:
Send the phone numbers of its registered handsets to the inquiry Handset
3956
Dev:
Send the current location query command to the missing Handset (916-987-6500)
3958
Dev:
Receive the current GPS location & map graphic from the missing Handset (916-987-6500)
3960
Dev:
Send current location & map graphic to the inquiry Handset

FIG. 40


4000
Route Tracking Listing
License Plate: CA-QFA955
Make: Ford 2011 White Campri
Date: 06/01/13
13:25 Speed: 35 mph
Block 2300 El Camino, Sunnyvale, CA.
13:30 speed: 28 mph
Block 2500 El Camino, Sunnyvale, CA.
13:35 speed: 29 mph
Block 2800 El Camino, Santa Clara, CA.
13:40 speed: 2 mph
Block 1000 Lawrence Exp, Santa Clara, CA.
Speedo-Alert Listing
License Plate: CA-QFA955
Make: Ford 2011 White Campri
75 Mph 13:25 – 13:32 04/03/13
Block 2300 El Camino, Sunnyvale, CA.
78 Mph 15:09 – 15:18 04/03/13
Block 8000 El Camino, Santa Clara, CA.
3182
GPS
4074
Speedo-meter
106
Dev
102
Handset
4072
Storage Server
4070
4070a
4051
4053
4055
4057
4059
4065
4067
4069
4071
4060
4062
4064
4066
4068
4061
4063
4076
4078
4080
4082
4084
4086
4088
4090
4092
4094
4096
4098


Route Tracking and Speedo-Alert Program & Setup
Maximum speed alert at Mph (Kph):
Network Storage Server destination:
Alert or not:
Yes
No
Turn the Speedo-Alert:
On
Off
Route Tracking is completely off
Tracking is On every 5 minutes
Cancel
Exe
4002
4004
4006
4008
4010
4012
4016
4018
4020
4021
4022
4023
4024
4026
4028
4032
4034
4036
4038
4040
4042
4044
4046
4048
4050
4051
4052
4053
4054
4056
4058


Tools
Calendar
Task
Security Auto
Security Home
xxx
4114A
4116A
4166A
Auto Alarm System Alert
4162A
4164A
Auto Alarm System Alert
4136A
4138A
4140A
4142A
4144A
Inbox
Alert from your
Auto Alarm System !
4110A
Break in
Date: 12/4/2012
Time: 09:34:12 AM
Location:
13311 Lantana Av Sara CA.
Car in Motion: No
Sources Alerted:
916-567-1234
808-123-4567
510-123-9876
Street Map . . .
4130A
4132A
4134A
4100A
New Text Message in your inbox
4102A
Auto Security
Alert !
4122A
4124A

FIG. 41A

FIG. 41B


4100B
New Text Message in your inbox
4104B
4110B
Inbox
4102B
Urgent!
Your Child might be in your car !
4112B
4114B
Video 0
Video 1
4116B
4118B
Confirm
Ignore
4120B
4130B
Please take these actions !
4132B
Unlock the car doors
4134B
Lower down car windows
4136B
Sound the horn
4138B
Turn on the car alarm
4140B
Turn the heater on
4142B
Turn the A/C on
4144B
Flash a light
4146B
Call Emergency
4148B
I am on my way
4150B
Actions being taken:
4152B
Unlock the car doors
4154B
Lower down car windows
4156B
Sound the horn
4158B
Turn on the car alarm
4160B
Turn the heater on
4162B
Turn the A/C on
4164B
Flash a light
4166B
Call Emergency
4168B
I am on my way
4180B
4190B


4202
Auto App Menu
4204
Auto Dev Facilities
4206
Control & Monitor
4208
Engine Status
4210
Toll Fee Pay Acc.
4212
Panic
4214
Lock/ Unlock
4212
4220
Engine Status Menu
4222
Fuel Level
4224
Tire Condition
4232
Electrical
4226
Last Service
4234
Oil Level
4228
Breaks
4236
Others
4230
Lights
4238

FIG. 42

4200


Home Alarm System Configuration
Door/window Entries
Entry 1
Enter new name:
_Main
Prev
Save
Next
Done
Cancel
4340
4342
4344
4346
4348
4350
4352
4354
Motion Inputs
Hall
LR
Back
Side
Loud Speakers/Horns
SPK 1
SPK 1
11
12
Cameras
Front
Back
Gara
Back Yard
Side
Patio
Rear
MB
Save
Exe
Cancel
4380
4382
4384
4386
4388
4390
4300
Home Alarm System Configuration
Door/window Entries
Main
Side
MB
BR1
Kitch
BR2
LR
Rear
Motion Inputs
Hall
LR
Back
Side
Loud Speakers/Horns
SPK 1
SPK 2
11
12
Cameras
1
2
3
4
4320
4322
4324
4326
4328
4330
4332
4334
4360
4362
4370
4372
4374
4376
4378
Home Control and Monitor
Status/ Monitor
Alarm Configure
Program/ Control
4302
4304
4306
4308
4310

FIG. 43


Home Security Status/Monitor
Door/window Entries
Main
Side
Kitch
LR
MB
BR1
BR2
Rear
Motion Inputs
Hall
LR
Back
Side
Cameras
Front
Kitch
Side
Rear
Back Yard
Gara
Patio
MB
4420
4422
4424
4402
4404
4406
4408
4410


Home Security Status/Monitor
Door/window Entries
Main
Side
Kitch
LR
MB
BR1
BR2
Rear
Motion Inputs
Hall
LR
Back
Side
Cameras
Front
Kitch
Side
Rear
Back Yard
Gara
Patio
MB
4430
4432
4408
4434


Home Security Status/Monitor
Camera – Back Yard
4470
4472
4474
4400

FIG. 44


Home Security Status/Monitor
Door/window Entries
Main
Side
Kitch
LR
MB
BR1
BR2
Rear
Motion Inputs
Hall
LR
Cameras
Front
Kitch
Side
Rear
Back Yard
Gara
Patio
MB
4450
4452
4410
4454
4456


Home Security Status/Monitor
Door/window Entries
Main
Side
Kitch
LR
MB
BR1
BR2
Rear
Motion Inputs
Hall
LR
Back
Side
Cameras
Front
Kitch
Side
Rear
Back Yard
Gara
Patio
MB
4402
4404
4406
4408
4410


Home Security Status/Monitor
Door/window Entries
Main
Side
Kitch
LR
MB
BR1
BR2
Rear
Motion Input
Hall
LR
Cameras
Front
Kitch
Side
Rear
Back Yard
Gara
Patio
MB
4440
4442
4444
4410
4446

FIG. 45


4500
4548
4550
4552
4554
4556
4558
4559
Alarm is OFF
Alarm is not Ready
Master Bedroom ..... opened
Panic
bypass
Configure
Program
KeyBoard
OFF
KeyPad
Camera Motion Alert
Disp Monitor Status
Activate Alarm " Stay "
Activate Alarm " Away "
Camera Motion Sound
Test
1 — 2 abc 3 def
4 ghi 5 jkl 6 mno
7 pqrs 8 tuv 9 wxyz
* — 0 ++ # .....
4544
4546
4580
4582
4582
Alarm is ON
Away (nobody's home)
Camera Motion is On (alert)
4560
4562
4564
4566
4568
4570
4572
4530
4532
4534
4536
4538
4540
4542
4502
4504
4506
4508
Alarm is OFF
Alarm is not Ready
Keypad
Keyboard
4536
Bypass
Main Entrance .....
Garage Entrance .....
Bedroom1 .....
Bedroom2 .....
Master Bedroom .....
Rear Entrance .....
Side Entrance .....
4574
4576


Alert !
4622
4624
Tools
Calendar
Task
Security Auto
Security Home
xxx
4612
4614
Inbox
Alert from your
Home Alarm System !
4602
4606
New Text Message in
your inbox


Alarm System Alert
Alarm Activated
Spk 1 & Spk 2
Time: 13:13
Date:2013/3/09
Sources Alerted:
916-567-1234
808-123-4567
530-123-9876
owner@myacc.com
2ndowner@acc.com
SPK 1
SPK 2
11
12
4660
4662
4664
4666
4668
4670
4672
4600
Point of Entry
Bedroom 2
Time: 13:09
Date: 2013/3/09
Alarm Sy
Door/window
Motion Inputs
Loud Speake
Kitch
LR
Rear
Side
Back
Front
BR 1
BR2
MB
Hall
4652
4654
4656
Alarm System Alert
Door/window Entries
Motion Inputs
Loud Speakers/Horns
4632
4634
4636
4638
4640
4642

FIG. 46


4710
4720
Inbox
N ew Text M essage in your inbox
4712
Alert from your H om e Alarm System !
4722
4724
4700

FIG . 47


4730
4740
4744
4742
10:23AM
10:24AM
4732


Home Appliances
Appliance Add
Appliance Remove
App Download
4802
4804
4808
4806
4809
Home Appliances Discovery
# 1. Door Lock DoorRUS A370
# 2. HelpAlert AlertOne B702
# 3. Heating & Air American Standard AH98
# 4. Cable Box GenCable 4302
# 5. Garage Opener LiftDoor 309
# 6. Lawn Sprinkler Toro -356
# 7. Electric Meter UtilMeter - 123
# 8. D. Bell & Intercom Bell&Intercom - 2277
Ignore conn
Ignore Conn
4810
4812
4814
4816
4818
4820
4822
4824
4826
4827
Home Appliances Connecting !
Exe
Cancel
4828
4829
4830
4832
4834
4836
4838
4840
4842
4844
4846
4847
4848 - 4849
Home Appliances
Appliance Add
Appliance Remove
Help Alert
Cable Box / TV
Sprinker
Electric Meter
App Download
Door Bell & Intercom
Door Lock
Heat/AC
Garage Opener
Door Bell & Intercom
4851
4853
4855
4857
4859
4861
4863
4865
4867
4869
4871
4873
4875
Door Lock
Help Alert
Heat/ AC
Cable Box/TV
Garage Opener
Sprin-kler
Electric Meter
Door Bell & Intercom
4872
4874
4876
4878
4880
4882
4884
4886
4885
4885A
4887
4887A
4889
4889A
4891
4891A
4893
4893A
4895
4895A
4897
4897A
4800
FIG. 48
Hand -set
Dev
102
106
4881
4883
4883A
4883B
4885B
4887B
4889B
4891B
4893B
4895B
4897B
DA
HA
AA
CA
GA
SA
EA
BA
4854
4856
4858
4860
4862
4864
4866
4868
4868a
4870
4850
4852
Control
Done
Home Appliances Connecting !
# 1. Door Lock DoorRUS A370
# 2. HelpAlert AlertOne B702
# 3. Heating & Air American Standard AH98
# 4. Cable Box GenCable 4302
# 5. Garage Opener LiftDoor 309
# 6. Lawn Sprinkler Toro -356
# 7. Electric Meter UtilMeter - 123
# 8. D. Bell & Intercom Bell&Intercom - 2277


4902
4886
4872
4874
4885
4876
4897
4884
4883
4887
4878
4895
4889
Dev
106
4893
4980
4891
4982
4984
4882
6190
6192
4882
118
6194
4880
110
4900
102

FIG. 49


Door Bell & Intercom
4886
Electric Meter
4884
Sprin-kler
4882
Garage Opener
4880
Cable Box/TV
4878
Heat/ AC
4876
Help Alert
4874
Door Lock
4872
5000
FIG. 50
Home Appliances
Appliance Add
Appliance Remove
App Dowload
5006
5009
New Appliances Found
# 1. Door Lock
IP Addr: 192.168.1.8
# 2. HelpAlert
IP Addr: 192.168.1.20
# 3. Heating & Air
IP Addr: 192.168.1.23
# 4. Cable Box
IP Addr: 192.168.1.26
# 5. Garage Opener
IP Addr: 192.168.1.29
# 6. Lawn Sprinkler
IP Addr: 192.168.1.41
# 7. Electric Meter
IP Addr: 192.168.1.100
# 8. D. Bell & Intercom
IP Addr: 192.168.1.102
Ignore conn
Ignore Conn
5010
5012
5014
5016
5018
5020
5022
5024
5026
5027
Home Appliances
Appliance Add
Appliance Remove
App Download
Help Alert
Cable Box / TV
Sprinker
Electric Meter
App Download
Door Lock
Heat/AC
Garage Opener
Door Bell & Intercom
Exe
Cancel
5057
5061
5065
5069
5071
5075
5051
5053
5055
5059
5063
5067
5073
5030
5032
5034
5036
5038
5040
5042
5044
5046
5047
5049
5048
5028
5029
5002
5004
5008
5009
Hand -set
Dev
102
106
5081
5083
5083A
5085
5085A
5087
5087A
5089
5089A
5091
5091A
5093
5093A
5095
5095A
5097
5097A
DA
HA
AA
CA
GA
SA
EA
BA
5083B
5085B
5087B
5089B
5091B
5093B
5095B
5097B
5070
5050
5052
5054
5056
5058
5060
5062
5064
5066
5068
5068a
Control
Done
Home Appliances Connecting !
# 1. Door Lock
IP Addr: 192.168.1.8
# 2. HelpAlert
IP Addr: 192.168.1.20
# 3. Heating & Air
IP Addr: 192.168.1.23
# 4. Cable Box
IP Addr: 192.168.1.26
# 5. Garage Opener
IP Addr: 192.168.1.29
# 6. Lawn Sprinkler
IP Addr: 192.168.1.41
# 7. Electric Meter
IP Addr: 192.168.1.100
# 8. D Bell & Intercom
IP Addr: 192.168.1.102


5102
4886
5097
5104
5083
4872
5095
4874
5085
4884
5106
5087
72°
OFF
ON
Prg
Heat
Air
4876
5089
Dev
4878
5093
106
5091
5180
5182
5184
4882
118
5082
6190
6192
6194
4880
110
5100
102

FIG. 51


5200
Home Device Removal
# 1. Door Lock A370 Remove
# 2. HelpAlert 111 Remove
# 3. American Std AH98 Remove
# 4. GenCable 4502 Remove
# 5. LiftDoor Remove
# 6. Toro – 356 Remove
# 7. Utilmeter – 123 Remove
# 8. Bell&Intercom – 2277 Remove
Exe
Cancel
5202
5204
5206
5208
5210
5212
5214
5216
5218
5220
5222
5224
Home Devices
# 1. Door Lock A370 IP Addr: 192.168.1.8
# 2. HelpAlert 111 IP Addr: 192.168.1.20
# 3. American Std AH98 IP Addr: 192.168.1.23
# 4. GenCable 4502 IP Addr: 192.168.1.26
# 5. LiftDoor 309 IP Addr: 192.168.1.29
# 6. Utilmeter – 1237 IP Addr: 192.168.1.100
# 7. Bell&Intercom – 2277 IP Addr: 192.168.1.102
5260
5262
5264
5266
5268
5270
5272
5274
5276
Home Appliances Menu
Appliance Add
Appliance Remove
Door Lock
Help Alert
Heat/AC
Cable Box / TV
Garage Opener
Sprinker
Door Bell & Intercom
Electric Meter
App Download
5051
5053
5055
5057
5059
5061
5063
5065
5067
5069
5071
5073
5075
Home Device Removal
# 1. Door Lock A370 Remove
# 2. HelpAlert 111 Remove
# 3. American Std AH98 Remove
# 4. GenCable 4502 Remove
# 5. LiftDoor 309 Remove
# 6. Toro – 356 Remove
# 7. Utilmeter – 123 Remove
# 8. Bell&Intercom – 2277 Remove
Exe
Cancel
5230
5232
5234
5236
5238
5240
5242
5244
5246
5248
5250
5252
Home Appliances Menu
Appliance Add
Appliance Remove
Door Lock
Help Alert
Heat/AC
Cable Box / TV
Garage Opener
Sprinker
Door Bell & Intercom
Electric Meter
App Download
5280
5282
5284
5286
5288
5290
5292
5294
5296
5297
5298
5299

FIG. 52


5302
4872
4874
72°
OFF
ON
Prg
Heat
Air
4876
5306
4886
4885
5318
4883
5304
5308
4878
4887
4889
4897
106
Dev
5303
4895
5310
5316
102
4884
4893
5314
5330
5332
4891
5312
4882
6190
6192
5334
4880
6194
5300

FIG. 53


5402
4872
4874
72°
4876
5304
5306
5308
4878
106
Dev
4886
5303
5318
4884
5310
5316
102
5312
5314
5330
5332
5334
4882
6190
6192
6194
4880

FIG. 54 5400




FIG. 55A




FIG. 55B




FIG. 55C




FIG. 55D




FIG. 56A




FIG. 56B







Tuesday Feb 12 2013
12:53 PM
Start Time: 8:00 AM Run Time: 60 min
On
Off
Clock Set
How Often
Rain Delay
Enter
Date Set
Run Time
Manual
Clear
Prog
Start Time
Auto
Station
OK
1 2 3
4 5 6
7 8 9
AM 0 PM
5730
5732
5734
5736
5738
5740
Tuesday Feb 12 2013
12:57 PM
Stations: 1 2 3 4 5 6 7 8
5772
5770
5774
FIG. 57
5700
5702
5704
5706
5708
Tuesday Feb 12 2013
12:52 PM
5710
5712
Tuesday Feb 12 2013
12:56 PM
Mo Tu Wd Th Fr Sa Su
5752
5750
5754


Account Application Setup
Account Name:
Sol Li
Account Address:
12833 Lantana Av.
Sara, CA. 95070
Handset Phone Number:
916-987-6543
Utility's web address:
www.pg&e.com/myacc/setup/xxxx
Exe
5834a
5836a
5820a
5822a
5824a
5826a
5828a
5830a
5832a
Electric Meter Reading
Meter S/N:
Account Name:
Sol Li
Account Address:
12833 Lantana Av.
Sara, CA. 95070
Account Number
444-3456789
Meter reading
76113449
39680 kWh
5876
5870
5872
5874
5800
Account Application Setup
Account Name:
Account Address:
Handset Phone Number:
Utility's web address:
Exe
5834
5836
5820
5822
5824
5826
5828
5830
5832
Account Payment Setup
PG&E Co.
1111 5th Av. SF, CA. 9xxxx
Account Number: 444-3456789
Meter S/N: 76113449
www.pg&e.com/myacc/payment/6789
Customer's Name & Address:
Sol Li
12833 Lantana Av.
Sara, CA. 95070
Handset number:
916-987-6543
Customer's Bank Name: Chase
222 6th Av. NY City, NY 10007
Payer's Bank Account Number:
0222288887
Account Type:
Visa MC AM Check Pay
Auto
The information is on file
All information protected by
secure payment transaction
Exe
Cancel
5863a
5864
5866
5840a
5842a
5844a
5846a
5848a
5850a
5852a
5854a
5856a
5858a
5860a
5862a
Electric Meter Menu
Meter Reading
Account Payment
Account Setup
Pay online
Monthly Usage Inf.
5802
5804
5810
5812
5814
5806
5808
Account Payment Setup
PG&E Co.
1111 5th Av. SF, CA. 9xxxx
Account Number: 444-3456789
Meter S/N: 76113449
www.pg&e.com/myacc/payment/6789
Customer's Name & Address:
Sol M. Li
12833 Lantana Av.
Sara, CA. 95070
Handset number: 916-987-6543
Customer's Bank Name & Address:
-
Payer's Bank Account Number:
-
Account Type:
Visa MC AM Check Auto Pay
Information on Record
All information protected by
secure payment transaction
5840
5842
5844
5846
5848
5850
5852
5854
5856
5858
5860
5862
5863

FIG. 58


Account Payment Info
PG&E Co.
1111 5th Av. SF, CA. 9xxxx
Account Number
444-3456789
Sol Li
12833 Lantana Av.
Sara, CA. 95070
Handset number:
916-987-6543
Customer's Bank Name: Chase
Bank Account Number: XXXXXX8887
Account Type: Visa
Amount: $99.00
May 1st, 2013
Exe
Cancel
5968
5969
5900
FIG. 59
5954
5956
5958
5960
5962
5964
5966
PG & E
Your electricity bill
Pay online
Cancel
Sol Li
Account Number
XXX-XXX6789
12833 Lantana Av.
Sara, CA. 95070
5930
Payment received Apr 1st, 2013
Thank you
Electricity Usage ..... 760 kWh
New balance ..... $99.00
As of May 1st, 2013
Payment Account ..... xxxxxx8003
Pay Information on file ...
Edit
All information protected by secure payment transaction
5946
5948
5950
5922
5924
5926
5928
5932
5934
5936
5938
5940
5942
5944
Electric Meter Monthly Reading
Date: May 1st, 2013
Meter S/N: .... 76113449
Account Name:
Sol Li
Account Address:
12833 Lantana Av.
Sara, CA. 95070
Account Number
444-3456789
Meter previous reading ..... 39680 kWh
Meter current reading ..... 40340 kWh
5902
5904
5906
5908
5910
5912
5914
5916
5918
5920
102
Handset
5982
Utility Co.
106
Dev
4884
E. Meter
5984
5985
5986
5987
5992
5993
5994
5995
5991
5988
5990
5980
5980A
5970
5972
5974
5976
Inbox
Your June 2013 electricity bill has been processed and paid in full.




6000A

FIG. 60A




6000B

FIG. 60B


Smart Pet Door Control
6102
6104
Program & Setup
Command
6106
6108
6100
Smart Pet Program & Setup
6112
6114
Add schedule
Record
6116
Delete schedule
Playback
6126
6118
6128
# 1
08:00 AM Out
08:20 AM In
6120
6122
# 2
12:00 PM Out
12:20 PM In
6124
# 3
04:00 PM Out
04:20 PM In
6132
Exec
6130
Smart Pet Command
6140
6142
Open/Open Door
Door closed
6144
6145
Call Pets
6146
Playback Audio
Audio Off
6148
6147
Record Audio
Audio Recording
6150
6149
Record Video
Camera Off
6152
6149
Playback Video
6154
6160
102
106
6190
6192
6194
Handset
Dev
Pet Door
Speaker
Camera
6162
6164
6166
6168
6170
6172
6174
6176
6178
6180
6182
6161

FIG. 61




FIG. 62

Provision Computer/Server

120

112

Cellular Service Provider
(CSP)
or "Service Provider"

114

116

Email Server

110

Base Transceiver Station
(BTS) or The Tower

118

Wireless Network

108

Dev Application Storage
Server
or "App Server"

102

104

106

PC/Tablet/Smart
Phone
/Handset
or "Handset"

BT/Wireless
USB/NFC/
infrared/wireless
LAN - SRC
(Short Range
Communication)

Program Control &
Monitor Device
(PCMD)
or "Dev"

124

Robotic
Device

100

120



122

FIG. 1