

october 2020



noForth website

## How to get noForth in the Seeed Studio GD32VF (Windows)

### What's needed?

- Seeed Studio GD32VF dev board
- Flash programmer (GD32 MCU Dfu Tool\_v3.8.1.5784)
- USB-C cable

### What to do?

1. Connect the board with the USB-C cable
2. Start GD32 MCU Dfu Tool
3. Replace the BOOT0 jumper to 3V3, then press the reset key
4. Mark **Erase all & verify** in the DFU Tool window
5. Click **open** in the "Download APP program file" section
  - Select **BIN files**
  - Select the chosen noForth binary and click "open"
  - Click the **OK button**
  - Now wait until the upload status reaches 100%
6. Replace the BOOT0 jumper to GND
7. Press RESET on the board and noForth will run

